

Citrix Provisioning 1811

MCLI Programmer's Guide

Revision 1
November 2018

Copyright and Trademark Notice

Information in this document is subject to change without notice. Companies, names, and data used in examples herein are fictitious unless otherwise noted. Other than printing one copy for personal use, no part of this document may be reproduced or transmitted in any form or by any means, electronic or mechanical, for any purpose, without the express written permission of Citrix Systems, Inc.

Copyright 2001—2018 Citrix Systems, Inc. All rights reserved.

Citrix, ICA (Independent Computing Architecture), NetScaler, and Program Neighborhood are registered trademarks; Citrix Presentation Server, Citrix Access Essentials, Citrix Access Gateway, Citrix Password Manager, Citrix Application Firewall, Citrix Application Gateway, Citrix Provisioning Services, Citrix Streaming Profiler, Citrix Streaming Client, Citrix Streaming Service, Citrix EdgeSight, Citrix WANScaler, Citrix SmoothRoaming, Citrix Authorized Learning Center, Citrix Subscription Advantage, Citrix Technical Support, and Speed Screen are trademarks of Citrix Systems, Inc. in the United States and other countries.

Copyright RSA Encryption 1996—1998 RSA Security Inc. All rights reserved.

Contents

Short command list	11
MCLI Add.....	11
MCLI Delete	11
MCLI Get	11
MCLI Info	12
MCLI Run.....	12
MCLI RunWithReturn.....	13
MCLI Set.....	14
MCLI SetList.....	14
Commands by Object Type	15
Many.....	15
AuthGroup	15
Collection.....	15
Device	15
Disk.....	16
DiskLocator	17
Farm	17
FarmView.....	17
Server.....	17
Site.....	18
SiteView.....	18
Store	18
System	18
Task.....	18
UpdateTask.....	19
VirtualHostingPool.....	19
CeipData.....	19
CisData	19
Error codes.....	19
MCLI Add.....	30
MCLI Add AuthGroup	30
MCLI Add CeipData.....	30
MCLI Add CisData	30

MCLI Add Collection	31
MCLI Add Device	31
MCLI Add DeviceWithPersonalvDisk	33
MCLI Add DiskLocator	35
MCLI Add DiskUpdateDevice	36
MCLI Add FarmView	37
MCLI Add Server	37
MCLI Add Site	39
MCLI Add SiteView	39
MCLI Add Store	40
MCLI Add UpdateTask	40
MCLI Add VirtualHostingPool	41
MCLI Delete	42
MCLI Delete AuthGroup	42
MCLI Delete Collection	43
MCLI Delete Device	43
MCLI Delete DeviceDiskCacheFile	43
MCLI Delete DiskLocator	44
MCLI Delete DiskUpdateDevice	44
MCLI Delete DiskVersion	44
MCLI Delete FarmView	45
MCLI Delete Server	45
MCLI Delete ServerStore	45
MCLI Delete Site	45
MCLI Delete SiteView	45
MCLI Delete Store	45
MCLI Delete UpdateTask	46
MCLI Delete VirtualHostingPool	46
MCLI Get	46
MCLI Get AdDomains	46
MCLI Get AuditActionParameters	46
MCLI Get AuditActionProperties	46
MCLI Get AuditActionSibling	47
MCLI Get AuditTrail	47

MCLI Get AuthGroup	52
MCLI Get AuthGroupUsage	52
MCLI Get CeipData.....	53
MCLI Get CisData	53
MCLI Get Collection.....	53
MCLI Get CommandDescription.....	55
MCLI Get CommandFields	55
MCLI Get CommandParameters	55
MCLI Get CommandSortFields.....	56
MCLI Get CommandStandardParameters.....	56
MCLI Get Device	56
MCLI Get DeviceBootstraps.....	60
MCLI Get DeviceCustomProperty	60
MCLI Get DeviceDiskPrinters	60
MCLI Get DeviceDiskTempVersion	61
MCLI Get DeviceInfo	62
MCLI Get DevicePersonality	67
MCLI Get DeviceStatus.....	67
MCLI Get Disk.....	68
MCLI Get DiskInfo.....	70
MCLI Get DiskInventory	73
MCLI Get DiskLocator	74
MCLI Get DiskLocatorCustomProperty	76
MCLI Get DiskLocatorLock.....	77
MCLI Get DiskPrinters.....	77
MCLI Get DiskUpdateDevice	78
MCLI Get DiskUpdateStatus	81
MCLI Get DiskVersion	82
MCLI Get ExceptionDescriptions.....	84
MCLI Get Farm	84
MCLI Get FarmView	85
MCLI Get Groups	86
MCLI Get NewVersionDisks	86
MCLI Get Server.....	86

MCLI Get ServerBiosBootstrap.....	90
MCLI Get ServerBootstrap	91
MCLI Get ServerBootstrapNames.....	92
MCLI Get ServerCustomProperty.....	92
MCLI Get ServerInfo.....	93
MCLI Get ServerStatus	96
MCLI Get ServerStore	97
MCLI Get Site	97
MCLI Get SiteView.....	98
MCLI Get Store.....	99
MCLI Get StoreSharedOrServerPath	100
MCLI Get Task.....	100
MCLI Get UndefinedDisks	101
MCLI Get UpdateTask.....	102
MCLI Get VirtualHostingPool	103
MCLI Get XDSite	105
MCLI Info	105
MCLI Info Group	105
MCLI Info LocalServer.....	105
MCLI Info MapiErrorCode	105
MCLI Info Version.....	106
MCLI Run.....	106
MCLI Run ActivateDevice	106
MCLI Run AddDeviceToDomain.....	107
MCLI Run AddDiskVersion	107
MCLI Run ApplyAutoUpdate	108
MCLI Run ArchiveAuditTrail	108
MCLI Run AssignAuthGroup	108
MCLI Run AssignDevice	109
MCLI Run AssignDisk.....	109
MCLI Run AssignDiskLocator	110
MCLI Run AssignServer.....	110
MCLI Run Boot	110
MCLI Run CancelTask	111

MCLI Run ClearTask	111
MCLI Run CopyPasteDevice	111
MCLI Run CopyPasteDisk	112
MCLI Run CopyPasteServer	112
MCLI Run CreateDirectory	112
MCLI Run CreateDiskCancel	112
MCLI Run DisableCollection	113
MCLI Run DisableDevice	113
MCLI Run DisableDeviceDiskLocator	113
MCLI Run DisableDiskLocator	114
MCLI Run DiskUpdateCancel	114
MCLI Run DiskUpdateStart	114
MCLI Run DisplayMessage	115
MCLI Run EnableCollection	115
MCLI Run EnableDevice	115
MCLI Run EnableDeviceDiskLocator	116
MCLI Run EnableDiskLocator	116
MCLI Run ExportDisk	116
MCLI Run ExportOemLicenses	117
MCLI Run ForceInventory	117
MCLI Run ImportDatabase	117
MCLI Run ImportDevices	118
MCLI Run ImportOemLicenses	118
MCLI Run MarkDown	119
MCLI Run MergeDisk	119
MCLI Run PromoteDiskVersion	120
MCLI Run Reboot	120
MCLI Run RemoveAuthGroup	121
MCLI Run RemoveDevice	121
MCLI Run RemoveDeviceFromDomain	122
MCLI Run RemoveDirectory	122
MCLI Run RemoveDisk	123
MCLI Run RemoveDiskLocator	123
MCLI Run ResetDatabaseConnection	123

MCLI Run ResetDeviceForDomain	124
MCLI Run RestartStreamService	124
MCLI Run RevertDiskVersion	125
MCLI Run SetOverrideVersion	125
MCLI Run SetupConnection	125
MCLI Run Shutdown	126
MCLI Run StartDeviceDiskTempVersionMode	127
MCLI Run StartStreamService	127
MCLI Run StopDeviceDiskTempVersionMode	127
MCLI Run StopStreamService	128
MCLI Run UnlockAllDisk	128
MCLI Run UnlockDisk	129
MCLI Run UnmapDisk	129
MCLI Run ValidateDirectory	129
MCLI RunWithReturn	129
MCLI RunWithReturn Boot	129
MCLI RunWithReturn CommandActions	130
MCLI RunWithReturn CreateDisk	130
MCLI RunWithReturn CreateDiskStatus	131
MCLI RunWithReturn CreateMaintenanceVersion	131
MCLI RunWithReturn DeviceCount	131
MCLI RunWithReturn DiskLocatorCount	132
MCLI RunWithReturn DisplayMessage	132
MCLI RunWithReturn Enabled	133
MCLI RunWithReturn Exists	134
MCLI RunWithReturn ImportDisk	135
MCLI RunWithReturn ListDirectories	135
MCLI RunWithReturn MaintenanceVersionExists	136
MCLI RunWithReturn MapDisk	136
MCLI RunWithReturn MappedDiskId	137
MCLI RunWithReturn MappedDriveLetter	137
MCLI RunWithReturn MinimumLastAutoAddDeviceNumber	137
MCLI RunWithReturn RebalanceDevices	137
MCLI RunWithReturn Reboot	138

MCLI RunWithReturn ReportBug	139
MCLI RunWithReturn ServerCount	139
MCLI RunWithReturn ServerName	139
MCLI RunWithReturn ServerStoreActiveDeviceCount	139
MCLI RunWithReturn Shutdown	140
MCLI RunWithReturn StoreFreeSpace	141
MCLI RunWithReturn TaskStatus	141
MCLI RunWithReturn UpdateBDM	141
MCLI RunWithReturn UploadCeip	142
MCLI Set	142
MCLI Set AuthGroup	142
MCLI Set CeipData	142
MCLI Set CisData	142
MCLI Set Collection	143
MCLI Set Device	144
MCLI Set Disk	146
MCLI Set DiskLocator	147
MCLI Set DiskUpdateDevice	148
MCLI Set DiskVersion	149
MCLI Set Farm	149
MCLI Set FarmView	150
MCLI Set Server	150
MCLI Set ServerBiosBootstrap	153
MCLI Set ServerBootstrap	154
MCLI Set ServerStore	155
MCLI Set Site	155
MCLI Set SiteView	156
MCLI Set Store	156
MCLI Set UpdateTask	157
MCLI Set VirtualHostingPool	158
MCLI Set XDSite	159
MCLI SetList	159
MCLI SetList DeviceBootstraps	159
MCLI SetList DeviceCustomProperty	160

MCLI SetList DeviceDiskPrinters.....	160
MCLI SetList DevicePersonality	160
MCLI SetList DiskLocatorCustomProperty	161
MCLI SetList ServerCustomProperty.....	161

Short command list

MCLI Add

```
MCLI Add AuthGroup
MCLI Add CeipData
MCLI Add CisData
MCLI Add Collection
MCLI Add Device
MCLI Add DeviceWithPersonalvDisk
MCLI Add DiskLocator
MCLI Add DiskUpdateDevice
MCLI Add FarmView
MCLI Add Server
MCLI Add Site
MCLI Add SiteView
MCLI Add Store
MCLI Add UpdateTask
MCLI Add VirtualHostingPool
```

MCLI Delete

```
MCLI Delete AuthGroup
MCLI Delete Collection
MCLI Delete Device
MCLI Delete DeviceDiskCacheFile
MCLI Delete DiskLocator
MCLI Delete DiskUpdateDevice
MCLI Delete DiskVersion
MCLI Delete FarmView
MCLI Delete Server
MCLI Delete ServerStore
MCLI Delete Site
MCLI Delete SiteView
MCLI Delete Store
MCLI Delete UpdateTask
MCLI Delete VirtualHostingPool
```

MCLI Get

```
MCLI Get AdDomains
MCLI Get AuditActionParameters
MCLI Get AuditActionProperties
MCLI Get AuditActionSibling
MCLI Get AuditTrail
MCLI Get AuthGroup
MCLI Get AuthGroupUsage
MCLI Get CeipData
MCLI Get CisData
MCLI Get Collection
MCLI Get CommandDescription
MCLI Get CommandFields
MCLI Get CommandParameters
MCLI Get CommandSortFields
MCLI Get CommandStandardParameters
```

```
MCLI Get Device
MCLI Get DeviceBootstraps
MCLI Get DeviceCustomProperty
MCLI Get DeviceDiskPrinters
MCLI Get DeviceDiskTempVersion
MCLI Get DeviceInfo
MCLI Get DevicePersonality
MCLI Get DeviceStatus
MCLI Get Disk
MCLI Get DiskInfo
MCLI Get DiskInventory
MCLI Get DiskLocator
MCLI Get DiskLocatorCustomProperty
MCLI Get DiskLocatorLock
MCLI Get DiskPrinters
MCLI Get DiskUpdateDevice
MCLI Get DiskUpdateStatus
MCLI Get DiskVersion
MCLI Get ExceptionDescriptions
MCLI Get Farm
MCLI Get FarmView
MCLI Get Groups
MCLI Get NewVersionDisks
MCLI Get Server
MCLI Get ServerBiosBootstrap
MCLI Get ServerBootstrap
MCLI Get ServerBootstrapNames
MCLI Get ServerCustomProperty
MCLI Get ServerInfo
MCLI Get ServerStatus
MCLI Get ServerStore
MCLI Get Site
MCLI Get SiteView
MCLI Get Store
MCLI Get StoreSharedOrServerPath
MCLI Get Task
MCLI Get UndefinedDisks
MCLI Get UpdateTask
MCLI Get VirtualHostingPool
MCLI Get XDSite
```

MCLI Info

```
MCLI Info Group
MCLI Info LocalServer
MCLI Info MapiErrorCode
MCLI Info Version
```

MCLI Run

```
MCLI Run ActivateDevice
MCLI Run AddDeviceToDomain
MCLI Run AddDiskVersion
MCLI Run ApplyAutoUpdate
MCLI Run ArchiveAuditTrail
MCLI Run AssignAuthGroup
MCLI Run AssignDevice
MCLI Run AssignDisk
```

```
MCLI Run AssignDiskLocator
MCLI Run AssignServer
MCLI Run Boot
MCLI Run CancelTask
MCLI Run ClearTask
MCLI Run CopyPasteDevice
MCLI Run CopyPasteDisk
MCLI Run CopyPasteServer
MCLI Run CreateDirectory
MCLI Run CreateDiskCancel
MCLI Run DisableCollection
MCLI Run DisableDevice
MCLI Run DisableDeviceDiskLocator
MCLI Run DisableDiskLocator
MCLI Run DiskUpdateCancel
MCLI Run DiskUpdateStart
MCLI Run DisplayMessage
MCLI Run EnableCollection
MCLI Run EnableDevice
MCLI Run EnableDeviceDiskLocator
MCLI Run EnableDiskLocator
MCLI Run ExportDisk
MCLI Run ExportOemLicenses
MCLI Run ForceInventory
MCLI Run ImportDatabase
MCLI Run ImportDevices
MCLI Run ImportOemLicenses
MCLI Run MarkDown
MCLI Run MergeDisk
MCLI Run PromoteDiskVersion
MCLI Run Reboot
MCLI Run RemoveAuthGroup
MCLI Run RemoveDevice
MCLI Run RemoveDeviceFromDomain
MCLI Run RemoveDirectory
MCLI Run RemoveDisk
MCLI Run RemoveDiskLocator
MCLI Run ResetDatabaseConnection
MCLI Run ResetDeviceForDomain
MCLI Run RestartStreamService
MCLI Run RevertDiskVersion
MCLI Run SetOverrideVersion
MCLI Run SetupConnection
MCLI Run Shutdown
MCLI Run StartDeviceDiskTempVersionMode
MCLI Run StartStreamService
MCLI Run StopDeviceDiskTempVersionMode
MCLI Run StopStreamService
MCLI Run UnlockAllDisk
MCLI Run UnlockDisk
MCLI Run UnmapDisk
MCLI Run ValidateDirectory
```

MCLI RunWithReturn

```
MCLI RunWithReturn Boot
MCLI RunWithReturn CommandActions
```

```
MCLI RunWithReturn CreateDisk
MCLI RunWithReturn CreateDiskStatus
MCLI RunWithReturn CreateMaintenanceVersion
MCLI RunWithReturn DeviceCount
MCLI RunWithReturn DiskLocatorCount
MCLI RunWithReturn DisplayMessage
MCLI RunWithReturn Enabled
MCLI RunWithReturn Exists
MCLI RunWithReturn ImportDisk
MCLI RunWithReturn ListDirectories
MCLI RunWithReturn MaintenanceVersionExists
MCLI RunWithReturn MapDisk
MCLI RunWithReturn MappedDiskId
MCLI RunWithReturn MappedDriveLetter
MCLI RunWithReturn MinimumLastAutoAddDeviceNumber
MCLI RunWithReturn RebalanceDevices
MCLI RunWithReturn Reboot
MCLI RunWithReturn ReportBug
MCLI RunWithReturn ServerCount
MCLI RunWithReturn ServerName
MCLI RunWithReturn ServerStoreActiveDeviceCount
MCLI RunWithReturn Shutdown
MCLI RunWithReturn StoreFreeSpace
MCLI RunWithReturn TaskStatus
MCLI RunWithReturn UpdateBDM
MCLI RunWithReturn UploadCeip
```

MCLI Set

```
MCLI Set AuthGroup
MCLI Set CeipData
MCLI Set CisData
MCLI Set Collection
MCLI Set Device
MCLI Set Disk
MCLI Set DiskLocator
MCLI Set DiskUpdateDevice
MCLI Set DiskVersion
MCLI Set Farm
MCLI Set FarmView
MCLI Set Server
MCLI Set ServerBiosBootstrap
MCLI Set ServerBootstrap
MCLI Set ServerStore
MCLI Set Site
MCLI Set SiteView
MCLI Set Store
MCLI Set UpdateTask
MCLI Set VirtualHostingPool
MCLI Set XDSite
```

MCLI SetList

```
MCLI SetList DeviceBootstraps
MCLI SetList DeviceCustomProperty
MCLI SetList DeviceDiskPrinters
MCLI SetList DevicePersonality
MCLI SetList DiskLocatorCustomProperty
```

```
MCLI SetList ServerCustomProperty
```

Commands by Object Type

Many

```
MCLI Get AuditActionParameters
MCLI Get AuditActionProperties
MCLI Get AuditActionSibling
MCLI Get AuditTrail
MCLI Get CommandDescription
MCLI Get CommandFields
MCLI Get CommandParameters
MCLI Get CommandSortFields
MCLI Get CommandStandardParameters
MCLI Get ExceptionDescriptions
MCLI Run ResetDatabaseConnection
MCLI Run SetupConnection
MCLI RunWithReturn CommandActions
MCLI RunWithReturn Enabled
MCLI RunWithReturn Exists
```

AuthGroup

```
MCLI Add AuthGroup
MCLI Delete AuthGroup
MCLI Get AuthGroup
MCLI Get AuthGroupUsage
MCLI Run AssignAuthGroup
MCLI Run RemoveAuthGroup
MCLI Set AuthGroup
```

Collection

```
MCLI Add Collection
MCLI Delete Collection
MCLI Get Collection
MCLI Run DisableCollection
MCLI Run EnableCollection
MCLI RunWithReturn MinimumLastAutoAddDeviceNumber
MCLI Set Collection
```

Device

```
MCLI Add Device
MCLI Add DeviceWithPersonalvDisk
MCLI Delete Device
MCLI Delete DeviceDiskCacheFile
MCLI Get Device
MCLI Get DeviceBootstraps
MCLI Get DeviceCustomProperty
MCLI Get DeviceDiskPrinters
MCLI Get DeviceDiskTempVersion
MCLI Get DeviceInfo
MCLI Get DevicePersonality
MCLI Get DeviceStatus
MCLI Run ActivateDevice
MCLI Run AddDeviceToDomain
```

```
MCLI Run AssignDevice
MCLI Run Boot
MCLI Run CopyPasteDevice
MCLI Run DisableDevice
MCLI Run DisableDeviceDiskLocator
MCLI Run DisplayMessage
MCLI Run EnableDevice
MCLI Run EnableDeviceDiskLocator
MCLI Run ExportOemLicenses
MCLI Run ImportDatabase
MCLI Run ImportDevices
MCLI Run ImportOemLicenses
MCLI Run MarkDown
MCLI Run Reboot
MCLI Run RemoveDevice
MCLI Run RemoveDeviceFromDomain
MCLI Run ResetDeviceForDomain
MCLI Run Shutdown
MCLI Run StartDeviceDiskTempVersionMode
MCLI Run StopDeviceDiskTempVersionMode
MCLI RunWithReturn Boot
MCLI RunWithReturn DeviceCount
MCLI RunWithReturn DisplayMessage
MCLI RunWithReturn Reboot
MCLI RunWithReturn Shutdown
MCLI RunWithReturn UpdateBDM
MCLI Set Device
MCLI SetList DeviceBootstraps
MCLI SetList DeviceCustomProperty
MCLI SetList DeviceDiskPrinters
MCLI SetList DevicePersonality
```

Disk

```
MCLI Add DiskUpdateDevice
MCLI Delete DiskUpdateDevice
MCLI Delete DiskVersion
MCLI Get Disk
MCLI Get DiskInfo
MCLI Get DiskInventory
MCLI Get DiskPrinters
MCLI Get DiskUpdateDevice
MCLI Get DiskUpdateStatus
MCLI Get DiskVersion
MCLI Get NewVersionDisks
MCLI Get UndefinedDisks
MCLI Run AddDiskVersion
MCLI Run AssignDisk
MCLI Run CopyPasteDisk
MCLI Run CreateDiskCancel
MCLI Run ExportDisk
MCLI Run ForceInventory
MCLI Run MergeDisk
MCLI Run PromoteDiskVersion
MCLI Run RemoveDisk
MCLI Run RevertDiskVersion
MCLI Run SetOverrideVersion
```

```
MCLI Run UnlockAllDisk
MCLI Run UnlockDisk
MCLI Run UnmapDisk
MCLI RunWithReturn CreateDisk
MCLI RunWithReturn CreateDiskStatus
MCLI RunWithReturn CreateMaintenanceVersion
MCLI RunWithReturn ImportDisk
MCLI RunWithReturn MaintenanceVersionExists
MCLI RunWithReturn MapDisk
MCLI RunWithReturn MappedDiskId
MCLI RunWithReturn MappedDriveLetter
MCLI Set Disk
MCLI Set DiskUpdateDevice
MCLI Set DiskVersion
```

DiskLocator

```
MCLI Add DiskLocator
MCLI Delete DiskLocator
MCLI Get DiskLocator
MCLI Get DiskLocatorCustomProperty
MCLI Get DiskLocatorLock
MCLI Run AssignDiskLocator
MCLI Run DisableDiskLocator
MCLI Run EnableDiskLocator
MCLI Run RemoveDiskLocator
MCLI RunWithReturn DiskLocatorCount
MCLI Set DiskLocator
MCLI SetList DiskLocatorCustomProperty
```

Farm

```
MCLI Get Farm
MCLI Get XDSite
MCLI Run ArchiveAuditTrail
MCLI Set Farm
MCLI Set XDSite
```

FarmView

```
MCLI Add FarmView
MCLI Delete FarmView
MCLI Get FarmView
MCLI Set FarmView
```

Server

```
MCLI Add Server
MCLI Delete Server
MCLI Delete ServerStore
MCLI Get Server
MCLI Get ServerBiosBootstrap
MCLI Get ServerBootstrap
MCLI Get ServerBootstrapNames
MCLI Get ServerCustomProperty
MCLI Get ServerInfo
MCLI Get ServerStatus
MCLI Get ServerStore
MCLI Run ApplyAutoUpdate
```

```
MCLI Run AssignServer
MCLI Run CopyPasteServer
MCLI Run CreateDirectory
MCLI Run RemoveDirectory
MCLI Run RestartStreamService
MCLI Run StartStreamService
MCLI Run StopStreamService
MCLI Run ValidateDirectory
MCLI RunWithReturn ListDirectories
MCLI RunWithReturn RebalanceDevices
MCLI RunWithReturn ReportBug
MCLI RunWithReturn ServerCount
MCLI RunWithReturn ServerName
MCLI RunWithReturn ServerStoreActiveDeviceCount
MCLI Set Server
MCLI Set ServerBiosBootstrap
MCLI Set ServerBootstrap
MCLI Set ServerStore
MCLI SetList ServerCustomProperty
```

Site

```
MCLI Add Site
MCLI Delete Site
MCLI Get Site
MCLI Get StoreSharedOrServerPath
MCLI Set Site
```

SiteView

```
MCLI Add SiteView
MCLI Delete SiteView
MCLI Get SiteView
MCLI Set SiteView
```

Store

```
MCLI Add Store
MCLI Delete Store
MCLI Get Store
MCLI RunWithReturn StoreFreeSpace
MCLI Set Store
```

System

```
MCLI Get AdDomains
MCLI Get Groups
MCLI Info Group
MCLI Info LocalServer
MCLI Info MapiErrorCode
MCLI Info Version
```

Task

```
MCLI Get Task
MCLI Run CancelTask
MCLI Run ClearTask
MCLI RunWithReturn TaskStatus
```

UpdateTask

```
MCLI Add UpdateTask
MCLI Delete UpdateTask
MCLI Get UpdateTask
MCLI Run DiskUpdateCancel
MCLI Run DiskUpdateStart
MCLI Set UpdateTask
```

VirtualHostingPool

```
MCLI Add VirtualHostingPool
MCLI Delete VirtualHostingPool
MCLI Get VirtualHostingPool
MCLI Set VirtualHostingPool
```

CeipData

```
MCLI Add CeipData
MCLI Get CeipData
MCLI RunWithReturn UploadCeip
MCLI Set CeipData
```

CisData

```
MCLI Add CisData
MCLI Get CisData
MCLI Set CisData
```

Error codes

```
0 Success: The command succeeded.
1 NotImplemented: The [v1] feature has not been implemented.
2 InvalidCommand: The [v1] command does not exist.
3 InvalidField: The [v1] field does not exist.
4 InvalidFieldFormat: The [v1] field is not formatted properly, the
    correct format is [v2].
5 InvalidParameter: The [v1] parameter is not valid.
6 InvalidParameterFormat: The [v1] parameter is not formatted properly,
    the correct format is [v2].
7 ReadOnlyField: Unable to change the [v1] field because it is read-only.
8 RequiredFieldMissing: The required [v1] field is missing.
9 RequiredFieldsMissing: The required [v1] or [v2] field is missing.
10 RequiredParameterMissing: The required [v1] parameter is missing.
11 RequiredParametersMissing: The required [v1] or [v2] parameter is
    missing.
12 InternalIdAndNameFieldsMustBeDefined: An internal error occurred. The
    [v1] field is not the next FieldSettings object after the ID.
13 NoFarmAccess: The domain/user does not have access to the Farm.
14 InvalidForeignKeyValue: The [v1] field with value [v2] is an invalid
    foreign key.
15 SetupError: The system was not configured correctly.
16 Executing: The [v1] command can only be called one at a time. Wait for
    the command to finish before running again.
17 NoDiskMapped: A vDisk has not yet been mapped.
18 DatabaseError: A database error occurred.
19 DuplicateKey: To avoid creating a duplicate key, the Add or Set command
    was cancelled.
```

```

20 DatabaseErrorMissed: An internal error occurred. An uncaught database
    error occurred.
21 AddCommandFailed: No objects were added during the last 'Add' command.
22 InsufficientPrivileges: Access denied. The appropriate privileges are
    not assigned to perform this task.
23 ZeroObjectsAffected: No object was added, updated, or deleted in the
    last operation.
24 OtherException: An unexpected MAPI error occurred.
25 InvalidFieldLength: The [v1] field value is too long, maximum length is
    [v2].
26 InvalidFieldValueMinMax: The [v1] field value is invalid, the minimum is
    [v2] and the maximum is [v3].
27 InvalidFieldValue: The [v1] field can only have values [v2] or [v3].
28 TooManyParameters: More parameters were specified than permitted.
29 TooFewParameters: Not enough identifying parameters specified.
30 FollowingParametersMissing: To use the [v1] parameter, [v2] or [v3] must
    also be used.
31 InconsistentData: The action is canceled because the Store directory
    date/times does not match. Update the Store directories to match.
32 DatabaseOpenFailed: Unable to contact the database server. Ensure Citrix
    Provisioning server is configured correctly.
33 DatabaseVersionWrong: The wrong database version is being used. Found
    version number: [v1] Expected version number: [v2]
34 DatabaseVersionNotFound: The database version number does not exist or
    was not found. Ensure Citrix Provisioning server is configured
    correctly.
35 SomeRequiredParametersMissing: Required parameters are missing.
36 PartialError: The following items failed:
    item1 Error message...
    item2 Error message...
37 NoItemsToProcess: There are no items to process.
38 NoDefaultCollectionDefined: Unable to add a Device until a default
    Collection is set.
39 NoDefaultSiteDefined: A default Site is not set, no Devices can be
    added.
40 InvalidCollection: The specified Collection does not exist.
41 InvalidAuthGroup: The specified AuthGroup does not exist.
42 InvalidGroup: The specified Group does not exist.
43 InvalidDevice: The specified Device does not exist.
44 InvalidDiskLocator: The specified vDisk does not exist.
45 InvalidServer: The specified Server does not exist.
46 InvalidServerSite: Server specified is not in the Site specified.
47 InvalidStoreSite: Store specified is not for the Site specified.
48 InvalidSiteView: The specified Site View does not exist.
49 InvalidSite: The specified Site does not exist.
50 InvalidDeviceDiskLocator: The specified Device or vDisk does not exist.
51 InvalidDeviceImport: Import failed because the file must have Device
    Name, Mac Address, Site Name, and Collection Name, and they must be
    tab or comma-delimited.
52 InvalidServerFrom: The Server to copy [v1]=[v2] was not found.
53 InvalidServerTo: No Server to copy to ([v1]=[v2]) was found.
54 InvalidDeviceFrom: The Device to copy [v1]=[v2] was not found.
55 InvalidDeviceTo: No Devices to copy to are found.
56 InvalidDiskFrom: The vDisk to copy [v1]=[v2] was not found.
57 InvalidDiskTo: No vDisk to copy to ([v1]=[v2]) was found.
58 InvalidDiskPath: The path '[v1]' to the vDisk file is not found.
59 VDiskFileNotFound: [v1]: vDisk file was not found.

```

60 InvalidDiskServer: There is no Server that can serve the vDisk [v1] or the Store to which this vDisk belongs. Verify that one or more Servers belonging to the Store are online and that there is sufficient free space for the operation you are attempting.

61 InvalidDiskForServer: Server [v1] cannot access all versions of vDisk [v2], the vDisk was updated on at least one other Server.

62 SameSiteRequired: Objects within the same Site must be selected.

63 TooFewFields: Not enough fields for a record.

64 ADerrorDC: Unable to connect to the Domain Controller (if any) or the default rootDSE. Error code: [v1], message: [v2], provider: [v3].

65 ADerrorOU: Unable to get the Organizational Unit setting (if any). Error code: [v1], message: [v2], provider: [v3].

66 ADerrorDefaultContainer: Unable to get the default computer accounts container (default location is Active Directory root> Computers). Error code: [v1], message: [v2], provider: [v3].

67 ADerrorCreate: Unable to create the computer account in Active Directory. Ensure the account does not already exist and that the appropriate permissions are available to perform this task. Error code: [v1], message: [v2], provider: [v3].

68 ADerrorNewAccount: Unable to get the newly created Active Directory computer account. Error code: [v1], message: [v2], provider: [v3].

69 ADerrorSam: Unable to set the Active Directory samAccountName property. Ensure the appropriate permissions exist to perform this task. Error code: [v1], message: [v2], provider: [v3].

70 ADerrorUserAccount: Unable to set the Active Directory userAccountControl property. Ensure the appropriate permissions exist to perform this task. Error code: [v1], message: [v2], provider: [v3].

71 ADerrorSave: Unable to save Active Directory change. Ensure the appropriate permissions exist to perform this task. Error code: [v1], message: [v2], provider: [v3].

72 ADerrorSetPassword: Unable to set a new password for this user account. Ensure the appropriate permissions exist to perform this task. Error code: [v1], message: [v2], provider: [v3].

73 ADerrorAddTrustee: Unable to add trustee (if any). Error code: [v1], message: [v2], provider: [v3].

74 ADerrorEnableAccount: Unable to enable the Active Directory account. Error code: [v1], message: [v3], provider: [v2].

75 ADerrorAlreadyExists: The computer name is already in use. Error code: [v1], message: [v3], provider: [v2]. Select a unique name for this machine.

76 ADerrorGeneral: A general Active Directory error occurred. Error code: [v1], message: [v2], provider: [v3].

77 ADerrorDirectorySearch: Unable to find Active Directory items meeting the search criteria entered. Error code: [v1], message: [v2], provider: [v3].

78 ADerrorSearchComputerAccount: Unable to perform the computer accounts search. Error code: [v1], message: [v2], provider: [v3].

79 ADerrorComputerAccountNotFound: Specified computer account not found. Error code: [v1], message: [v2], provider: [v3].

80 ADerrorComputerAccountHold: This computer account is currently unavailable. Ensure that Active Directory is running properly. Error code: [v1], message: [v2], provider: [v3].

81 ADerrorComputerAccountMove: Failed to move the computer account to the target organizational unit set (also returned if caller lacks permission). Error code: [v1], message: [v2], provider: [v3].

82 ADerrorDelete: Unable to delete this computer account. Ensure the appropriate permissions exist to perform this task. Error code: [v1], message: [v2], provider: [v3].
83 ADerrorPasswordGeneration: Unable to generate this password. Ensure the appropriate permissions exist to perform this task.
84 MapDiskNoDriver: Unable to map vDisk because a driver was not found.
85 MapDiskDeniedByServer: Unable to map the vDisk. Mapping was denied by the Server.
86 MapDiskLocalAccessDenied: Unable to map the vDisk. Denied local access.
87 MapDiskMiniportError: Unable to map vDisk because of a Miniport error.
88 UnmapDiskFailed: Failed to unmap a vDisk.
89 DuplicateDisk: The vDisk [v1] already exists on [v2] at [v3].
90 DuplicateDiskLocator: A DiskLocator: [v1] already exists on Site: [v2].
91 DiskCreationInProgress: The vDisk [v1] is being created on [v2] at [v3].
92 InvalidServerStore: A database integrity error occurred. The Server is not set to deliver vDisks from the Store, but should be.
93 InvalidStore: The specified Store does not exist.
94 InvalidFarmView: Farm View specified does not exist.
95 InvalidStorePath: Store path is empty.
96 ManagementInterfaceError:
 Management Interface: Undefined error.
 Management Interface: Database interface is inaccessible.
 Management Interface: Database interface library is inaccessible.
 Management Interface: The database access library is a version incompatible with the Management Server.
 Management Interface: Database interface library is invalid.
 Management Interface: Database interface could not be created.
 Management Interface: Database could not be opened.
 Management Interface: Database is in use.
 Management Interface: Database error occurred.
 Management Interface: Not implemented.
 Management Interface: Registry entry was not found.
 Management Interface: Request was not created.
 Management Interface: Operating System error occurred.
 Management Interface: vDisk error.
 Management Interface: vDisk header is incomplete.
 Management Interface: vDisk footer is incomplete.
 Management Interface: vDisk boot record is incomplete.
 Management Interface: vDisk boot sector is incomplete.
 Management Interface: vDisk size is below the minimum.
 Management Interface: vDisk size is above the maximum.
 Management Interface: vDisk boot record template is inaccessible.
 Management Interface: vDisk boot sector template is inaccessible.
 Management Interface: vDisk lock was not found.
 Management Interface: vDisk has exclusive lock.
 Management Interface: vDisk has shared lock.
 Management Interface: vDisk lock error.
 Management Interface: vDisk format is incompatible.
 Management Interface: vDisk prefooter is incomplete.
 Management Interface: vDisk creation is in progress.
 Management Interface: vDisk creation information was not found.
 Management Interface: vDisk creation cancellation was requested.
 Management Interface: vDisk file was not found.
 Management Interface: vDisk file path was not found.
 Management Interface: vDisk file access was denied.
 Management Interface: Cancelled.
 Management Interface: Registry key for the product is inaccessible.

Management Interface: Registry key for the installation folder is inaccessible.

Management Interface: Registry key for the management interface is inaccessible.

Management Interface: Registry key for the database path is inaccessible.

Management Interface: Registry key for the management interface IP address is inaccessible.

Management Interface: Buffer size is too small.

Management Interface: Buffer size is too large.

Management Interface: Unknown error.

Management Interface: Remote Server failed to relay a request.

Management Interface: Remote Server is not servicing the Device.

Management Interface: Remote Server or Device refused the request.

Management Interface: Local Server failed to complete a request to a Server or Device.

Management Interface: Local Server failed to complete a request to a Server.

Management Interface: Remote requests were disabled because of an initialization error.

Management Interface: Remote request failed.

Management Interface: Remote request timed out.

Management Interface: Remote request result was not found.

Management Interface: Remote request receiver failed to initialize.

Management Interface: Management command failed for all objects.

Management Interface: Failed to get the preshared key in secure version.

Management Interface: VHD Error.

Management Interface: vDisk properties were lost.

Management Interface: Insufficient Memory.

Management Interface: The network path was not found.

Management Interface: The network name cannot be found.

Management Interface: File already exists.

Management Interface: The geometry of the vDisk is not accessible.

Management Interface: Unable to create the vDisk because the store media is read-only.

Management Interface: vDisk file is being used by another process.

97 ServerTimeout: Server did not respond to a request in time.

98 NotFound: [v1] not found.

99 AccountRetrieve: Account information for user [v1] was not found.

100 ActiveDevice: The task cannot be performed on active Devices. Shut down the Devices before attempting to perform the task.

101 ActiveDiskLocator: The task cannot be performed on active vDisks. Shut down the Devices that are using the vDisks before attempting to perform the task.

102 AssignedDiskLocator: Unable to delete a vDisk that is currently assigned to a Device. Unassign all Devices, then delete the vDisk.

103 ActiveServer: The task cannot be performed on active Servers. Shut down the Servers before attempting to perform the task.

104 NotEnoughFreeDiskSpace: There is not enough free disk space to create the vDisk.

105 InvalidDiskName: The vDisk name has one or more invalid characters. The invalid characters are < > | " \ / : * ?.

106 CannotDeleteLastAuthGroup: Deleting the last Authorization Group causes the system to be inoperable.

107 CannotDeleteUsedAuthGroup: An Authorization Group that is currently in use cannot be deleted.

```

108 ServerStartFailed: The Server did not start successfully. Ensure the
    appropriate permissions exist for the service account.
109 ServerStopFailed: The Server did not stop successfully.
110 LockOwnerNotFound: The Device that owns the lock was not found, the
    vDisk was not unlocked.
111 PossiblySharedVDisk: Unable to delete File [v1]. It is possible that the
    file is being referenced in other Sites or Stores.
112 StorePathInaccessible: The Store path [v1] is inaccessible.
113 InvalidAction: The [v1] action does not exist.
114 InvalidObjectType: The [v1] objectType does not exist.
115 TooManyRecords: The amount of data returned using Get is too large. Use
    GetFirst and GetNext instead of Get.
116 InvalidUserGroup: The specified UserGroup does not exist.
117 InvalidAuditAction: The specified AuditAction does not exist.
118 LoginFailed: The database login failed. Ensure the appropriate
    permissions exist to access the database.
119 DatabaseConnectionError: Unable to connect to the database. Restore the
    connection in order to manage the farm.
120 CreateTriggersParsing: Unable to parse the database script
    'CreateTriggers' at: [v1]
121 CreateStoredProcParsing: Unable to parse the database script
    'CreateStoredProcedures' at: [v1]
122 MediaIsReadOnly: Management Interface: Unable to create the vDisk
    because the store media is read-only.
123 ConnectedDeviceForVirtualHostingPool: Unable to delete this VM from a
    machine catalog because it is connected to a Delivery Group.
124 ADerrorDN: Unable to get the distinguishedName property. Ensure the
    appropriate Active Directory permissions exist to perform this task.
    Error code: [v1], message: [v2], provider: [v3].
125 ADerrorGetSecDes: Unable to get the Active Directory Security Descriptor
    property. Error code: [v1], message: [v2], provider: [v3].
126 ADerrorSetSecDes: Unable to set the Active Directory Security Descriptor
    property. Ensure the appropriate permissions exist to perform this
    task. Error code: [v1], message: [v2], provider: [v3].
127 ADerrorDNSHostName: Unable to set the DNS Host Name property
    (DNSHostName). Ensure the appropriate permissions exist to perform
    this task. Error code: [v1], message: [v2], provider: [v3].
128 ADerrorDisplayName: Unable to set the displayName property. Error code:
    [v1], message: [v2], provider: [v3].
129 ADerrorBind: This device was unable to bind to the Domain Controller.
    Ensure the Domain Controller is running. Error code: [v1], message:
    [v2], provider: [v3].
130 ADerrorGetSPN: Unable to get an Active Directory Service Principal Name.
    Error code: [v1], message: [v2], provider: [v3].
131 ADerrorWriteSPN: Unable to write the Active Directory Service Principal
    Name. Error code: [v1], message: [v2], provider: [v3]
132 ADerrorSearch: Unable to perform the requested Search. Error code: [v1],
    message: [v2], provider: [v3].
133 ADerrorMoveToOU: Unable to move the Active Directory account to the
    requested Organizational Unit. Ensure the appropriate permissions
    exist to perform this task. Error code: [v1], message: [v2], provider:
    [v3].
134 ADerrorDeleteAccount: Unable to delete this computer account. Ensure the
    appropriate permissions exist to delete accounts. Error code: [v1],
    message: [v2], provider: [v3].
135 ADerrorBadParameters: Incorrect parameters sent to Citrix Provisioning
    from Studio. Error code: [v1], message: [v2], provider: [v3].

```

```
136 VolumeInUse: The volume is being used.
137 VolumeAccessDenied: Volume access is denied.
138 VolumeUnknownVolume: An unknown volume was specified.
139 VolumeGeneralError: An error occurred when executing a volume command.
140 MaintenanceServerError: Action cannot be performed, [v1] is a
    maintenance server for [v2].
141 NotManagedStore: The action cannot be performed because the store is not
    managed.
142 PathNotExist: The path does not exist on the given Server.
143 PathNoCreatePermission: The path does not have the appropriate create
    permissions.
144 PathNoReadPermission: The path does not have the appropriate read
    permissions.
145 PathNoWritePermission: The path does not have the appropriate write
    permissions.
146 PathNoDeletePermission: The path does not have the appropriate delete
    permissions.
147 IPCProtocolError: An internal error occurred. A field is missing from
    the process communication protocol data.
148 InvalidStoreServer: No active Server can serve the Store [v1].
149 ConstraintCheck: A database constraint caused an Add or Update to be
    stopped.
150 VamtNotFound: The Volume Activation Management Tool cannot be found.
151 ADerrorCannotGetObjectSID: Cannot return objectSID. Error code: [v1],
    message: [v2], provider: [v3].
152 ADerrorCannotDisableAccount: Cannot disable the Active Directory account
    at this time. Ensure that all account users are logged off before
    attempting to disable the account. Error code: [v1], message: [v2],
    provider: [v3].
153 ADerrorFailedToChangePassword: Unable to reset the machine account
    password. Ensure the appropriate permissions exist to perform this
    Active Directory task. Error code: [v1], message: [v2], provider:
    [v3].
154 ADerrorFailedToCopyDCName: Unable to copy the Domain Controller name.
    Error code: [v1], message: [v2], provider: [v3].
155 ADerrorDCNameIsTooLong: The Domain Controller name entered exceeds the
    maximum character length of [v4]. Error code: [v1], message: [v2],
    provider: [v3].
156 SiteMakUserPassword: The Site's makUser and makPassword fields must have
    values.
157 VamtError: See the log for additional error details.
158 InactiveDevice: Device specified is not active.
159 DiskIsInPrivateMode: This task cannot be performed because the vDisk is
    in private image mode.
160 AlreadyInChangeMode: Unable to complete this operation, vDisk is already
    in Maintenance, Merge, or Test mode.
161 CannotCreateMaintenanceDisk: Cannot create maintenance vDisk.
162 CannotEnterMaintenanceMode: To place a vDisk in Maintenance Mode
    requires using a Server. No Server is available at this time.
163 NotInMaintenanceMode: Unable to perform this action because the vDisk is
    not in Maintenance Mode.
164 NoVersionForMaintenanceMode: Unable to place this vDisk in Maintenance
    Mode because the highest version is not found.
165 NoVersionFound: Unable to perform this action because a version record
    was not found in the database.
166 Obsolete: The [v1] feature is obsolete.
167 DatabaseWarning: A database warning occurred.
```

```

168 DatabaseSQL: A database SQL error occurred.
169 DatabaseResource: A database resource error occurred.
170 InvalidUpdateTask: The specified UpdateTask does not exist.
171 InvalidVirtualHostingPool: The specified VirtualHostingPool does not
    exist.
172 RemoteCommand: An exception occurred executing a command on a remote
    Server.
173 IpcNotConfigured: An internal error occurred. The process communication
    interface must be configured before executing remote commands.
174 DiskAlreadySetForUpdate: The vDisk is already set for Update with Device
    [v1] in Site [v2].
175 InvalidDiskVersion: The vDisk Version specified is not valid.
176 HostResolution: Could not resolve the host name for [v1].
177 InProcess: The remote task is taking longer than expected. TaskId: [v1]
178 DateMustBeInFuture: The [v1] must be in the future.
179 InvalidRemoteReturn: The remote command did not return valid data.
180 InvalidParameterValueMinMax: The [v1] parameter value is invalid, the
    minimum is [v2] and the maximum is [v3].
181 InvalidParameterNotNumeric: The [v1] parameter value is invalid, it is
    not numeric.
182 InvalidParameterNotGuid: The [v1] parameter value is invalid, it is not
    a GUID.
183 PassThroughMessage: [v1]
184 DiskUpdateNotEnabled: The Automatic vDisk Update option must be enabled
    and the vDisk Update Server must be defined. Set these in the Site
    properties.
185 PvsStatusException:
    Windows API error occurred, number 0xE000FFFF.
    SQL error occurred, number 0xE001FFFF.
    Manager error occurred. Error number 0xE002FFFF.
    StreamProcess error occurred. Error number 0xE003FFFF.
    Stream Database error occurred. Error number 0xE004FFFF.
    Management error occurred. Error number 0xE005FFFF.
    Shutdown in progress; request ignored. Error number 0xE0050001.
    CreateDiffDisk: Malformed packet; missing one or more arguments. Error
        number 0xE0050002.
    DeleteDiffDisk: Malformed file name; cannot parse directory and name.
        Error number 0xE0050003.
    DeleteDiffDisk: Malformed packet; missing one or more arguments. Error
        number 0xE0050004.
    IPC: Failed to read mtGetLocks parameters. Error number 0xE0050005.
    IPC: Failed to read mtGetLockStatus parameters. Error number
        0xE0050006.
    IPC: Failed to read mtLock parameters. Error number 0xE0050007.
    IPC: Failed to read mtUnlock parameters. Error number 0xE0050008.
    MergeDisk event: Malformed packet; unknown message type. Error number
        0xE0050009.
    MergeDisk event: Unknown target request ID. Error number 0xE005000A.
    MergeDisk event: Malformed packet; missing one or more arguments.
        Error number 0xE005000B.
    MergeDisk: Malformed packet; missing one or more arguments. Error
        number 0xE005000C.
    ValidateDisk: Malformed packet; missing one or more arguments. Error
        number 0xE005000D.
    VHD Library error occurred. Error number 0xE006FFFF.
    VHD Library: Not implemented. Error number 0xE0060001.
    VHD Library: Handle pointer is invalid. Error number 0xE0060002.

```

VHD Library: Length of the path exceeds the limit of the file system.
Error number 0xE0060003.

VHD Library: Name is empty. Error number 0xE0060004.

VHD Library: Length of the name exceeds the limit of the file system.
Error number 0xE0060005.

VHD Library: Size of a parameter was too big. Error number 0xE0060006.

VHD Library: Size of a parameter was too small. Error number
0xE0060007.

VHD Library: The media is write protected. Error number 0xE0060008.

VHD Library: Type is invalid. Error number 0xE0060009.

VHD Library: Footer is incomplete. Error number 0xE006000A.

VHD Library: Failed to read or write the entire VHD Header. Error
number 0xE006000B.

VHD Library: Failed to read or write the entire VHD Block Allocation
Table. Error number 0xE006000C.

VHD Library: Failed to read or write all of the VHD properties. Error
number 0xE006000D.

VHD Library: VHD footer is corrupt. Error number 0xE006000E.

VHD Library: VHD header is corrupt. Error number 0xE006000F.

VHD Library: Failed to read or write the VHD objects. Error number
0xE0060010.

VHD Library: Destination string is too small. Error number 0xE0060011.

VHD Library: Destination string pointer is NULL. Error number
0xE0060012.

VHD Library: Source string pointer is NULL. Error number 0xE0060013.

VHD Library: Offset is before the beginning of the VHD data area.
Error number 0xE0060014.

VHD Library: Offset is after the end of the VHD data area. Error
number 0xE0060015.

VHD Library: Failed to allocate memory because it was unavailable.
Error number 0xE0060016.

VHD Library: Caller cancelled the last create request. Error number
0xE0060017.

VHD Library: Failed to read or write all of the data as requested.
Error number 0xE0060018.

VHD Library: Failed to create a Universal Unique Identification for a
VHD. Error number 0xE0060019.

VHD Library: Failed to find the VHD properties. Error number
0xE006001A.

VHD Library: Failed to read or write the entire sector bitmap within a
block. Error number 0xE006001B.

VHD Library: Failed to read or write the entire block. Error number
0xE006001C.

VHD Library: Failed to open the file that represents the VHD. Error
number 0xE006001D.

VHD Library: Requested number of bytes exceeds the remainder of bytes
in a block. Error number 0xE006001E.

VHD Library: Accessed past end of the VHD file. Error number
0xE006001F.

VHD Library: Differencing VHD Unique ID (UUID) differs to parent VHD
Unique ID. Error number 0xE0060020.

VHD Library: Differencing VHD timestamp differs to parent VHD last
modified time. Error number 0xE0060021.

VHD Library: Failed to read or write the entire VHD Block Allocation
Table Map. Error number 0xE0060022.

IPC error occurred. Error number 0xE007FFFF.

There was an unknown transmission error. Error number 0xE0070001.

No response received for successful send. Error number 0xA0070002.
 Message processor timed out. Error number 0xE0070003.
 Retry limit exhausted. Error number 0xE0070004.
 Message recipient task is not active. Error number 0xE0070005.
 Socket send/recv cannot be retried. Error number 0xE0070006.
 Port shutdown due to connection opens exhausted. Error number 0xE0070007.
 Port shutdown due to flood of junk packets. Error number 0xE0070008.
 Port shutdown due to receive retries exhausted. Error number 0xE0070009.
 Transport does not support fragmentation. Error number 0xE007000A.
 One or more packet fragments are missing. Error number 0xE007000B.
 Error sending message. Error number 0xE0070100.
 Message acknowledgement timeout. Error number 0xA0070101.
 Command timeout. Error number 0xE0070102.
 Not implemented. Error number 0xE0070103.
 Error verifying message port number, must be >= 0 and <= 65535. Error number 0xE0070104.
 Command initialization failed. Error number 0xE0070105.
 Start of IPC failed. Error number 0xE0070106.
 Stop of IPC failed. Error number 0xE0070107.
 Memory allocation failure. Error number 0xE0070108.
 Internal error, failure to wait long enough for a communication response to be received. Error number 0xE0070109.
 Disk Update error occurred. Error number 0xE008FFFF.
 Inventory error occurred. Error number 0xE009FFFF.
 Inventory Table: Failed to start thread. Error number 0xE0090001.
 Inventory Table: Invalid Entry. Error number 0xE0090002.
 Inventory Table: Failed to initialize inventory. Error number 0xE0090003.
 Shutdown in progress; request ignored. Error number 0xE0090004.
 Get Disk Inventory: Parameters bad. Error number 0xE0090033.
 Populate database: Failed offline. Error number 0xE0090065.
 Populate database: Server get by name failed. Error number 0xE0090066.
 Populate database: Uninitialized. Error number 0xE0090067.
 Populate database: Get host name failed. Error number 0xE0090068.
 Populate database: Char conversion failed. Error number 0xE0090069.
 Populate database: Initialization failed. Error number 0xE009006A.
 Populate database: Database open failed. Error number 0xE009006B.
 Populate database: Get all disk locators failed. Error number 0xE009006C.
 Inventory Table: Not yet implemented. Error number 0xE009006D.
 Notifier error occurred. Error number 0xE00AFFFF.
 MAPI error occurred. Error number 0xE00BFFFF.
 186 TaskCancelled: Task [v1] is cancelled and is not running.
 187 TaskCompleted: Task [v1] has been completed and is not running.
 188 TaskInProgress: Task [v1] is running and cannot be processed.
 189 InvalidTask: The specified Task does not exist.
 190 InventoryServerCannotContactDatabase: The Inventory Service cannot contact the database.
 191 ServerOffline: The Server is offline.
 192 ServerStateUnknown: The Server state is unknown.
 193 HighestVersionIsPending: Could not complete this action because the highest vDisk version is still pending. The scheduled date for the version has not occurred yet.
 194 MergeInvalidWithCurrentVersions: Merge is not valid with the current versions that exist.

```
195 DiskInventoryError: vDisk versions are not up to date on all Servers
    that access this vDisk. Update all Servers with the latest versions of
    the vDisk files.
196 VDiskFileNotFoundWarning: [v1]: vDisk file was not found because it was
    deleted.
197 CannotAssignActiveServer: Stop the Server before attempting to assign
    the Server to a different site.
198 CannotAssignServerWithActiveDevice: Before attempting to assign the
    Server to a different site, shut down Devices connecting to the
    Server, then shut down the Server.
199 MappedDiskLocator: The vDisk is mapped and cannot be changed.
200 InvalidTemplateDevice: The Template Device must be a Production Device
    that does not have a Personal vDisk.
201 DeviceWithPersonalvDiskInvalid: Unable to process a Device that uses a
    personal vDisk.
202 CreatingDisk: Server is creating a vDisk so change cannot be done.
203 AssignedDiskLocatorToDeviceWithPersonalvDisk: Unable to delete a vDisk
    if the vDisk is currently assigned to a Device that uses a Personal
    vDisk. Unassign the Device, then delete the vDisk.
204 InvalidMacAddress: The MAC address for this VM is invalid. Configure the
    VM with a valid MAC address.
205 CannotGetMacFromHypervisor: The hypervisor did not return the MAC
    address for this VM: [v1]
206 Win32SystemException: A system error occurred.
207 RemoteManagementIpCannotBeResolved: Unable to resolve the management IP
    for Server [v1].
208 LocalManagementIpNotSet: The management IP for local server [v1] is not
    set in registry IPC\IPv4Address.
209 PerformVolumeMaintenanceTaskPermissions: Ensure the Service Account user
    has the appropriate 'Perform volume maintenance task' permissions.
210 CannotLoginToVirtualHostingPool: Unable to log on to the virtual hosting
    pool [v1]. Ensure that the hypervisor server is running properly.
211 VirtualHostingPoolNotSetForDevice: The virtualHostingPoolId for device
    [v1] with bdmBoot must be set.
212 ActiveBdmBootDeviceCannotProcess: The Boot Device Manager [v1] did not
    process successfully.
213 CannotMovePvdDeviceToAnotherSite: Personal vDisk Devices cannot be moved
    to another site.
214 XenDesktopSiteInvalid: Citrix Virtual Desktops Site for Devices is not
    valid, the Citrix Virtual Desktops Site is: [v1]
215 XenDesktopServiceListOutOfDate: Citrix Virtual Desktops Site [v1] is not
    reachable, check that the Citrix PVS Soap Server service user has
    Citrix Virtual Desktops permissions and network connectivity.
216 NoXenDesktopServiceForPersonalvDiskCapability: No Citrix Virtual
    Desktops service found for Personal vDisk capability.
217 InsufficientPermissionsToPreparePersonalvDisks: The user account for the
    Citrix PVS Soap Server has insufficient permissions to prepare
    Personal vDisks.
218 NotEnoughFreeDiskSpaceForManifest: There is not enough free disk space
    to create the manifest.
219 OperationCannotBeDoneOnlyPvdDevicesAssigned: Operation cannot be done,
    only Personal vDisk Devices are assigned.
220 DiskFormatCannotBeSetToVHD: The format cannot be set to VHD since no VHD
    vDisk file is found in the path, [v1], for Server, [v2].
221 DiskFormatCannotBeSetToVHDX: The format cannot be set to VHDX since no
    VHDX vDisk file is found in the path, [v1], for Server, [v2].
```

```

222 TemporaryVersionIsSet: This task cannot be performed because a temporary
    version is set.
223 DiskIsUsingPersistentCacheOnServer: A temporary version cannot be used
    for a vDisk that is using persistent cache on server.
224 UploadAlreadyInProgress: An upload is already in progress by Server
    [v1].
225 FieldMustBeNull: Field [v1] must be null.
226 DuplicateData: Record already exists in [v1] table for Farm.
227 CisUploadTokenGenerateError: Error generating upload token for My Citrix
    username [v1] ([v2]).
228 InvalidCredentials: The username or password is incorrect.
229 NoWriteAccessToFolders: No write access to folders [v1] or [v2].
230 ReportCreationError: Error creating problem report: [v1].
231 PvsProxyNotSupported: PVS Proxy not supported on this host
232 CannotCreateRegKey: Cannot create Registry key [v1]
4100 ADerrorUnexpectedError: An unexpected Active Directory related error
    occurred. Ensure the appropriate permissions exist to perform this
    task. Error code: [v1], message: [v2], provider: [v3].

```

MCLI Add

MCLI Add commandName[/r field=value[field2=value2]]

MCLI Add AuthGroup

Add an Active Directory or Windows Group for authorization.

/r or -r	Record to add. All record fields that do not have a Default are required.
authGroupName	Name of the Active Directory or Windows Group. Max Length=450
description	User description. Default="" Max Length=250
resultId	If successful, the GUID of the record added.

MCLI Add CeipData

Add a new entry to CeipData table.

/r or -r	Record to add. All record fields that do not have a Default are required.
enabled	1 if CEIP is enabled, otherwise 0. Min=0, Max=1
nextUpload	Date and time next CEIP upload is due if enabled is 1. Default=null
inProgress	1 if an upload is currently in progress, otherwise 0. Default=0
serverId	ID of server that is currently uploading, null if inProgress is 0. Default=null Length=36
oneTimeUpload	1 to perform a one time upload. Default=0
resultId	If successful, the GUID of the record added.

MCLI Add CisData

Add a new entry to CisData table.

/r or -r	Record to add. All record fields that do not have a Default are required.
userName	Username used to obtain the token Default=null Max Length=255

path	Path where the last problem report bundle was saved Default=null Max Length=255
password	Password of the user required to obtain the token. This is required only by Set and Add
resultId	If successful, the GUID of the record added.
MCLI Add Collection	
Add a Collection to a Site.	
/r or -r	Record to add. All record fields that do not have a Default are required.
collectionName	Name of the Collection. It is unique within the Site. Max Length=50
siteId	GUID of the Site that this Collection is a member of. It is not used with siteName. Length=36
siteName	Name of the Site that this Collection is a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
lastAutoAddDeviceNumber	The Device Number of the last Auto Added Device. Default=0
enabled	1 when Devices in the Collection can be booted, 0 otherwise. Default=1
autoAddPrefix	The string put before the Device Number for Auto Add. Default=null ASCII computer name characters no end digit Max Length=12
autoAddSuffix	The string put after the Device Number for Auto Add. Default=null ASCII computer name characters no begin digit Max Length=12
autoAddZeroFill	1 when zeros be placed before the Device Number up to the autoAddNumberLength for Auto Add, 0 otherwise. Default=1
autoAddNumberLength	The maximum length of the Device Number for Auto Add. This length plus the autoAddPrefix length plus the autoAddSuffix length must be less than 16. Required that $((lenautoAddPrefix+lenautoAddSuffix)+autoAddNumberLength) \leq 15$. Min=3, Max=9, Default=4
resultId	If successful, the GUID of the record added.

MCLI Add Device

Add a new Device to a collection.

/r or -r	Record to add. All record fields that do not have a Default are required.
deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
collectionId	GUID of the Collection this Device is to be a member of. It is not used with collectionName. Length=36
collectionName	Name of the Collection this Device is to be a member of. siteName or siteId must also be used.
siteId	GUID of the Site the collectionName is to be a member of. This or siteName is used with collectionName.

siteName	Name of the Site the collectionName is to be a member of. This or siteId is used with collectionName.
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
bootFrom	Device to boot from. Choices are 1 for vDisk, 2 for Hard Disk, and 3 for Floppy. This cannot be Set for a Device with Personal vDisk. Min=1, Max=3, Default=1
className	Used by Automatic Update feature to match new versions of Disks to a Device. This cannot be Set for a Device with Personal vDisk. Default="" Max Length=41
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
enabled	1 when it can be booted, 0 otherwise. This cannot be Set for a Device with Personal vDisk. Default=1
localDiskEnabled	If there is a local disk menu choice for the Device, this is 1. This cannot be Set for a Device with Personal vDisk. Default=0
authentication	Device log in authentication. Choices are 0 for none, 1 for User Name/Password, and 2 for Extern. This cannot be Set for a Device with Personal vDisk. Min=0, Max=2, Default=0
user	Name of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=20
password	Password of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=100
copyTemplate	1 if the Template Device for the collection, if it exists, should be used for the property settings of the added Device. Default=0
adTimestamp	The time the Active Directory machine account password was generated. Do not set this field, it is only set internally by PVS. Default=0
adSignature	The signature of the Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default=0
adPassword	The Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default="" ASCII Max Length=256
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device belongs to. Do not set this field, it

domainObjectSID	is only set internally by PVS. Default=null Max Length=255 The value of the objectSID AD attribute of the same name for the Device's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=186
domainControllerName	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
domainTimeCreated	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null
type	1 when it performs test of Disks, 2 when it performs maintenance on Disks, 3 when it has a Personal vDisk, 4 when it has a Personal vDisk and performs tests, 0 otherwise. Min=0, Max=2, Default=0
localWriteCacheDiskSize	The size in GB to format the Device cache file disk. If the value is 0, then the disk is not formatted. Min=0, Max=2048, Default=0
virtualHostingPoolId	GUID that uniquely identifies the Virtual Hosting Pool for a VM. This is needed when Adding a VM device. Default=null Length=36
hypVmId	Hypervisor VM ID for HCL Default=null Max Length=250
bdmBoot	Use PXE boot when set to 0, BDM boot when set to 1. Default is PXE Default=0
bdmType	Use PXE boot when set to 0, BDM (Bios) boot when set to 1 and BDM (Uefi) boot when set to 2. Default=0
bdmFormat	1 use VHD for BDMboot, 2 use ISO, 3 use USB. Default=0
bdmUpdated	Timestamp of the last BDM boot disk update. Default=null
bdmCreated	Timestamp when BDM device was created Default=null
xsPvsProxyUuid	UUID of XenServer PVS_proxy Default=null Length=36
enableXsProxy	Enable XenServerProxy when set to 1 Default=null
resultId	If successful, the GUID of the record added.

MCLI Add DeviceWithPersonalvDisk

Add a new Device with Personal vDisk to a collection.	
/r or -r	Record to add. All record fields that do not have a Default are required.
deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
collectionId	GUID of the Collection this Device with Personal vDisk is to be a member of. It is not used with collectionName. Length=36

collectionName	Name of the Collection this Device with Personal vDisk is to be a member of. siteName or siteId must also be used.
diskLocatorId	GUID of the Disk Locator to update with this Device.
siteId	GUID of the Site the collectionName is to be a member of. This or siteName is used with collectionName.
siteName	Name of the Site the collectionName is to be a member of. This or siteId is used with collectionName.
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX-XX. Uniquely identifies the Device with Personal vDisk. Length=17
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
adTimestamp	The time the Active Directory machine account password was generated. Do not set this field, it is only set internally by PVS. Default=0
adSignature	The signature of the Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default=0
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device with Personal vDisk belongs to. Do not set this field, it is only set internally by PVS. Default=null Max Length=255
domainObjectSID	The value of the objectSID AD attribute of the same name for the Device with Personal vDisk's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=186
domainControllerName	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
domainTimeCreated	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null
type	3 when it has a Personal vDisk, 4 when it has a Personal vDisk and performs tests. Min=3, Max=4, Default=3
pvdDriveLetter	Personal vDisk Drive letter. Range is F to Z. Default=null Max Length=1
localWriteCacheDiskSize	The size in GB to format the Device cache file disk. If the value is 0, then the disk is not formatted. Min=0, Max=2048, Default=0
bdmBoot	Use BDM instead of PXE boot when set to 1. Default=0

xdSiteId	GUID of the XenDesktop Site. Default=null Length=36
xdCatalogId	Integer identifier of the XenDesktop Catalog. Default=null
virtualHostingPoolId	GUID that uniquely identifies the Virtual Hosting Pool for a VM. This is needed when Adding a VM device. Default=null Length=36
enableXsProxy	Enable XenServerProxy when set to 1 Default=null
resultId	If successful, the GUID of the record added.

MCLI Add DiskLocator

Add a Disk Locator to a Site. The Disk file must already exist.	
/r or -r	Record to add. All record fields that do not have a Default are required.
diskLocatorName	Name of the Disk Locator File. It is unique within the Store. ASCII Max Length=52
siteId	GUID of the Site this DiskLocator is to be a member of. It is not used with siteName. Length=36
siteName	Name of the Site this DiskLocator is to be a member of. It is not used with siteId.
storeId	GUID of the Store that this Disk Locator is a member of. siteName or siteId must also be used. It is not used with storeName. Length=36
storeName	Name of the Store that this Disk Locator is a member of. siteName or siteId must also be used. It is not used with storeId.
description	User description. Default="" Max Length=250
menuText	Text that is displayed in the Boot Menu. If this field has no value, the name value is used. Default="" ASCII Max Length=64
serverId	GUID of the single Server that this Disk Locator is assigned to. It is not used with serverName. Default=null Length=36
serverName	Name of the single Server that this Disk Locator is assigned to. It is not used with serverId. Default=null
enabled	1 when this disk can be booted, 0 otherwise. Default=1
rebalanceEnabled	1 when this Server can automatically rebalance Devices, 0 otherwise. Default=0
rebalanceTriggerPercent	Percent over fair load that triggers a dynamic Device rebalance. Min=5, Max=5000, Default=25
subnetAffinity	Qualifier for subnet affinity when assigning a Server. 0=None, 1=Best Effort, 2=Fixed. Min=0, Max=2, Default=0
newDiskWriteCacheType	The writeCacheType that if a new Disk will be created, it will be set with. It is only used when a new Disk is being created. Value are: 0 (Private), (other values are standard image) 1 (Cache on Server), 3 (Cache in Device RAM), 4 (Cache on Device Hard Disk), 7 (Cache on Server, Persistent), or 9 (Cache

format	in Device RAM with Overflow on Hard Disk) Default=0
resultId	Format of the image when adding a DiskLocator for a vDisk that has never been added to the Farm. VHDX is the only format that requires this field. Values are: 0 (VHD) and 1 (VHDX). Default=0 If successful, the GUID of the record added.

MCLI Add DiskUpdateDevice

Add a new Device related to a Disk that can be updated.	
/r or -r	Record to add. All record fields that do not have a Default are required.
deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
virtualHostingPoolId	GUID of the Virtual Hosting Pool. It is not used with virtualHostingPoolName. Default=null Length=36
virtualHostingPoolName	Name of the Virtual Hosting Pool.
diskLocatorId	GUID of the Disk Locator to update with this Device.
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
adTimestamp	The time the Active Directory machine account password was generated. Do not set this field, it is only set internally by PVS. Default=0
adSignature	The signature of the Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default=0
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device belongs to. Do not set this field, it is only set internally by PVS. Default=null Max Length=255
domainObjectSID	The value of the objectSID AD attribute of the same name for the Device's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=186
domainControllerName	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
domainTimeCreated	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null

adPassword	The Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default="" Max Length=256
resultId	If successful, the GUID of the record added.

MCLI Add FarmView

Add a View to a Farm.
 /r or -r

farmViewName	Record to add. All record fields that do not have a Default are required.
description	name of the Farm View. Max Length=50
resultId	User description. Default="" Max Length=250 If successful, the GUID of the record added.

MCLI Add Server

Add a Server to a Site.
 /r or -r

serverName	Record to add. All record fields that do not have a Default are required.
siteId	Computer name with no spaces. ASCII computer name characters Max Length=21
siteName	GUID of the Site this Server is to be a member of. It is not used with siteName. Length=36
description	Name of the Site this Server is to be a member of. It is not used with siteId.
adMaxPasswordAge	User description. Default="" Max Length=250
licenseTimeout	Number of days before a password expires. Min=1, Max=30, Default=7
vDiskCreatePacing	Amount of seconds before a license times out. Min=15, Max=300, Default=30
firstPort	VDisk create time pacing in milliseconds. Min=0, Max=5, Default=0
lastPort	Number of the first UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6910
threadsPerPort	Number of the last UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6930
buffersPerThread	Number of worker threads per IO port. Required that (threadPerPort * numberPorts * numberIPs) <= 1000. Min=1, Max=60, Default=8
serverCacheTimeout	Number of buffers per worker thread. Min=1, Max=128, Default=24
ioBurstSize	Number of seconds to wait before considering another Server is down. Min=5, Max=60, Default=8
maxTransmissionUnits	Number of bytes read/writes can send in a burst of packets. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=4096, Max=61440, Default=32768
	Ethernet maximum transmission unit size for the protocol for use for Server and Device. Required that

```

ioBurstSize/ (maxTransmissionUnits-76) <=32.
Min=502, Max=16426, Default=1506
maxBootDevicesAllowed Maximum number of Devices allowed to boot
simultaneously. Min=1, Max=1000, Default=500
maxBootSeconds Maximum number of seconds for a Device to
boot. Min=10, Max=900, Default=60
bootPauseSeconds Number of seconds that a Device will pause
during login if its server busy. Min=1,
Max=60, Default=10
adMaxPasswordAgeEnabled Age the password, when set to 1. Default=0
eventLoggingEnabled Enable event logging, when set to 1.
Default=0
nonBlockingIoEnabled Use non-Blocking IO, when set to 1.
Default=1
ip One or more streaming ip addresses. If more
than one ip is included, the ip addresses
are comma delimited.
initialQueryConnectionPoolSize Initial size of database connection
pool for non-transactional queries. Min=1,
Max=1000, Default=50
initialTransactionConnectionPoolSize Initial size of database
connection pool for transactional queries.
Min=1, Max=1000, Default=50
maxQueryConnectionPoolSize Maximum size of database connection pool
for non-transactional queries. Min=1,
Max=32767, Default=1000
maxTransactionConnectionPoolSize Maximum size of database connection
pool for transactional queries. Min=1,
Max=32767, Default=1000
refreshInterval Interval, in number of seconds, the server
should wait before refreshing settings. If
set to 0, unused database connections are
never released. Min=0, Max=32767,
Default=300
unusedDbConnectionTimeout Interval, in number of seconds, a
connection should go unused before it is to
be released. Min=0, Max=32767, Default=300
busyDbConnectionRetryCount Number of times a failed database
connection will be retried. Min=0,
Max=32767, Default=2
busyDbConnectionRetryInterval Interval, in number of milliseconds,
the server should wait before retrying to
connect to a database. Min=0, Max=10000,
Default=25
localConcurrentIoLimit Maximum concurrent IO transactions it
performs for vDisks that are local. A value
of 0 disables the feature. Min=0, Max=128,
Default=4
remoteConcurrentIoLimit Maximum concurrent IO transactions it
performs for vDisks that are remote. A value
of 0 disables the feature. Min=0, Max=128,
Default=4
logLevel Level to perform logging at. Values are: 0
(None), 1 (Fatal), 2 (Error), 3 (Warning), 4
(Info), 5 (Debug), and 6 (Trace). Min=0,
Max=6, Default=4

```

logFileSizeMax	Maximum size log files can reach in Megabytes. Min=1, Max=50, Default=5
logFileBackupCopiesMax	Maximum number of log file backups. Min=1, Max=50, Default=4
powerRating	A strictly relative rating of this Server's capabilities when compared to other Servers in the Store(s) it belongs too; can be used to help tune load balancing. Min=0.1, Max=1000, Default=1
lastCeipUploadAttempt	Time that this server last attempted a CEIP upload. Default=null
lastBugReportAttempt	Time that this server last attempted to upload or generate a bug report bundle. Default=null
lastBugReportStatus	Status of the last bug report on this server. Default=null Max Length=250
lastBugReportResult	Status of the last bug report on this server. Default=null Max Length=4000
lastBugReportSummary	Summary of the last bug report on this server. Default=null Max Length=250
resultId	If successful, the GUID of the record added.

MCLI Add Site

Add a Site to the system.

/r or -r

siteName	Record to add. All record fields that do not have a Default are required.
description	Name of the Site. Max Length=50
inventoryFilePollingInterval	User description. Default="" Max Length=250
enableDiskUpdate	The number of seconds between polls for Disk changes in the Stores. Min=1, Max=600, Default=60
diskUpdateServerId	1 when Disk Updated is enabled for the Site, 0 otherwise. Default=0
diskUpdateServerName	GUID of the Disk Update Server for the Site. Not used with diskUpdateServerName. Default=null Length=36
makUser	Name of the Disk Update Server for the Site. Not used with diskUpdateServerId. Default=null
makPassword	User name used for MAK activation. Default=null Max Length=64
enableXsProxy	User password used for MAK activation. Default=null Max Length=64
virtualHostingPoolId	Enable XenServerProxy when set to 1
virtualHostingPoolName	Default=null
xsPvsSiteUuid	GUID of the VirtualHostingPool object.
resultId	Name of the VirtualHostingPool object.
	GUID of the XenServer PVS Site.
	If successful, the GUID of the record added.

MCLI Add SiteView

Add a View to a Site.

/r or -r

siteViewName

siteViewName	Record to add. All record fields that do not have a Default are required.
	Name of the Site View. Max Length=50

siteId	GUID of the Site this View is to be a member of. It is not used with siteName. Length=36
siteName	Name of the Site this View is to be a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
resultId	If successful, the GUID of the record added.

MCLI Add Store

Add a Store to the system.
 /r or -r

storeName	Record to add. All record fields that do not have a Default are required.
siteId	Name of the Store. Max Length=50
siteName	GUID of the Site where Administrators of that Site can change this Store. Not used for Farm Stores. siteName can be used instead. Default=null Length=36
description	Name of the Site where Administrators of that Site can change this Store. Not used for Farm Stores. siteId can be used instead. Default=null
path	User description. Default="" Max Length=250
cachePath	Default directory path that the Servers use to access this Store. Max Length=255
resultId	Default Cache path(s) that the Servers use with this Store. It is an ordered comma-delimited list. If none are specified the caches will be placed in the WriteCache subdirectory of the Store path. Default=None If successful, the GUID of the record added.

MCLI Add UpdateTask

Add a new Update Task for the Site.

/r or -r	Record to add. All record fields that do not have a Default are required.
updateTaskName	Name of the Update Task. It is unique within the Site. Max Length=50
siteId	GUID of the Site that this Update Task is a member of. It is not used with siteName. Length=36
siteName	Name of the Site that this Update Task is a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
enabled	1 when it will be processed, 0 otherwise. Default=1
hour	The hour of the day to perform the task. Min=0, Max=23, Default=0
minute	The minute of the hour to perform the task. Min=0, Max=59, Default=0
recurrence	The update will reoccur on this schedule. 0 = None, 1 = Daily, 2 = Every Weekday, 3 = Weekly, 4 = Monthly Date, 5 = Monthly Type. Min=0, Max=5, Default=0
dayMask	Days selected values. 1 = Monday, 2 = Tuesday, 4 = Wednesday, 8 = Thursday, 16 = Friday, 32 = Saturday, 64 = Sunday, 128 =

date	Day. Default=0. This is used with Weekly and Monthly Type recurrence. Min=1, Max=255, Default=4 Comma delimited days of the month. Numbers from 1-31 are the only valid values. This is used with Monthly Date recurrence. Default="" Max Length=83
monthlyOffset	When to happen monthly. 0 = None, 1 = First, 2 = Second, 3 = Third, 4 = Forth, 5 = Last. This is used with Monthly Type recurrence. Min=0, Max=5, Default=3
esdType	Esd to use. Valid values are SCCM or WSUS. If no value, a custom script is run on the client. Default=null Max Length=50
preUpdateScript	Script file to run before the update starts. Default=null Max Length=255
preVmScript	Script file to run before the VM is loaded. Default=null Max Length=255
postUpdateScript	Script file to run after the update finishes. Default=null Max Length=255
postVmScript	Script file to run after the VM is unloaded. Default=null Max Length=255
domain	Domain to add the Disk Update Device(s) to. If not included, the first Domain Controller found on the Server is used. Default=null Max Length=255
organizationUnit	Organizational Unit to add the Disk Update Device(s) to. This parameter is optional. If it is not specified, the device is added to the built in Computers container. Child OU's should be delimited with forward slashes, e.g. "ParentOU/ChildOU". Special characters in an OU name, such as "'", '#', '+', ',', ';', '>', '=', must be escaped with a backslash. For example, an OU called "commaIn,TheMiddle" must be specified as "commaIn\,TheMiddle". The old syntax of delimiting child OU's with a comma is still supported, but deprecated. Note that in this case, the child OU comes first, e.g. "ChildOU,ParentOU". Default=null Max Length=255
postUpdateApprove	Access to place the version in after the update has occurred. 0 = Production, 1 = Test, 2 = Maintenance. Min=0, Max=2, Default=0
resultId	If successful, the GUID of the record added.

MCLI Add VirtualHostingPool

Add a new Virtual Hosting Pool for the Site.

/r or -r

virtualHostingPoolName

Record to add. All record fields that do not have a Default are required.

Name of the Virtual Hosting Pool. It is unique within the Site. Max Length=50

siteId	GUID of the Site that this Virtual Hosting Pool is a member of. It is not used with siteName. Length=36
siteName	Name of the Site that this Virtual Hosting Pool is a member of. It is not used with siteId.
type	Type of the Virtual Hosting Pool. 0 = Citrix XenServer, 1 = Microsoft SCVMM/Hyper-V, 2 = VMWare vSphere/ESX. Min=0, Max=3, Default=0
description	User description. Default="" Max Length=250
server	Name or IP of the Host Server. Max Length=255
port	Port of the Host Server. Min=80, Max=65534, Default=80
datacenter	Datacenter of the Virtual Hosting Pool. Default="" Max Length=250
updateLimit	Number of updates at the same time. Min=2, Max=1000, Default=1000
updateTimeout	Timeout for updates. Min=2, Max=240, Default=60
shutdownTimeout	Timeout for shutdown. Min=2, Max=30, Default=10
userName	Name to use when logging into the Server.
password	Password to use when logging into the Server.
xdHostingUnitUuid	UUID of XenDesktop Hosting Unit Default=null Length=36
prepopulateEnabled	Enable prepopulate when set to 1 Default=0
xsPvsSiteUuid	UUID of XenServer PVS_site Default=null Length=36
platformVersion	Hypervisor Host Version Default=null Max Length=250
xdHcHypervisorConnectionName	Hypervisor Connection Name for HCL Connection Details object Default=null Max Length=250
xdHcHypervisorConnectionUid	Hypervisor Connection Uid for HCL Connection Details object Default=null Max Length=250
xdHcRevision	Revision for HCL Connection Details object Default=null Max Length=250
xdHcCustomProperties	Custom Properties for HCL Connection Details object Default=null Max Length=250
xdHcSslThumbprints	Ssl Thumbprints for HCL Connection Details object Default=null Max Length=250
disableHostXsProxy	True to disable PVS-Accelerator Default=null
resultId	If successful, the GUID of the record added.

MCLI Delete

MCLI Delete commandName[/p name=value[name2=value2]]

MCLI Delete AuthGroup

Delete an AuthGroup Active Directory or Windows Group name.
 /p or -p
 One of these required
 authGroupId
 authGroupName

Parameters needed for this Delete.

GUID of the AuthGroup to Delete.
 Name of the AuthGroup to Delete.

Optional force	When set to 1, the AuthGroup will be Deleted even if being used, otherwise an error is returned if being used.
-------------------	--

MCLI Delete Collection

Delete a Collection.

/p or -p	Parameters needed for this Delete.
This required	
collectionId	GUID of the Collection to Delete.
or this required & resolution	
collectionName	Name of the Collection to Delete.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Delete Device

Delete one or more Devices.

/p or -p	Parameters needed for this Delete.
One of these required	
deviceId	GUID of the Device to Delete.
deviceName	Name of the Device to Delete.
deviceMac	MAC of the Device to Delete.
collectionId	GUID of the Collection to delete all Devices.
or this required & resolution	
collectionName	Name of the Collection to delete all Devices.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Delete DeviceDiskCacheFile

Delete the Disk cache files for a Device.

/p or -p	Parameters needed for this Delete.
One of these required	
deviceId	GUID of the Device to Delete Disk cache files.
deviceName	Name of the Device to Delete Disk cache files.
deviceMac	MAC of the Device to Delete Disk cache files.
This required	
diskLocatorId	GUID of the Disk Locator to Delete Disk cache files.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Delete Disk cache files.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.

storeName Name of the Store that is needed when a diskLocatorName is used.

MCLI Delete DiskLocator

Delete one or more Disk Locators.

/p or -p	Parameters needed for this Delete.
This required	
diskLocatorId	GUID of the Disk Locator to Delete.
or one of these required & resolutions	
diskLocatorName	Name of the Disk Locator File to Delete.
storeId	GUID of the Store to delete all DiskLocators.
storeName	Name of the Store to delete all DiskLocators.
Optional	
deleteDiskFile	1 if the Disk File should be deleted, 0 otherwise. Default=0
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Delete DiskUpdateDevice

Delete a Disk Update Device.

/p or -p	Parameters needed for this Delete.
One of these required	
deviceId	GUID of the Disk Update Device to Delete.
deviceName	Name of the Disk Update Device to Delete.
deviceMac	MAC of the Disk Update Device to Delete.

MCLI Delete DiskVersion

Remove the latest Disk version or no longer needed version if no Devices are currently booted from that version.

/p or -p	Parameters needed for this Delete.
This required	
diskLocatorId	GUID of the Disk Locator to Delete the Version from.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Delete the Version from.
Optional	
version	Specifies the version that should be deleted. Used when deleting versions that are no longer needed because of a Merge.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.

storeName	Name of the Store that is needed when a diskLocatorName is used.
-----------	--

MCLI Delete FarmView

Delete a View from the Farm.

/p or -p
One of these required
farmViewId
farmViewName

Parameters needed for this Delete.

GUID of the Farm View to Delete.
Name of the Farm View to Delete.

MCLI Delete Server

Delete a Server.

/p or -p
One of these required
serverId
serverName

Parameters needed for this Delete.

GUID of the Server to Delete.
Name of the Server to Delete.

MCLI Delete ServerStore

Delete the connection from a Server to a Store.

/p or -p
One of these required
serverId
serverName

One of these required
storeId
storeName

Parameters needed for this Delete.

GUID of a Server that uses the path to get to the Store.
Name of a Server that uses the path to get to the Store.

GUID of the Store.
Name of the Store.

MCLI Delete Site

Delete a Site.

/p or -p
One of these required
siteId
siteName

Parameters needed for this Delete.

GUID of the Site to Delete.
Name of the Site to Delete.

MCLI Delete SiteView

Delete a View from a Site.

/p or -p
This required
siteViewId
or this required & resolution
siteViewName
One of these resolutions when needed
siteId
siteName

Parameters needed for this Delete.

GUID of the Site View to Delete.
Name of the Site View to Delete.
GUID of the Site.
Name of the Site.

MCLI Delete Store

Delete a Store.

/p or -p
One of these required
storeId
storeName

Parameters needed for this Delete.

GUID of the Store to Delete.
Name of the Store to Delete.

MCLI Delete UpdateTask

Delete an Update Task from a Site.

/p or -p	Parameters needed for this Delete.
This required	
updateTaskId	GUID of the Update Task to Delete.
or this required & resolution	
updateTaskName	Name of the Update Task to Delete.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Delete VirtualHostingPool

Delete a Virtual Hosting Pool from a Site.

/p or -p	Parameters needed for this Delete.
This required	
virtualHostingPoolId	GUID of the Virtual Hosting Pool to Delete.
or this required & resolution	
virtualHostingPoolName	Name of the Virtual Hosting Pool to Delete.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Get

MCLI Get commandName[/p name=value[name2=value2]] [/s field[-]] [/f field[field2]]

MCLI Get AdDomains

Get all of the available Active Directory domains.

/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the Domain.
records	If successful, records retrieved.

MCLI Get AuditActionParameters

Get the Parameters of an Audit Action.

/p or -p	Parameters needed for the Get.
This required	
auditActionId	GUID of the Audit Action to Get Parameters for.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
auditParameterName	Name of the parameter. Max Length=50
value	Value of the parameter. Max Length=1000
records	If successful, records retrieved.

MCLI Get AuditActionProperties

Get the Properties of an Audit Action.

/p or -p	Parameters needed for the Get.
This required	
auditActionId	GUID of the Audit Action to Get Properties for.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.

auditPropertyName	Name of the property. Max Length=50
oldValue	Previous value of the Property. Default=null Max Length=1000
newValue	New value of the Property. Default=null Max Length=1000
records	If successful, records retrieved.

MCLI Get AuditActionSibling

Get the Sibling of an Audit Action. It is the 2nd object involved with the action.

/p or -p	Parameters needed for the Get.
This required	
auditActionId	GUID of the Audit Action to Get Sibling for.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
auditActionId	GUID of the action. Length=36
type	Type of object that action was performed on. Values are: 1 (AuthGroup), 2 (Collection), 3 (Device), 4 (Disk), 5 (DiskLocator), 6 (Farm), 7 (FarmView), 8 (Server), 9 (Site), 10 (SiteView), 11 (Store), 12 (System), and 13 (UserGroup)
objectId	GUID of the object of the action. Length=36
objectName	Name of the object of the action. Max Length=1000
path	Path of the object of the action. An example is Site\Collection for a Device. Default=null Max Length=101
siteId	GUID of the Site for the object of the action. Empty when not valid. Default=null Length=36
subId	GUID of the Collection or Store of the action. Empty when not valid. Default=null Length=36
records	If successful, records retrieved.

MCLI Get AuditTrail

Get the Audit Trail actions for a Farm, Site, Server, DiskLocator, Collection, Device, User Group, Site View, Farm View or Store. All Audit Trail actions are returned if no parameters are passed. The result can be filtered by parent, user\domain and date range.

/p or -p	Parameters needed for the Get.
One of these optional	
auditActionId	GUID of the Audit Action to Get.
parentId	Parent auditActionId of the records to retrieve. If no parameters are included, only records with no parent are returned.
rootId	Root auditActionId of the records to retrieve. All of the actions caused by the root action are returned. If no parameters are included, only records with no root are returned.
siteId	GUID of the Site to get the Audit Trail for.
siteName	Name of the Site to get the Audit Trail for.

collectionId	GUID of the Collection to get the Audit Trail for.
siteViewId	GUID of the Site View to get the Audit Trail for.
farmViewId	GUID of the Farm View to get the Audit Trail for.
farmViewName	Name of the Farm View to get the Audit Trail for.
serverId	GUID of the Server to get the Audit Trail for.
serverName	Name of the Server to get the Audit Trail for.
deviceId	GUID of the Device to get the Audit Trail for.
deviceName	Name of the Device to get the Audit Trail for.
deviceMac	MAC of the Device to get the Audit Trail for.
storeId	GUID of the Store to get the Audit Trail for.
storeName	Name of the Store to get the Audit Trail for.
diskLocatorId	GUID of the DiskLocator to get the Audit Trail for.
or one of these optional & resolutions	
collectionName	Name of the Collection to get the Audit Trail for.
siteViewName	Name of the Site View to get the Audit Trail for.
diskLocatorName	Name of the DiskLocator to get the Audit Trail for.
Optional	
userName	User that performed the action.
domain	Domain of the user that performed the action.
beginDate	Date of the first actions to get. If not included, all actions until the endDate are returned. If neither this or the endDate are included, then only actions that occurred in the last week are returned. Format is: yyyy/mm/dd
endDate	Date of the last actions to get. If not included, all actions from the beginDate until now are returned. If neither this or the beginDate are included, then only actions that occurred in the last week are returned. Format is: yyyy/mm/dd
type	Comma delimited list of types to get. Values are listed in the type field description.
action	Comma delimited list of actions to get. Values are listed in the action field description.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
auditActionId	GUID of the action. Length=36
time	Date/Time the action occurred down to the millisecond. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=getdate
userName	User that performed the action. Max Length=255
domain	Domain of the user that performed the action. Max Length=255
type	Type of object that action was performed on. Values are: 0 (Many), 1 (AuthGroup), 2 (Collection), 3 (Device), 4 (Disk), 5 (DiskLocator), 6 (Farm), 7 (FarmView), 8 (Server), 9 (Site), 10 (SiteView), 11 (Store), 12 (System), and 13 (UserGroup)
action	Name of the action taken. This is a number that is converted to a string for display. Values are: 1 (AddAuthGroup), 2 (AddCollection), 3 (AddDevice), 4 (AddDiskLocator), 5 (AddFarmView), 6 (AddServer), 7 (AddSite), 8 (AddSiteView), 9 (AddStore), 10 (AddUserGroup), 11 (AddVirtualHostingPool), 12 (AddUpdateTask), 13 (AddDiskUpdateDevice), 1001 (DeleteAuthGroup), 1002 (DeleteCollection), 1003 (DeleteDevice), 1004 (DeleteDeviceDiskCacheFile), 1005 (DeleteDiskLocator), 1006 (DeleteFarmView), 1007 (DeleteServer), 1008 (DeleteServerStore), 1009 (DeleteSite), 1010 (DeleteSiteView), 1011 (DeleteStore), 1012 (DeleteUserGroup), 1013 (DeleteVirtualHostingPool), 1014 (DeleteUpdateTask), 1015 (DeleteDiskUpdateDevice), 1016 (DeleteDiskVersion), 2001 (RunAddDeviceToDomain), 2002 (RunApplyAutoUpdate), 2003 (RunApplyIncrementalUpdate), 2004 (RunArchiveAuditTrail), 2005 (RunAssignAuthGroup), 2006 (RunAssignDevice), 2007 (RunAssignDiskLocator), 2008 (RunAssignServer), 2009 (RunWithReturnBoot), 2010 (RunCopyPasteDevice), 2011 (RunCopyPasteDisk), 2012 (RunCopyPasteServer), 2013 (Run.CreateDirectory), 2014 (RunCreateDiskCancel), 2015 (RunDisableCollection), 2016 (RunDisableDevice), 2017 (RunDisableDeviceDiskLocator), 2018

(RunDisableDiskLocator), 2019
(RunDisableUserGroup), 2020
(RunDisableUserGroupDiskLocator), 2021
(RunWithReturnDisplayMessage), 2022
(RunEnableCollection), 2023
(RunEnableDevice), 2024
(RunEnableDeviceDiskLocator), 2025
(RunEnableDiskLocator), 2026
(RunEnableUserGroup), 2027
(RunEnableUserGroupDiskLocator), 2028
(RunExportOemLicenses), 2029
(RunImportDatabase), 2030
(RunImportDevices), 2031
(RunImportOemLicenses), 2032 (RunMarkDown),
2033 (RunWithReturnReboot), 2034
(RunRemoveAuthGroup), 2035
(RunRemoveDevice), 2036
(RunRemoveDeviceFromDomain), 2037
(RunRemoveDirectory), 2038
(RunRemoveDiskLocator), 2039
(RunResetDeviceForDomain), 2040
(RunResetDatabaseConnection), 2041
(RunRestartStreamingService), 2042
(RunWithReturnShutdown), 2043
(RunStartStreamingService), 2044
(RunStopStreamingService), 2045
(RunUnlockAllDisk), 2046 (RunUnlockDisk),
2047 (RunServerStoreVolumeAccess), 2048
(RunServerStoreVolumeMode), 2049
(RunMergeDisk), 2050 (RunRevertDiskVersion),
2051 (RunPromoteDiskVersion), 2052
(RunCancelDiskMaintenance), 2053
(RunActivateDevice), 2054
(RunAddDiskVersion), 2055 (RunExportDisk),
2056 (RunAssignDisk), 2057 (RunRemoveDisk),
2058 (RunDiskUpdateStart), 2059
(RunDiskUpdateCancel), 2060
(RunSetOverrideVersion), 2061
(RunCancelTask), 2062 (RunClearTask), 2063
(RunForceInventory), 2064 RunUpdateBDM, 2065
(RunStartDeviceDiskTempVersionMode), 2066
(RunStopDeviceDiskTempVersionMode), 3001
(RunWithReturnCreateDisk), 3002
(RunWithReturnCreateDiskStatus), 3003
(RunWithReturnMapDisk), 3004
(RunWithReturnRebalanceDevices), 3005
(RunWithReturnCreateMaintenanceVersion),
3006 (RunWithReturnImportDisk), 4001
(RunByteArrayInputImportDevices), 4002
(RunByteArrayInputImportOemLicenses), 5001
(RunByteArrayOutputArchiveAuditTrail), 5002
(RunByteArrayOutputExportOemLicenses), 6001
(SetAuthGroup), 6002 (SetCollection), 6003
(SetDevice), 6004 (SetDisk), 6005
(SetDiskLocator), 6006 (SetFarm), 6007
(SetFarmView), 6008 (SetServer), 6009
(SetServerBiosBootstrap), 6010

```

(SetServerBootstrap), 6011 (SetServerStore),
6012 (SetSite), 6013 (SetSiteView), 6014
(SetStore), 6015 (SetUserGroup), 6016
SetVirtualHostingPool, 6017 SetUpdateTask,
6018 SetDiskUpdateDevice, 7001
(SetListDeviceBootstraps), 7002
(SetListDeviceBootstrapsDelete), 7003
(SetListDeviceBootstrapsAdd), 7004
(SetListDeviceCustomProperty), 7005
(SetListDeviceCustomPropertyDelete), 7006
(SetListDeviceCustomPropertyAdd), 7007
(SetListDeviceDiskPrinters), 7008
(SetListDeviceDiskPrintersDelete), 7009
(SetListDeviceDiskPrintersAdd), 7010
(SetListDevicePersonality), 7011
(SetListDevicePersonalityDelete), 7012
(SetListDevicePersonalityAdd), 7013
(SetListDiskLocatorCustomProperty), 7014
(SetListDiskLocatorCustomPropertyDelete),
7015 (SetListDiskLocatorCustomPropertyAdd),
7016 (SetListServerCustomProperty), 7017
(SetListServerCustomPropertyDelete), 7018
(SetListServerCustomPropertyAdd), 7019
(SetListUserGroupCustomProperty), 7020
(SetListUserGroupCustomPropertyDelete), and
7021 (SetListUserGroupCustomPropertyAdd)
GUID of the object of the action.
Default=null Length=36
Name of the object of the action.
Default=null Max Length=1000
Path of the object of the action. An example
is Site\Collection for a Device.
Default=null Max Length=101
GUID of the Site for the object of the
action. Empty when not valid. Default=null
Length=36
GUID of the Collection or Store of the
action. Empty when not valid. Default=null
Length=36
GUID of the parent action (one that
triggered this action) if one exists. Empty
when not valid. Default=null Length=36
GUID of the root action (one that triggered
this group of actions) if one exists. Empty
when not valid. Default=null Length=36
An or'ed value that indicates if there are
any details for this action. A value of 15
indicates that there are Children, Sibling,
Parameters and Properties for the action.
Values are: 0 (None), 1 (Children), 2
(Sibling), 4 (Parameters), and 8
(Properties) Default=0
If successful, records retrieved.

```

MCLI Get AuthGroup

MCLI Get AuthGroupUsage

Get the items that are authorized for an AuthGroup.

One of these required

authGroupId

authGroupName

/f or -f

GUID of the AuthGroup to Get all items that are authorized for it.
Name of the AuthGroup to Get all items that are authorized for it.
List of fields to retrieve, if not included, all fields are retrieved.

id	GUID of the item. The item can be a Farm, Site or Collection. It will be empty for Farm.
name	Name of the item. The item can be a Farm, Site or Collection.
role	Role of the AuthGroup for the item. 100 is Farm Administrator, 200 is Site Administrator, 300 is Collection Administrator, and 400 is Collection Operator. Default=999
records	If successful, records retrieved.

MCLI Get CeipData

Get the CEIP configuration	
/p or -p	Parameters needed for the Get.
Optional	
uuid	CEIP UUID of this Farm. This is optional since there is only one.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
enabled	1 if CEIP is enabled, otherwise 0. Min=0, Max=1
uuid	CEIP UUID. Length=36
nextUpload	Date and time next CEIP upload is due if enabled is 1. Default=null
inProgress	1 if an upload is currently in progress, otherwise 0. Default=0
serverId	ID of server that is currently uploading, null if inProgress is 0. Default=null
Length=36	Length=36
oneTimeUpload	1 to perform a one time upload. Default=0
records	If successful, records retrieved.

MCLI Get CisData

Get the CIS configuration	
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
cisDataId	CIS UUID Length=36
userName	Username used to obtain the token Default=null Max Length=255
uploadToken	Token for uploading bundles to CIS Default=null Max Length=10
path	Path where the last problem report bundle was saved Default=null Max Length=255
password	Password of the user required to obtain the token. This is required only by Set and Add
records	If successful, records retrieved.

MCLI Get Collection

Get the fields for a Collection or all Collections in a Site or Farm. All Collections are returned if no parameters are passed.	
/p or -p	Parameters needed for the Get.
One of these optional	
collectionId	GUID of the Collection to Get.
siteId	GUID of the Site to Get all Collections for.

siteName	Name of the Site to Get all Collections for.
or this optional & resolution	
collectionName	Name of the Collection to Get.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
collectionName	Name of the Collection. It is unique within the Site. Max Length=50
description	User description. Default="" Max Length=250
deviceCount	Read-only count of Devices in this Collection. Default=0
deviceWithPVDCount	Read-only count of Devices with Personal vDisk in this Collection. Default=0
activeDeviceCount	Read-only count of active Devices in this Collection. Default=0
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
collectionId	Read-only GUID that uniquely identifies this Collection. Length=36
collectionName	Name of the Collection. It is unique within the Site. Max Length=50
siteId	GUID of the Site that this Collection is a member of. It is not used with siteName. Length=36
siteName	Name of the Site that this Collection is a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
templateDeviceId	GUID of a Device in the Collection whose settings are used for initial values of new Devices. Not used with templateDeviceName. Default=null Length=36
templateDeviceName	Name of a Device in the Collection whose settings are used for initial values of new Devices. Not used with templateDeviceId. Default=null
lastAutoAddDeviceNumber	The Device Number of the last Auto Added Device. Default=0
enabled	1 when Devices in the Collection can be booted, 0 otherwise. Default=1
deviceCount	Read-only count of Devices in this Collection. Default=0
deviceWithPVDCount	Read-only count of Devices with Personal vDisk in this Collection. Default=0
activeDeviceCount	Read-only count of active Devices in this Collection. Default=0
makActivateNeededCount	Read-only count of active Devices that need MAK activation in this Collection. Default=0
autoAddPrefix	The string put before the Device Number for Auto Add. Default=null ASCII computer name characters no end digit Max Length=12
autoAddSuffix	The string put after the Device Number for Auto Add. Default=null ASCII computer name characters no begin digit Max Length=12

autoAddZeroFill	1 when zeros be placed before the Device Number up to the autoAddNumberLength for Auto Add, 0 otherwise. Default=1
autoAddNumberLength	The maximum length of the Device Number for Auto Add. This length plus the autoAddPrefix length plus the autoAddSuffix length must be less than 16. Required that $((lenautoAddPrefix+lenautoAddSuffix)+autoAddNumberLength) \leq 15$. Min=3, Max=9, Default=4
role	Read-only Role of the user for this item. 100 is Farm Administrator, 200 is Site Administrator, 300 is Collection Administrator, and 400 is Collection Operator. Default=999
records	If successful, records retrieved.

MCLI Get CommandDescription

Return one or more commands with description.	
/p or -p	Parameters needed for the Get.
This required	
Action	Action to get commands with description for.
Optional	
Type	Command Type of the Action to get a description for.
ObjectType	Object Type to get command descriptions for. Valid Object Types are: Many, AuthGroup, Collection, Device, Disk, DiskLocator, Farm, FarmView, Server, Site, SiteView, Store, and System.
IType	Interface Type to get command descriptions for. Values are: 0 (Mcli), 1 (PowerShell), 2 (SoapServer). Default=0
Culture	Optional culture to use for the command descriptions returned.
records	If successful, records retrieved.

MCLI Get CommandFields

Return one record with fields and descriptions.	
/p or -p	Parameters needed for the Get.
This required	
Action	Action to get fields.
This required	
Type	Type of the Action to get fields.
Optional	
Culture	Optional culture to use for the field descriptions returned.
records	If successful, records retrieved.

MCLI Get CommandParameters

Return records with parameter type, parameters and descriptions. Parameter types that maybe returned include: Optional, RequiredSingle, OptionalSingle, RequiredSingleAmbiguous, OptionalSingleAmbiguous, and Resolution.	
/p or -p	Parameters needed for the Get.
This required	

Action	Action to get parameters.
This required	
Type	Type of the Action to get parameters.
Optional	
Culture	Optional culture to use for the parameter descriptions returned.
records	If successful, records retrieved.

MCLI Get CommandSortFields

Return one record with sort fields and descriptions.	
/p or -p	Parameters needed for the Get.
This required	
Action	Action to get sort fields.
This required	
Type	Type of the Action to get sort fields.
Optional	
Culture	Optional culture to use for the sort field descriptions returned.
records	If successful, records retrieved.

MCLI Get CommandStandardParameters

Return one record with standard parameter types and descriptions. Parameter types that maybe returned include: parameters, fields, record, records, sortField, resultId, rv, startPosition, maxRecords, totalCount, dataIn, dataOut, and commands.	
/p or -p	Parameters needed for the Get.
This required	
Action	Action to get standard parameter types and descriptions.
This required	
Type	Type of the Action to get standard parameter types and descriptions.
Optional	
Culture	Optional culture to use for the standard parameter descriptions returned.
records	If successful, records retrieved.

MCLI Get Device

Get the fields for a Device, all Devices in a Collection, Site, Farm View, or Farm. All Devices are returned if no parameters are passed.	
/p or -p	Parameters needed for the Get.
One of these optional	
deviceId	GUID of the Device to Get.
deviceName	Name of Device to Get.
deviceMac	MAC of the Device to Get.
collectionId	GUID of the Collection to Get all Devices for.
serverId	GUID of the Server to Get all Devices for.
serverName	Name of the Server to Get all Devices for.
diskLocatorId	GUID of the DiskLocator to Get all Devices for.
siteViewId	GUID of the Site View to Get all Devices for.
siteId	GUID of the Site.
siteName	Name of the Site.

farmViewId	GUID of the Farm View to Get all Devices for.
farmViewName	Name of the Farm View to Get all Devices for.
bdmBoot	Include only the BDM Devices when set to 1. PXE devices if set to 0. If not included, all Devices are returned.
deviceIdList	Comma delimited list of GUIDs of the Devices to Get. Maximum length is 8000 characters.
deviceNameList	Comma delimited list of Names of the Devices to Get. Maximum length is 8000 characters.
deviceMacList	Comma delimited list of MACs of the Devices to Get. Maximum length is 8000 characters.
or one of these optional & resolutions	
collectionName	Name of the Collection to Get all Devices for.
diskLocatorName	Name of the DiskLocator to Get all Devices for.
siteViewName	Name of the Site View to Get all Devices for.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
bootFrom	Device to boot from. Choices are 1 for vDisk, 2 for Hard Disk, and 3 for Floppy. This cannot be Set for a Device with Personal vDisk. Min=1, Max=3, Default=1
className	Used by Automatic Update feature to match new versions of Disks to a Device. This cannot be Set for a Device with Personal vDisk. Default="" Max Length=41
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
deviceId	Read-only GUID that uniquely identifies this Device. Length=36
deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
collectionId	GUID of the Collection this Device is to be a member of. It is not used with collectionName. Length=36

collectionName	Name of the Collection this Device is to be a member of. siteName or siteId must also be used.
siteId	GUID of the Site the collectionName is to be a member of. This or siteName is used with collectionName.
siteName	Name of the Site the collectionName is to be a member of. This or siteId is used with collectionName.
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
bootFrom	Device to boot from. Choices are 1 for vDisk, 2 for Hard Disk, and 3 for Floppy. This cannot be Set for a Device with Personal vDisk. Min=1, Max=3, Default=1
className	Used by Automatic Update feature to match new versions of Disks to a Device. This cannot be Set for a Device with Personal vDisk. Default="" Max Length=41
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
enabled	1 when it can be booted, 0 otherwise. This cannot be Set for a Device with Personal vDisk. Default=1
localDiskEnabled	If there is a local disk menu choice for the Device, this is 1. This cannot be Set for a Device with Personal vDisk. Default=0
role	Read-only Role of the user for this item. 100 is Farm Administrator, 200 is Site Administrator, 300 is Collection Administrator, and 400 is Collection Operator. Default=999
authentication	Device log in authentication. Choices are 0 for none, 1 for User Name/Password, and 2 for Extern. This cannot be Set for a Device with Personal vDisk. Min=0, Max=2, Default=0
user	Name of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=20
password	Password of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=100
active	1 if the Device is currently active, 0 otherwise. Default=0
template	1 if the Device is the template in its Collection, 0 otherwise. Default=0
adTimestamp	The time the Active Directory machine account password was generated. Do not set this field, it is only set internally by PVS. Default=0
adSignature	The signature of the Active Directory machine account password. Do not set this

adPassword	field, it is only set internally by PVS. Default=0
logLevel	The Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default="" ASCII Max Length=256 Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device belongs to. Do not set this field, it is only set internally by PVS. Default=null Max Length=255
domainObjectSID	The value of the objectSID AD attribute of the same name for the Device's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=186
domainControllerName	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
domainTimeCreated	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null
type	1 when it performs test of Disks, 2 when it performs maintenance on Disks, 3 when it has a Personal vDisk, 4 when it has a Personal vDisk and performs tests, 0 otherwise. Min=0, Max=4, Default=0
pvdDriveLetter	Read-only Personal vDisk Drive letter. Range is E to U and W to Z. Default=null Max Length=1
localWriteCacheDiskSize	The size in GB to format the Device cache file disk. If the value is 0, then the disk is not formatted. Min=0, Max=2048, Default=0
virtualHostingPoolId	GUID that uniquely identifies the Virtual Hosting Pool for a VM. This is needed when Adding a VM device. Default=null Length=36
hypVmId	Hypervisor VM ID for HCL Default=null Max Length=250
temporaryVersionSet	Read-only 1 when temporary version is set. Default=0
bdmBoot	Use PXE boot when set to 0, BDM boot when set to 1. Default is PXE Default=0
bdmType	Use PXE boot when set to 0, BDM (Bios) boot when set to 1 and BDM (Uefi) boot when set to 2. Default=0
bdmFormat	1 use VHD for BDMboot, 2 use ISO, 3 use USB. Default=0
bdmUpdated	Timestamp of the last BDM boot disk update. Default=null
bdmCreated	Timestamp when BDM device was created Default=null

xsPvsProxyUuid	UUID of XenServer PVS_proxy Default=null Length=36
records	If successful, records retrieved.
MCLI Get DeviceBootstraps	
Get all Bootstrap files for a Device, and the menuText for each.	
/p or -p	Parameters needed for the Get.
One of these required	
deviceId	GUID of the Device.
deviceName	Name of the Device.
deviceMac	MAC of the Device.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
bootstrap	Name of the bootstrap file. Max Length=259
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
bootstrap	Name of the bootstrap file. Max Length=259
menuText	Text that is displayed in the Boot Menu. If this field has no value, the bootstrap value is used. Default="" ASCII Max Length=64
records	If successful, records retrieved.

MCLI Get DeviceCustomProperty

Get the Device Custom Property names and values.	
/p or -p	Parameters needed for the Get.
One of these required	
deviceId	GUID of the Device.
deviceName	Name of the Device.
deviceMac	MAC of the Device.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
name	Name of the Device custom property. Max Length=250
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the Device custom property. Max Length=250
value	Value of the Device custom property. Max Length=1000
records	If successful, records retrieved.

MCLI Get DeviceDiskPrinters

Get all non-disabled Printers for a Device/Disk, and the setting for each.	
/p or -p	Parameters needed for the Get.
One of these required	
deviceId	GUID of the Device.
deviceName	Name of the Device.
deviceMac	MAC of the Device.
This required	
diskLocatorId	GUID of the Disk Locator.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File.
One of these resolutions when needed	

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
name	Name of the Printer. Must come from the list of Printers available on the Disk.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the Printer. Must come from the list of Printers available on the Disk.
state	Valid states are 1 (enabled network), 2 (enabled local), or 3 (default). 0 (disabled) can be used when setting a Printer that used to be 1 or 2 to 0. The list of all Printers available come from the Disk. Min=0, Max=3
records	If successful, records retrieved.

MCLI Get DeviceDiskTempVersion

Get Temporary Disk Version information for a Device, DiskLocator, Disk Version, Site or Farm.

/p or -p	Parameters needed for the Get.
One of these optional	
deviceId	GUID of the Device to get the temporary disk version information for.
deviceName	Name of the Device to get the temporary disk version information for.
deviceMac	MAC of the Device to get the temporary disk version information for.
siteId	GUID of the Site to get temporary disk version information for, and also resolution for diskLocatorName.
siteName	Name of the Site to get temporary disk version information for, and also resolution for diskLocatorName.
diskLocatorId	GUID of the Disk Locator to get temporary disk version information for.
or this optional & resolution	
diskLocatorName	Name of the Disk Locator to get temporary disk version information for.
This optional & resolution	
version	Version of the DiskLocator specified to get temporary disk version information for. Needs the diskLocatorId or diskLocatorName too.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
deviceName	Read-only Computer name that uniquely identifies the Device with temporary version. ASCII computer name characters
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
deviceID	Read-only GUID that uniquely identifies the Device with temporary version. Length=36
deviceName	Read-only Computer name that uniquely identifies the Device with temporary version. ASCII computer name characters
diskLocatorId	Read-only GUID that uniquely identifies the Disk Locator with temporary version. Length=36
diskLocatorName	Read-only Name of the Disk Locator File with temporary version. It is unique within the Store. ASCII
siteId	Read-only GUID of the Site the Device and DiskLocator are a member of.
siteName	Read-only Name of the Site the Device and DiskLocator are a member of.
storeId	Read-only GUID of the Store that the Disk Locator is a member of.
storeName	Read-only Name of the Store that the Disk Locator is a member of.
version	Read-only Disk version the temporary is for.
records	If successful, records retrieved.

MCLI Get DeviceInfo

Get the fields and status for a Device, all Devices in a Collection, Site, Farm View, or Farm. All Devices are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
deviceID	GUID of the Device to Get.
deviceName	Name of Device to Get.
deviceMac	MAC of the Device to Get.
collectionId	GUID of the Collection to Get all Devices for.
serverId	GUID of the Server to Get all Devices for.
serverName	Name of the Server to Get all Devices for.
diskLocatorId	GUID of the DiskLocator to Get all Devices for.
siteViewId	GUID of the Site View to Get all Devices for.
siteId	GUID of the Site.
siteName	Name of the Site.
farmViewId	GUID of the Farm View to Get all Devices for.
farmViewName	Name of the Farm View to Get all Devices for.
deviceIDList	Comma delimited list of GUIDs of the Devices to Get. Maximum length is 8000 characters.
deviceNameList	Comma delimited list of Names of the Devices to Get. Maximum length is 8000 characters.

deviceMacList	Comma delimited list of MACs of the Devices to Get. Maximum length is 8000 characters.
bdmBoot	Include only the BDM Devices when set to 1. PXE devices if set to 0. If not included, all Devices are returned.
or one of these optional & resolutions	
collectionName	Name of the Collection to Get all Devices for.
diskLocatorName	Name of the DiskLocator to Get all Devices for.
siteViewName	Name of the Site View to Get all Devices for.
Optional	
onlyActive	Include only the active Devices when set to 1. If not included or set to 1, all Devices are returned. Only active Devices are always returned for serverId, serverName, or version.
makLicenseActivated	Optional MAK licensing indicator value to only return active Devices for. Values are: 0 (MAK not used), 1 (Not Activated), 2 (Activated).
version	Version of the Disk to Get all active Devices for. This is used with diskLocatorId or diskLocatorName.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
bootFrom	Device to boot from. Choices are 1 for vDisk, 2 for Hard Disk, and 3 for Floppy. This cannot be Set for a Device with Personal vDisk. Min=1, Max=3, Default=1
className	Used by Automatic Update feature to match new versions of Disks to a Device. This cannot be Set for a Device with Personal vDisk. Default="" Max Length=41
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
serverName	Read-only Name of the Server that the Device is using. It is equal to "" if the Device is not active.
diskLocatorName	Read-only name of the Disk Locator File that the Device is using. It is equal to the list

of Disk Locator names for the Device if the Device is not active.
 /f or -f
 List of fields to retrieve, if not included, all fields are retrieved.
 deviceId
 Read-only GUID that uniquely identifies this Device. Length=36
 deviceName
 Computer name with no spaces. ASCII computer name characters Max Length=15
 collectionId
 GUID of the Collection this Device is to be a member of. It is not used with collectionName. Length=36
 collectionName
 Name of the Collection this Device is to be a member of. siteName or siteId must also be used.
 siteId
 GUID of the Site the collectionName is to be a member of. This or siteName is used with collectionName.
 siteName
 Name of the Site the collectionName is to be a member of. This or siteId is used with collectionName.
 description
 User description. Default="" Max Length=250
 deviceMac
 Ethernet address as a string in the form XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
 bootFrom
 Device to boot from. Choices are 1 for vDisk, 2 for Hard Disk, and 3 for Floppy. This cannot be Set for a Device with Personal vDisk. Min=1, Max=3, Default=1
 className
 Used by Automatic Update feature to match new versions of Disks to a Device. This cannot be Set for a Device with Personal vDisk. Default="" Max Length=41
 port
 UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
 enabled
 1 when it can be booted, 0 otherwise. This cannot be Set for a Device with Personal vDisk. Default=1
 localDiskEnabled
 If there is a local disk menu choice for the Device, this is 1. This cannot be Set for a Device with Personal vDisk. Default=0
 role
 Read-only Role of the user for this item. 100 is Farm Administrator, 200 is Site Administrator, 300 is Collection Administrator, and 400 is Collection Operator. Default=999
 authentication
 Device log in authentication. Choices are 0 for none, 1 for User Name/Password, and 2 for Extern. This cannot be Set for a Device with Personal vDisk. Min=0, Max=2, Default=0
 user
 Name of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=20
 password
 Password of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=100

active	1 if the Device is currently active, 0 otherwise. Default=0
template	1 if the Device is the template in its Collection, 0 otherwise. Default=0
adTimestamp	The time the Active Directory machine account password was generated. Do not set this field, it is only set internally by PVS. Default=0
adSignature	The signature of the Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default=0
adPassword	The Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default="" ASCII Max Length=256
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device belongs to. Do not set this field, it is only set internally by PVS. Default=null Max Length=255
domainObjectSID	The value of the objectSID AD attribute of the same name for the Device's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=186
domainControllerName	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
domainTimeCreated	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null
type	1 when it performs test of Disks, 2 when it performs maintenance on Disks, 3 when it has a Personal vDisk, 4 when it has a Personal vDisk and performs tests, 0 otherwise. Min=0, Max=4, Default=0
pvdDriveLetter	Read-only Personal vDisk Drive letter. Range is E to U and W to Z. Default=null Max Length=1
localWriteCacheDiskSize	The size in GB to format the Device cache file disk. If the value is 0, then the disk is not formatted. Min=0, Max=2048, Default=0
virtualHostingPoolId	GUID that uniquely identifies the Virtual Hosting Pool for a VM. This is needed when Adding a VM device. Default=null Length=36
hypVmId	Hypervisor VM ID for HCL Default=null Max Length=250
temporaryVersionSet	Read-only 1 when temporary version is set. Default=0
bdmBoot	Use PXE boot when set to 0, BDM boot when set to 1. Default is PXE Default=0

bdmType	Use PXE boot when set to 0, BDM (Bios) boot when set to 1 and BDM (Uefi) boot when set to 2. Default=0
bdmFormat	1 use VHD for BDMboot, 2 use ISO, 3 use USB. Default=0
bdmUpdated	Timestamp of the last BDM boot disk update. Default=null
bdmCreated	Timestamp when BDM device was created Default=null
xsPvsProxyUuid	UUID of XenServer PVS_proxy Default=null Length=36
ip	Read-only IP of the Device. It is equal to "" if the Device is not active.
serverPortConnection	Read-only Port of the Server that the Device is using. It is equal to "" if the Device is not active. Default=0
serverIpConnection	Read-only IP of the Server that the Device is using. It is equal to "" if the Device is not active.
serverId	Read-only GUID of the Server that the Device is using. It is equal to "" if the Device is not active. Length=36
serverName	Read-only Name of the Server that the Device is using. It is equal to "" if the Device is not active.
diskLocatorId	Read-only GUID of the Disk Locator that the Device is using. It is equal to "" if the Device is not active. Length=36
diskLocatorName	Read-only name of the Disk Locator File that the Device is using. It is equal to the list of Disk Locator names for the Device if the Device is not active.
diskVersion	Read-only version of the Disk Locator File that the Device is using. It is equal to "" if the Device is not active. Default=0
diskVersionAccess	State of the Disk Version. Values are: 0 (Production), 1 (Maintenance), 2 (MaintenanceHighestVersion), 3 (Override), 4 (Merge), 5 (MergeMaintenance), 6 (MergeTest), and 7 (Test). It is equal to "" if the Device is not active. Default=0
diskFileName	Name of the Disk File including the extension. It is equal to "" if the Device is not active.
status	1 or 2 numbers in the format n,n. They are the number of retries and if ram cache is being used, ram cache percent used. It is equal to "" if the Device is not active.
licenseType	0 when None, 1 for Desktop, 2 for Server, 5 for OEM SmartClient, 6 for XenApp, 7 for XenDesktop. It is equal to 0 if the Device is not active. Default=0
makLicenseActivated	Read-only indicator if MAK licensing is being used and is activated. Values are: 0 (MAK not used), 1 (Not Activated), 2 (Activated). It is equal to "" if the Device is not active. Default=0

model	Oem Only: Read-only model of the computer. Values are OptiPlex 745, 755, 320, 760, FX160, or Default. It is equal to "" if the Device is not active.
license	Oem Only: Read-only type of the license. Values are 0 when None, 1 or 2 when Desktop. It is equal to 0 if the Device is not active. Default=0
records	If successful, records retrieved.

MCLI Get DevicePersonality

Get the Device Personality names and values.

/p or -p	Parameters needed for the Get.
One of these required	
deviceId	GUID of the Device.
deviceName	Name of the Device.
deviceMac	MAC of the Device.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
name	Name of the Device personality item. Max Length=250
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the Device personality item. Max Length=250
value	Value for the Device personality item. Max Length=1000
records	If successful, records retrieved.

MCLI Get DeviceStatus

Get the DeviceStatus fields for a Device or all Devices for a Server, Disk Locator, or Farm. All Devices are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
deviceId	GUID of the Device to Get status for.
deviceName	Name of Device to Get status for.
deviceMac	MAC of the Device to Get status for.
serverId	GUID of the Server to Get all Device Status for.
serverName	Name of the Server to Get all Device Status for.
diskLocatorId	GUID of the Disk Locator to Get all DeviceStatus for.
collectionId	GUID of the Collection to Get all DeviceStatus for.
or one of these optional & resolutions	
diskLocatorName	Name of the Disk Locator File to Get all DeviceStatus for.
collectionName	Name of the Collection to Get all DeviceStatus for.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
deviceName	Read-only Name of the Device. Can be used with Get Device.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
deviceId	Read-only GUID of the Device. Can be used with Get Device. Length=36
deviceName	Read-only Name of the Device. Can be used with Get Device.
ip	Read-only IP of the Device.
serverPortConnection	Read-only Port of the Server that the Device is using. Default=0
serverIpConnection	Read-only IP of the Server that the Device is using.
serverId	Read-only GUID of the Server that the Device is using. Length=36
serverName	Read-only Name of the Server that the Device is using.
diskLocatorId	Read-only GUID of the Disk Locator that the Device is using. Length=36
diskLocatorName	Read-only name of the Disk Locator File that the Device is using.
diskVersion	Read-only version of the Disk Locator File that the Device is using. Default=0
diskVersionAccess	State of the Disk Version. Values are: 0 (Production), 1 (Maintenance), 2 (MaintenanceHighestVersion), 3 (Override), 4 (Merge), 5 (MergeMaintenance), 6 (MergeTest), and 7 (Test) Default=0
diskFileName	Name of the Disk File including the extension.
status	1 or 2 numbers in the format n,n. They are the number of retries and if ram cache is being used, ram cache percent used.
licenseType	0 when None, 1 for Desktop, 2 for Server, 5 for OEM SmartClient, 6 for XenApp, 7 for XenDesktop. Default=0
makLicenseActivated	Read-only indicator if MAK licensing is being used and is activated. Values are: 0 (MAK not used), 1 (Not Activated), 2 (Activated). Default=0
records	If successful, records retrieved.

MCLI Get Disk

Get the fields for a single disk.

/p or -p	Parameters needed for the Get.
This required	
diskLocatorId	GUID of the Disk Locator.
or this required & resolution	
diskLocatorName	Name of the Disk Locator.

One of these resolutions when needed

siteId	GUID of the Site.
siteName	Name of the Site.

One of these resolutions when needed

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

/f or -f

class	Class of the Disk. Max Length=40
imageType	Type of this image (software type). Max Length=40
diskSize	Read-only size of the image. The value is 0 when it is not available. Default=0
vhdBlockSize	Block size in KB. For VHD it is only used with Dynamic type. Tested sizes for VHD are 512, 2048, and 16384. VHD Min=512, Max=16384, Default=2048. For VHDX it is used for all types. Tested size for VHDX is 32768. VHDX Min=1024, Max= 262144, Default=32768. Default=0
logicalSectorSize	Logical Sector Size. Values are: 512, 4096, Default=512
writeCacheSize	RAM cache size (MB). Not 0 when used with Cache in Device RAM, and Cache in Device RAM with Overflow on Hard Disk. A value of 0 will disable the RAM use for Cache in Device RAM with Overflow on Hard Disk. Min=0, Max=131072, Default=0
autoUpdateEnabled	Automatically update this image for matching Devices when set to 1. Default 0
activationDateEnabled	Use activation date to activate image when set to 1. Default 0
adPasswordEnabled	Enable AD password management when set to 1.
haEnabled	Enable HA when set to 1.
printerManagementEnabled	Invalid printers will be deleted from the Device when set to 1.
writeCacheType	0 (Private), 1 (Cache on Server), 3 (Cache in Device RAM), 4 (Cache on Device Hard Disk), 7 (Cache on Server, Persistent), 9 (Cache in Device RAM with Overflow on Hard Disk), 10 (Private async), 11 (Server persistent async), 12 (Cache in Device RAM with Overflow on Hard Disk async) Min=0, Max=12, Default=0
licenseMode	0 (None), 1 (Multiple Activation Key), or 2 (Key Management Service). Min=0, Max=2, Default=0
activeDate	Date to activate the disk if autoUpdateEnabled and activationDateEnabled are 1. Format is yyyy/mm/dd. Empty when the autoUpdateEnabled or activationDateEnabled are 0.
longDescription	Description of the Disk. Max Length=399
operatingSystem	Operating System of Disk. Max Length=250
osType	Operating System Type of Disk. Max Length=40

serialNumber	User defined serial number. Max Length=36
date	User defined date. Max Length=40
author	User defined author. Max Length=40
title	User defined title. Max Length=40
company	User defined company. Max Length=40
internalName	User defined name. Max Length=63
originalFile	User defined original file. Max Length=127
hardwareTarget	User defined hardware target. Max Length=127
majorRelease	User defined major release number. Min=0, Max=4294967295, Default=0
minorRelease	User defined minor release number. Min=0, Max=4294967295, Default=0
build	User defined build number. Min=0, Max=4294967295, Default=0
clearCacheDisabled	Clear cached secrets disabled.
format	Format of the image. Values are: 0 (VHD), 1 (VHDX). Default=0
records	If successful, records retrieved.

MCLI Get DiskInfo

Get the fields for a Disk and Disk Locator or all Disks and Disk Locators for a Device, Server, Store, Site, or Farm. All Disks and DiskLocators are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
diskLocatorId	GUID of the Disk Locator to Get.
deviceId	GUID of the Device to Get all DiskLocators for.
deviceName	Name of the Device to Get all DiskLocators for.
deviceMac	MAC of the Device to Get all DiskLocators for.
serverId	GUID of the Server to Get all DiskLocators for.
serverName	Name of the Server to Get all DiskLocators for.
updateTaskId	GUID of the Update Task to Get all DiskLocators for.
siteId	GUID of the Site to Get all DiskLocators for.
siteName	Name of the Site to Get all DiskLocators for.
or one of these optional &	resolutions
diskLocatorName	Name of the Disk Locator File to Get.
storeId	GUID of the Store to Get all DiskLocators for.
storeName	Name of the Store to Get all DiskLocators for.
updateTaskName	Name of the Update Task to Get all DiskLocators for.
One of these optional	
single	Include single server connection when set to 1. If this and All are not included, both connection types are included.
all	Include all server connections for the store when set to 1. If this and Single are not

	included, both connection types are included.
Optional onlyActive	Include only the active DiskLocators when set to 1. If not included or set to 0, all DiskLocators are returned.
updateDevice	Include DiskLocators that have an Update Device when set to 1. Include DiskLocators that do not have an Update Device when set to 0. If this parameter is not included, then all DiskLocators are returned.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
diskLocatorName	Name of the Disk Locator File. It is unique within the Store. ASCII Max Length=52
description	User description. Default="" Max Length=250
menuText	Text that is displayed in the Boot Menu. If this field has no value, the name value is used. Default="" ASCII Max Length=64
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
diskLocatorId	Read-only GUID that uniquely identifies this Disk Locator. Length=36
diskLocatorName	Name of the Disk Locator File. It is unique within the Store. ASCII Max Length=52
siteId	GUID of the Site this DiskLocator is to be a member of. It is not used with siteName. Length=36
siteName	Name of the Site this DiskLocator is to be a member of. It is not used with siteId.
storeId	GUID of the Store that this Disk Locator is a member of. siteName or siteId must also be used. It is not used with storeName. Length=36
storeName	Name of the Store that this Disk Locator is a member of. siteName or siteId must also be used. It is not used with storeId.
description	User description. Default="" Max Length=250
menuText	Text that is displayed in the Boot Menu. If this field has no value, the name value is used. Default="" ASCII Max Length=64
serverId	GUID of the single Server that this Disk Locator is assigned to. It is not used with serverName. Default=null Length=36
serverName	Name of the single Server that this Disk Locator is assigned to. It is not used with serverId. Default=null

enabled	1 when this disk can be booted, 0 otherwise. Default=1
role	Read-only Role of the user for this item. 100 is Farm Administrator, 200 is Site Administrator, 300 is Collection Administrator, and 999 is read-only. Default=999
mapped	1 if the Disk is currently mapped, 0 otherwise. Default=0
enabledForDevice	1 when this disk is enabled for the Device specified, 0 otherwise. This is only returned when a Device is specified. Default=1
active	1 if the DiskLocator is currently active, 0 otherwise. Default=0
rebalanceEnabled	1 when this Server can automatically rebalance Devices, 0 otherwise. Default=0
rebalanceTriggerPercent	Percent over fair load that triggers a dynamic Device rebalance. Min=5, Max=5000, Default=25
subnetAffinity	Qualifier for subnet affinity when assigning a Server. 0=None, 1=Best Effort, 2=Fixed. Min=0, Max=2, Default=0
diskUpdateDeviceId	GUID of the DiskUpdateDevice that is used when updates are performed. Default=null
diskUpdateDeviceName	Name of the DiskUpdateDevice that is used when updates are performed. Default=null
temporaryVersionSet	Read-only 1 when temporary version(s) are set. Default=0
class	Class of the Disk. Max Length=40
imageType	Type of this image (software type). Max Length=40
diskSize	Read-only size of the image. The value is 0 when it is not available. Default=0
vhdBlockSize	Block size in KB. For VHD it is only used with Dynamic type. Tested sizes for VHD are 512, 2048, and 16384. VHD Min=512, Max=16384, Default=2048. For VHDX it is used for all types. Tested size for VHDX is 32768. VHDX Min=1024, Max= 262144, Default=32768. Default=0
logicalSectorSize	Logical Sector Size. Values are: 512, 4096, Default=512
writeCacheSize	RAM cache size (MB). Not 0 when used with Cache in Device RAM, and Cache in Device RAM with Overflow on Hard Disk. A value of 0 will disable the RAM use for Cache in Device RAM with Overflow on Hard Disk. Min=0, Max=131072, Default=0
autoUpdateEnabled	Automatically update this image for matching Devices when set to 1. Default 0
activationDateEnabled	Use activation date to activate image when set to 1. Default 0
adPasswordEnabled	Enable AD password management when set to 1.
haEnabled	Enable HA when set to 1.
printerManagementEnabled	Invalid printers will be deleted from the Device when set to 1.

writeCacheType	0 (Private), 1 (Cache on Server), 3 (Cache in Device RAM), 4 (Cache on Device Hard Disk), 7 (Cache on Server, Persistent), 9 (Cache in Device RAM with Overflow on Hard Disk), 10 (Private async), 11 (Server persistent async), 12 (Cache in Device RAM with Overflow on Hard Disk async) Min=0, Max=12, Default=0
licenseMode	0 (None), 1 (Multiple Activation Key), or 2 (Key Management Service). Min=0, Max=2, Default=0
activeDate	Date to activate the disk if autoUpdateEnabled and activationDateEnabled are 1. Format is yyyy/mm/dd. Empty when the autoUpdateEnabled or activationDateEnabled are 0.
longDescription	Description of the Disk. Max Length=399
operatingSystem	Operating System of Disk. Max Length=250
osType	Operating System Type of Disk. Max Length=40
serialNumber	User defined serial number. Max Length=36
date	User defined date. Max Length=40
author	User defined author. Max Length=40
title	User defined title. Max Length=40
company	User defined company. Max Length=40
internalName	User defined name. Max Length=63
originalFile	User defined original file. Max Length=127
hardwareTarget	User defined hardware target. Max Length=127
majorRelease	User defined major release number. Min=0, Max=4294967295, Default=0
minorRelease	User defined minor release number. Min=0, Max=4294967295, Default=0
build	User defined build number. Min=0, Max=4294967295, Default=0
clearCacheDisabled	Clear cached secrets disabled.
format	Format of the image. Values are: 0 (VHD), 1 (VHDX). Default=0
deviceCount	Read-only count of Devices. Default=0
locked	1 if the Disk is currently locked, 0 otherwise. Default=0
records	If successful, records retrieved.

MCLI Get DiskInventory

Get the fields for Inventory Status of a Disk Version or all Disk Versions for a Disk Locator.	
/p or -p	Parameters needed for the Get.
This required	
diskLocatorId	GUID of the Disk Locator to Get Disk Version Inventory of.
or this required & resolution	
diskLocatorName	Name of the Disk Locator to Get Disk Version Inventory of.
Optional	
version	Specific Version to Get.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
version	Version number. The base disk is version 0, the other version numbers are in part of the file name.
serverId	GUID of the Server that the Disk Version Inventory is being reported about.
serverName	Name of the Server that the Disk Version Inventory is being reported about.
filePath	Path used to access the disk version from the Server. Empty if the information is not available.
fileTime	Date/Time of the date version file. Format is: YYYY-MM-DD HH:MM:SS. 0000-00-00 00:00:00 if the information is not available.
propertiesTime	Date/Time of the disk properties. Format is: YYYY-MM-DD HH:MM:SS. 0000-00-00 00:00:00 if the information is not available.
state	The number code of the inventory state. Values are: 0 (Up to date), 1 (version file is missing), 2 (version file is out of date), 3 (properties are missing), 4 (properties are out of date), 5 (server is not reachable).
active	1 if the Server is currently active, 2 if unknown, and 0 otherwise.
records	If successful, records retrieved.

MCLI Get DiskLocator

Get the fields for a Disk Locator or all Disk Locators for a Device, Server, Store, Site, or Farm. All DiskLocators are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
diskLocatorId	GUID of the Disk Locator to Get.
deviceId	GUID of the Device to Get all DiskLocators for.
deviceName	Name of the Device to Get all DiskLocators for.
deviceMac	MAC of the Device to Get all DiskLocators for.
serverId	GUID of the Server to Get all DiskLocators for.
serverName	Name of the Server to Get all DiskLocators for.
updateTaskId	GUID of the Update Task to Get all DiskLocators for.
siteId	GUID of the Site to Get all DiskLocators for.
siteName	Name of the Site to Get all DiskLocators for.

or one of these optional & resolutions	
diskLocatorName	Name of the Disk Locator File to Get.
storeId	GUID of the Store to Get all DiskLocators for.
storeName	Name of the Store to Get all DiskLocators for.
updateTaskName	Name of the Update Task to Get all DiskLocators for.
One of these optional	
single	Include single server connection when set to 1. If this and All are not included, both connection types are included.
all	Include all server connections for the store when set to 1. If this and Single are not included, both connection types are included.
Optional	
onlyActive	Include only the active DiskLocators when set to 1. If not included or set to 0, all DiskLocators are returned.
updateDevice	Include DiskLocators that have an Update Device when set to 1. Include DiskLocators that do not have an Update Device when set to 0. If this parameter is not included, then all DiskLocators are returned.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
diskLocatorName	Name of the Disk Locator File. It is unique within the Store. ASCII Max Length=52
description	User description. Default="" Max Length=250
menuText	Text that is displayed in the Boot Menu. If this field has no value, the name value is used. Default="" ASCII Max Length=64
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
diskLocatorId	Read-only GUID that uniquely identifies this Disk Locator. Length=36
diskLocatorName	Name of the Disk Locator File. It is unique within the Store. ASCII Max Length=52
siteId	GUID of the Site this DiskLocator is to be a member of. It is not used with siteName. Length=36
siteName	Name of the Site this DiskLocator is to be a member of. It is not used with siteId.
storeId	GUID of the Store that this Disk Locator is a member of. siteName or siteId must also be used. It is not used with storeName. Length=36

storeName	Name of the Store that this Disk Locator is a member of. siteName or siteId must also be used. It is not used with storeId.
description	User description. Default="" Max Length=250
menuText	Text that is displayed in the Boot Menu. If this field has no value, the name value is used. Default="" ASCII Max Length=64
serverId	GUID of the single Server that this Disk Locator is assigned to. It is not used with serverName. Default=null Length=36
serverName	Name of the single Server that this Disk Locator is assigned to. It is not used with serverId. Default=null
enabled	1 when this disk can be booted, 0 otherwise. Default=1
role	Read-only Role of the user for this item. 100 is Farm Administrator, 200 is Site Administrator, 300 is Collection Administrator, and 999 is read-only. Default=999
mapped	1 if the Disk is currently mapped, 0 otherwise. Default=0
enabledForDevice	1 when this disk is enabled for the Device specified, 0 otherwise. This is only returned when a Device is specified. Default=1
active	1 if the DiskLocator is currently active, 0 otherwise. Default=0
rebalanceEnabled	1 when this Server can automatically rebalance Devices, 0 otherwise. Default=0
rebalanceTriggerPercent	Percent over fair load that triggers a dynamic Device rebalance. Min=5, Max=5000, Default=25
subnetAffinity	Qualifier for subnet affinity when assigning a Server. 0=None, 1=Best Effort, 2=Fixed. Min=0, Max=2, Default=0
diskUpdateDeviceId	GUID of the DiskUpdateDevice that is used when updates are performed. Default=null
diskUpdateDeviceName	Name of the DiskUpdateDevice that is used when updates are performed. Default=null
temporaryVersionSet	Read-only 1 when temporary version(s) are set. Default=0
records	If successful, records retrieved.

MCLI Get DiskLocatorCustomProperty

Get the DiskLocator Custom Property names and values.

/p or -p	Parameters needed for the Get.
This required	
diskLocatorId	GUID of the Disk Locator to Get Custom Properties.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Get Custom Properties.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
name	Name of the DiskLocator custom property. Max Length=250
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the DiskLocator custom property. Max Length=250
value	Value of the DiskLocator custom property. Max Length=1000
records	If successful, records retrieved.

MCLI Get DiskLocatorLock

Get the fields for all the locks of a Disk Locator.

/p or -p	Parameters needed for the Get.
This required	
diskLocatorId	GUID of the Disk Locator to Get the Locks.
or this required & resolution	
diskLocatorName	Name of Disk Locator to Get the Locks.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
exclusive	1 when the lock is exclusive, 0 when it is shared. Default=0
deviceId	GUID of the Device that has the lock, will not be included if a Server has the lock.
deviceName	Name of the Device that has the lock, will not be included if a Server has the lock.
serverId	GUID of the Server that has the lock, will not be included if a Device has the lock.
serverName	Name of the Server that has the lock, will not be included if a Device has the lock.
readOnly	1 when lock is because file system is read only, 0 when file system is read write Default=0
records	If successful, records retrieved.

MCLI Get DiskPrinters

Get all available Printers for a Disk.

/p or -p	Parameters needed for the Get.
This required	
diskLocatorId	GUID of the Disk Locator.

```

or this required & resolution
  diskLocatorName           Name of the Disk Locator.
One of these resolutions when needed
  siteId                   GUID of the Site.
  siteName                 Name of the Site.
One of these resolutions when needed
  storeId                  GUID of the Store that is needed when a
                           diskLocatorName is used.
  storeName                Name of the Store that is needed when a
                           diskLocatorName is used.
/s or -s
                           Name of field to sort on. If not included,
                           the first field listed is used. Append a - to
                           the field name to get descending order.
  name                     Read-only Name of the Printer.
  network                 1 when the printer is networked, 0
                           otherwise.
/f or -f
                           List of fields to retrieve, if not included,
                           all fields are retrieved.
  name                     Read-only Name of the Printer.
  network                 1 when the printer is networked, 0
                           otherwise.
  records                 If successful, records retrieved.

```

MCLI Get DiskUpdateDevice

Get the fields and status for a Disk Update Device, or all Disk Update Devices for a Site, Server, DiskLocator or Farm. All Disk Update Devices are returned if no parameters are passed.

```

/p or -p
                           Parameters needed for the Get.

One of these optional
  deviceId                GUID of the Disk Update Device to Get.
  deviceName              Name of Disk Update Device to Get.
  deviceMac               MAC of the Disk Update Device to Get.
  serverId                GUID of the Server to Get all Disk Update
                           Devices for.
  serverName              Name of the Server to Get all Disk Update
                           Devices for.
  diskLocatorId           GUID of the DiskLocator to Get the Disk
                           Update Device for.
  updateTaskId            GUID of the Update Task to Get all Disk
                           Update Devices for.
  siteId                  GUID of the Site.
  siteName                Name of the Site.

or one of these optional &
  diskLocatorName          Name of the DiskLocator to Get the Disk
                           Update Device for.
  updateTaskName           Name of the Update Task to Get all Disk
                           Update Devices for.

Optional
  onlyActive               Include only the active Disk Update Devices
                           when set to 1. If not included or set to 0,
                           all Disk Update Devices are returned. Only
                           active Disk Update Devices are always
                           returned for serverId or serverName.
  makLicenseActivated     Optional MAK licensing indicator value to
                           only return active Disk Update Devices for.

```

Values are: 0 (MAK not used), 1 (Not Activated), 2 (Activated).

One of these resolutions when needed

siteId	GUID of the Site.
siteName	Name of the Site.

One of these resolutions when needed

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

/s or -s

deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
virtualHostingPoolName	Name of the Virtual Hosting Pool.
diskLocatorName	Name of the Disk Locator File to update with this Device.
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901

/f or -f

deviceId	List of fields to retrieve, if not included, all fields are retrieved.
deviceName	Read-only GUID that uniquely identifies this Device. Length=36
virtualHostingPoolId	Computer name with no spaces. ASCII computer name characters Max Length=15
virtualHostingPoolName	GUID of the Virtual Hosting Pool. It is not used with virtualHostingPoolName. Default=null Length=36
diskLocatorId	Name of the Virtual Hosting Pool.
diskLocatorName	GUID of the Disk Locator to update with this Device.
siteId	Name of the Disk Locator File to update with this Device.
siteName	GUID of the Site this Disk Update Device is to be a member of.
storeId	Name of the Site this Disk Update Device is to be a member of.
storeName	GUID of the Store that the Disk Locator is a member of.
description	Name of the Store that the Disk Locator is a member of.
deviceMac	User description. Default="" Max Length=250
port	Ethernet address as a string in the form XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
active	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
adTimestamp	1 if the Device is currently active, 0 otherwise. Default=0
	The time the Active Directory machine account password was generated. Do not set

adSignature	this field, it is only set internally by PVS. Default=0 The signature of the Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default=0
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device belongs to. Do not set this field, it is only set internally by PVS. Default=null Max Length=255
domainObjectSID	The value of the objectSID AD attribute of the same name for the Device's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=186
domainControllerName	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
domainTimeCreated	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null
adPassword	The Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default="" Max Length=256
ip	Read-only IP of the Device. It is equal to "" if the Device is not active.
serverPortConnection	Read-only Port of the Server that the Device is using. It is equal to "" if the Device is not active. Default=0
serverIpConnection	Read-only IP of the Server that the Device is using. It is equal to "" if the Device is not active.
serverId	Read-only GUID of the Server that the Device is using. It is equal to "" if the Device is not active. Length=36
serverName	Read-only Name of the Server that the Device is using. It is equal to "" if the Device is not active.
diskVersion	Read-only version of the Disk Locator File that the Device is using. It is equal to "" if the Device is not active. Default=0
status	1 or 2 numbers in the format n,n. They are the number of retries and if ram cache is being used, ram cache percent used. It is equal to "" if the Device is not active.
licenseType	0 when None, 1 for Desktop, 2 for Server, 5 for OEM SmartClient, 6 for XenApp, 7 for XenDesktop. It is equal to 0 if the Device is not active. Default=0

makLicenseActivated	Read-only indicator if MAK licensing is being used and is activated. Values are: 0 (MAK not used), 1 (Not Activated), 2 (Activated). It is equal to "" if the Device is not active. Default=0
model	Oem Only: Read-only model of the computer. Values are OptiPlex 745, 755, 320, 760, FX160, or Default. It is equal to "" if the Device is not active.
license	Oem Only: Read-only type of the license. Values are 0 when None, 1 or 2 when Desktop. It is equal to 0 if the Device is not active. Default=0
records	If successful, records retrieved.

MCLI Get DiskUpdateStatus

Get the status of an Update Task, or all Update Tasks for a Site or Farm.
All Disk Update Tasks are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
updateTaskId	GUID of the Update Task to Get.
deviceId	GUID of the Disk Update Device to Get Disk Update Status for.
deviceName	Name of the Disk Update Device to Get Disk Update Status for.
deviceMac	MAC of the Disk Update Device to Get Disk Update Status for.
diskUpdateTaskId	GUID of the Disk Update Task and Device relationship to Get Disk Update Status for.
siteId	GUID of the Site to Get all Update Tasks for. Also used with updateTaskName.
siteName	Name of the Site to Get all Update Tasks for. Also used with updateTaskName.
or this optional & resolution	
updateTaskName	Name of the Update Task to Get.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
updateTaskName	Name of the Update Task.
description	User description of the Update Task.
diskLocatorName	Name of the Disk Locator File to update.
virtualHostingPoolName	Name of the Virtual Hosting Pool being used for the update.
deviceName	Name of the Device being used to do the update.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
diskUpdateTaskId	GUID that uniquely identifies this Update Task and Device relationship. Length=36
updateTaskId	GUID that uniquely identifies the Update Task. Length=36
updateTaskName	Name of the Update Task.
description	User description of the Update Task.

diskLocatorId	GUID of the Disk Locator to update.
diskLocatorName	Name of the Disk Locator File to update.
virtualHostingPoolId	GUID of the Virtual Hosting Pool being used for the update.
virtualHostingPoolName	Name of the Virtual Hosting Pool being used for the update.
deviceId	GUID that Device being used to do the update.
deviceName	Name of the Device being used to do the update.
siteId	GUID of the Site that this Update Task Name is a member of.
siteName	Name of the Site that this Update Task Name is a member of.
storeId	GUID of the Store that the Disk Locator is a member of.
storeName	Name of the Store that the Disk Locator is a member of.
previousResult	Status of the last run. Values are: 0 (Ready), 1 (Update Pending), 2 (Preparing Image), 3 (Starting VM), 4 (Update In Progress), 5 (Stopping VM), 6 (Submitting Image), 7 (Reverting Image), 8 (Invalid), 9 (Aborted), 10 (Completed Successfully), 11 (No Updates) Min=0, Max=11, Default=0
previousResultMessage	Message string that includes the results of the last run. Default="" Max Length=255
currentStatus	Current status of the update. Values are: 0 (Ready), 1 (Update Pending), 2 (Preparing Image), 3 (Starting VM), 4 (Update In Progress), 5 (Stopping VM), 6 (Submitting Image), 7 (Reverting Image), 8 (Invalid), 9 (Aborted), 10 (Completed Successfully), 11 (No Updates) Min=0, Max=11, Default=0
currentStatusMessage	Message string that includes the results of the run. Default="" Max Length=255
records	If successful, records retrieved.

MCLI Get DiskVersion

Get the fields for a Disk Version or all Disk Versions for a Disk Locator.	
/p or -p	Parameters needed for the Get.
This required	
diskLocatorId	GUID of the Disk Locator to Get Disk Versions of.
or this required & resolution	
diskLocatorName	Name of the Disk Locator to Get Disk Versions of.
One of these optional	
version	Specific Version to Get.
type	When set to 1, get the Maintenance or MaintenanceHighestVersion access version if it exists. When set to 2, get the Test access versions if any exist. When set to 3, get the Override access version if it exists.
One of these resolutions when needed	

siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
version	Read-only version number. The base disk is version 0, the other version numbers are in part of the file name. Default=0
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
version	Read-only version number. The base disk is version 0, the other version numbers are in part of the file name. Default=0
description	User description. Default="" Max Length=250
type	Read-only type of the Disk Version. Values are: 0 (Base), 1 (Manual), 2 (Automatic), 3 (Merge), and 4 (MergeBase) Min=0, Max=4, Default=0
createDate	Read-only Date/Time that the Disk Version was created. Default=getdate
scheduledDate	Date/Time that the Disk Version is scheduled to become available. Format is: YYYY-MM-DD HH:MM. When empty, the disk version is made available immediately. Default=null
deleteWhenFree	Read-only 1 if the Disk Version is no longer needed because of a merge. If not current booted by a Device, it can be deleted. Default=0
access	Read-only access of the Disk Version. Values are: 0 (Production), 1 (Maintenance), 2 (MaintenanceHighestVersion), 3 (Override), 4 (Merge), 5 (MergeMaintenance), 6 (MergeTest), and 7 (Test) Min=0, Max=7, Default=0
diskFileName	Name of the Disk File including the extension. Default=null
deviceCount	Read-only count of Devices. Default=0
goodInventoryStatus	1 when the up to date file is accessible by all Servers, 0 otherwise. Default=0
taskId	When a Merge is occurring, this will be set with the task number of the process that is occurring. Default=null
canDelete	Read-only 1 when the version can be deleted. Default=0
canMerge	Read-only 1 when the version can be update merged. Will be set for the highest version number. Default=0
canMergeBase	Read-only 1 when the version can be base merged. Will be set for the highest version number. Default=0
canPromote	Read-only 1 when the version can be promoted. Default=0

canRevertTest	Read-only 1 when the version can be reverted to Test Access. Default=0
canRevertMaintenance	Read-only 1 when the version can be reverted to Maintenance Access. Default=0
canSetScheduledDate	Read-only 1 when the version can have the scheduled date modified. Default=0
canOverride	Read-only 1 when the version can be set as the Override. Default=0
isPending	Read-only 1 when the version scheduledDate has not occurred. Default=0
temporaryVersionSet	Read-only 1 when temporary version(s) are set. Some changes cannot be made to the version when this is set. Default=0
records	If successful, records retrieved.

MCLI Get ExceptionDescriptions

Return all of the exceptions with description.	
/p or -p	Parameters needed for the Get.
Optional	
Culture	Optional culture to use for the exception descriptions returned.
records	If successful, records retrieved.

MCLI Get Farm

Get the fields for the Farm.	
/p or -p	Parameters needed for the Get.
Optional	
farmId	GUID of the Farm to Get. This is optional since there is only one Farm.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
farmId	Read-only GUID that uniquely identifies this Farm. Length=36
farmName	Name of the Farm. Default="" Max Length=50
description	User description. Default="" Max Length=250
autoAddEnabled	1 when Auto Add is enabled, 0 otherwise. Default=0
auditingEnabled	1 when Auditing is enabled, 0 otherwise. Default=0
lastAuditArchiveDate	Last date of Audit Trail data that was Archived. Format is yyyy/mm/dd Default=null
defaultSiteId	GUID of the Site to place new Devices into automatically. Not used with defaultSiteName. Default=null Length=36
defaultSiteName	Name of the Site to place new Devices into automatically. Not used with defaultSiteId. Default=null
offlineDatabaseSupportEnabled	1 when Offline Database Support is enabled, 0 otherwise. Default=0
adGroupsEnabled	Active Directory groups are used for authorization, when set to 1. Windows groups are used when set to 0. Default=0
licenseServer	License server name. Default="" Max Length=255

licenseServerPort	License server port. Min=1025, Max=65534, Default=27000
licenseTradeUp	License server trade up, when set to 1. Default=0
licenseSKU	licenseSKU. 0 for on-premises, 1 for cloud. Min=0, Max=1, Default=0
automaticMergeEnabled	1 when Automatic Merge is enabled, 0 otherwise. If the number of versions becomes more than the maxVersions value, a merge will occur at the end of PromoteDiskVersion. Default=1
maxVersions	Maximum number a versions of a Disk that can exist before a merge will automatically occur. Min=3, Max=50, Default=5
mergeMode	Mode to place the version in after a merge has occurred. Values are: 0 (Production), 1 (Test) and 2 (Maintenance). Min=0, Max=2, Default=2
databaseServerName	Read-only name of the database server.
databaseInstanceName	Read-only name of the database instance.
databaseName	Read-only name of the database.
failoverPartnerServerName	Read-only name of the database server.
failoverPartnerInstanceName	Read-only name of the database server instance.
multiSubnetFailover	Read-only Database MultiSubnetFailover value
role	Read-only Role of the user for this item. 100 is Farm Administrator, and 999 is read-only. Default=999
records	If successful, records retrieved.

MCLI Get FarmView

Get the fields for a Farm View or all Farm Views in the Farm. All Farm Views are returned if no parameters are passed.	
/p or -p	Parameters needed for the Get.
One of these optional	
farmViewId	GUID of the Farm View to Get.
farmViewName	Name of the Farm View to Get.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
farmViewName	name of the Farm View. Max Length=50
description	User description. Default="" Max Length=250
deviceCount	Read-only count of Devices in this Farm View. Default=0
activeDeviceCount	Read-only count of active Devices in this Farm View. Default=0
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
farmViewId	Read-only GUID that uniquely identifies this Farm View. Length=36
farmViewName	name of the Farm View. Max Length=50
description	User description. Default="" Max Length=250
deviceCount	Read-only count of Devices in this Farm View. Default=0
activeDeviceCount	Read-only count of active Devices in this Farm View. Default=0

makActivateNeededCount records	Read-only count of active Devices that need MAK activation in this Farm View. Default=0 If successful, records retrieved.
-----------------------------------	---

MCLI Get Groups

Get all of the available groups.	
/p or -p	Parameters needed for the Get.
This optional name	Name of the Group(s) to retrieve. Wildcards are allowed when searching for Active Directory groups. For example, "user*" will return YOUR_DOMAIN/BUILTIN/Users, and "*" will return all the Active Directory groups available.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the Group.
records	If successful, records retrieved.

MCLI Get NewVersionDisks

Get new Disk versions for the Store on the Server specified.	
/p or -p	Parameters needed for the Get.
One of these required serverId	GUID of the Server to look for new Disk versions.
serverName	Name of the Server to look for new Disk versions.
One of these required storeId	GUID of the Store that the Server services to look for new Disk versions.
storeName	Name of the Store that the Server services to look for new Disk versions.
Optional autoAddEnabled	1 when undefined Disk versions found should be automatically added, 0 otherwise. Default=0
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
name	Name of the disk file without the extension.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the disk file without the extension.
status	Status of the disk file. Values are: 0 (Valid), 1 (Missing Properties File), 2 (Access Denied), 3 (Access Denied and Missing Properties File), 4 (Invalid Disk File), 5 (Manifest Invalid)
records	If successful, records retrieved.

MCLI Get Server

Get the fields for a Server, all Servers in a Site that use a Store, service a DiskLocator, or for the whole Farm. All Servers are returned if no parameters are passed.	
/p or -p	Parameters needed for the Get.

One of these optional

serverId	GUID of the Server to Get.
serverName	Name of the Server to Get.
siteId	GUID of the Site to Get all Servers.
siteName	Name of the Site to Get all Servers.
diskLocatorId	GUID of the Disk Locator to Get all Servers.

or this optional & resolution

diskLocatorName	Name of the Disk Locator File to Get all Servers.
-----------------	---

One of these optional & resolutions

storeId	GUID of the Store to Get all Servers.
storeName	Name of the Store to Get all Servers.

Optional

all	Set to 1 with storeId or storeName to Get all Servers for the Store including ones with invalid paths.
-----	--

One of these resolutions when needed

siteId	GUID of the Site.
siteName	Name of the Site.

One of these resolutions when needed

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

/s or -s

serverName	Computer name with no spaces. ASCII computer name characters Max Length=21
description	User description. Default="" Max Length=250
adMaxPasswordAge	Number of days before a password expires. Min=1, Max=30, Default=7
licenseTimeout	Amount of seconds before a license times out. Min=15, Max=300, Default=30
vDiskCreatePacing	VDisk create time pacing in milliseconds. Min=0, Max=5, Default=0
firstPort	Number of the first UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6910
lastPort	Number of the last UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6930
threadsPerPort	Number of worker threads per IO port. Required that (threadPerPort * numberPorts * numberIPs) <= 1000. Min=1, Max=60, Default=8
buffersPerThread	Number of buffers per worker thread. Min=1, Max=128, Default=24
serverCacheTimeout	Number of seconds to wait before considering another Server is down. Min=5, Max=60, Default=8
ioBurstSize	Number of bytes read/writes can send in a burst of packets. Required that ioBurstSize/ (maxTransmissionUnits-76) <= 32. Min=4096, Max=61440, Default=32768

maxTransmissionUnits	Ethernet maximum transmission unit size for the protocol for use for Server and Device. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=502, Max=16426, Default=1506
maxBootDevicesAllowed	Maximum number of Devices allowed to boot simultaneously. Min=1, Max=1000, Default=500
maxBootSeconds	Maximum number of seconds for a Device to boot. Min=10, Max=900, Default=60
bootPauseSeconds	Number of seconds that a Device will pause during login if its server busy. Min=1, Max=60, Default=10
adMaxPasswordAgeEnabled /f or -f	Age the password, when set to 1. Default=0 List of fields to retrieve, if not included, all fields are retrieved.
serverId	Read-only GUID that uniquely identifies this Server. Length=36
serverName	Computer name with no spaces. ASCII computer name characters Max Length=21
siteId	GUID of the Site this Server is to be a member of. It is not used with siteName. Length=36
siteName	Name of the Site this Server is to be a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
adMaxPasswordAge	Number of days before a password expires. Min=1, Max=30, Default=7
licenseTimeout	Amount of seconds before a license times out. Min=15, Max=300, Default=30
vDiskCreatePacing	VDisk create time pacing in miliseconds. Min=0, Max=5, Default=0
firstPort	Number of the first UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6910
lastPort	Number of the last UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6930
threadsPerPort	Number of worker threads per IO port. Required that (threadPerPort * numberPorts * numberIPs) <= 1000. Min=1, Max=60, Default=8
buffersPerThread	Number of buffers per worker thread. Min=1, Max=128, Default=24
serverCacheTimeout	Number of seconds to wait before considering another Server is down. Min=5, Max=60, Default=8
ioBurstSize	Number of bytes read/writes can send in a burst of packets. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=4096, Max=61440, Default=32768
maxTransmissionUnits	Ethernet maximum transmission unit size for the protocol for use for Server and Device. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=502, Max=16426, Default=1506

maxBootDevicesAllowed	Maximum number of Devices allowed to boot simultaneously. Min=1, Max=1000, Default=500
maxBootSeconds	Maximum number of seconds for a Device to boot. Min=10, Max=900, Default=60
bootPauseSeconds	Number of seconds that a Device will pause during login if its server busy. Min=1, Max=60, Default=10
adMaxPasswordAgeEnabled	Age the password, when set to 1. Default=0
eventLoggingEnabled	Enable event logging, when set to 1. Default=0
nonBlockingIoEnabled	Use non-Blocking IO, when set to 1. Default=1
role	Read-only Role of the user for this item. 100 is Farm Administrator, and 200 is Site Administrator. Default=999
ip	One or more streaming ip addresses. If more than one ip is included, the ip addresses are comma delimited.
initialQueryConnectionPoolSize	Initial size of database connection pool for non-transactional queries. Min=1, Max=1000, Default=50
initialTransactionConnectionPoolSize	Initial size of database connection pool for transactional queries. Min=1, Max=1000, Default=50
maxQueryConnectionPoolSize	Maximum size of database connection pool for non-transactional queries. Min=1, Max=32767, Default=1000
maxTransactionConnectionPoolSize	Maximum size of database connection pool for transactional queries. Min=1, Max=32767, Default=1000
refreshInterval	Interval, in number of seconds, the server should wait before refreshing settings. If set to 0, unused database connections are never released. Min=0, Max=32767, Default=300
unusedDbConnectionTimeout	Interval, in number of seconds, a connection should go unused before it is to be released. Min=0, Max=32767, Default=300
busyDbConnectionRetryCount	Number of times a failed database connection will be retried. Min=0, Max=32767, Default=2
busyDbConnectionRetryInterval	Interval, in number of milliseconds, the server should wait before retrying to connect to a database. Min=0, Max=10000, Default=25
localConcurrentIoLimit	Maximum concurrent IO transactions it performs for vDisks that are local. A value of 0 disables the feature. Min=0, Max=128, Default=4
remoteConcurrentIoLimit	Maximum concurrent IO transactions it performs for vDisks that are remote. A value of 0 disables the feature. Min=0, Max=128, Default=4
active	1 if the Server is currently active, 2 if unknown, and 0 otherwise. Min=0, Max=2, Default=0

logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=4
logFileSizeMax	Maximum size log files can reach in Megabytes. Min=1, Max=50, Default=5
logFileBackupCopiesMax	Maximum number of log file backups. Min=1, Max=50, Default=4
powerRating	A strictly relative rating of this Server's capabilities when compared to other Servers in the Store(s) it belongs too; can be used to help tune load balancing. Min=0.1, Max=1000, Default=1
serverFqdn	Read-only fully qualified domain name. Default=null Max Length=1024
managementIp	IP address used for management communications between Servers. Default=0.0.0.0
lastCeipUploadAttempt	Time that this server last attempted a CEIP upload. Default=null
lastBugReportAttempt	Time that this server last attempted to upload or generate a bug report bundle. Default=null
lastBugReportStatus	Status of the last bug report on this server. Default=null Max Length=250
lastBugReportResult	Status of the last bug report on this server. Default=null Max Length=4000
lastBugReportSummary	Summary of the last bug report on this server. Default=null Max Length=250
records	If successful, records retrieved.

MCLI Get ServerBiosBootstrap

Oem Only: Get the bootstrap fields for the Server dell_bios.bin BIOS bootstrap file.	
/p or -p	Parameters needed for the Get.
One of these required	
serverId	GUID of the Server to Get the dell_bios.bin BIOS bootstrap file from.
serverName	Name of the Server to Get the dell_bios.bin BIOS bootstrap file from.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
enabled	Automatically update the BIOS on the target device with these setting when set to 1, otherwise do not use these settings. Default=0
dhcpEnabled	Use DHCP to retrieve target device IP when set to 1, otherwise use the static domain, dnsIpAddress1 and dnsIpAddress2 settings. Default=1
lookup	Use DNS to find the Server when set to 1 with the serverName host value, otherwise use the bootserver1_Ip, bootserver1_Port, bootserver2_Ip, bootserver2_Port, bootserver3_Ip, bootserver3_Port,

verboseMode	bootserver4_Ip, and bootserver4_Port settings. Default=1 Display verbose diagnostic information when set to 1. Default=0
interruptSafeMode	Interrupt safe mode (use if target device hangs during boot) when set to 1. Default=0
paeMode	PAE mode (use if PAE enabled in boot.ini of target device) when set to 1. Default=0
bootFromHdOnFail	For network recovery reboot to hard drive when set to 1, restore network connection when set to 0. Default=0
recoveryTime	When bootFromHdOnFail is 1, this is the number of seconds to wait before reboot to hard drive. Min=10, Max=60000, Default=50
pollingTimeout	Login polling timeout in milliseconds. Min=1000, Max=60000, Default=5000
generalTimeout	Login general timeout in milliseconds. Min=1000, Max=60000, Default=5000
serverName	Host to use for DNS lookup. Only used when lookup is 1. Default=IMAGESERVER1
bootserver1_Ip	1st boot server IP. Only used when lookup is 0.
bootserver1_Port	1st boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
bootserver2_Ip	2nd boot server IP. Only used when lookup is 0. Default=0.0.0.0
bootserver2_Port	2nd boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
bootserver3_Ip	3rd boot server IP. Only used when lookup is 0. Default=0.0.0.0
bootserver3_Port	3rd boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
bootserver4_Ip	4th boot server IP. Only used when lookup is 0. Default=0.0.0.0
bootserver4_Port	4th boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
domain	Domain of the primary and secondary DNS servers. Only used when dhcpEnabled is 0.
dnsIpAddress1	Primary DNS server IP. Only used when dhcpEnabled is 0.
dnsIpAddress2	Secondary DNS server IP. Only used when dhcpEnabled is 0.
records	If successful, records retrieved.

MCLI Get ServerBootstrap

Get the bootstrap fields for the Server and named bootstrap file specified.

/p or -p	Parameters needed for the Get.
One of these required	
serverId	GUID of the Server to Get the named bootstrap file from.
serverName	Name of the Server to Get the named bootstrap file from.
This required	
name	Name of the bootstrap file.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.

bootserver1_Ip	1st boot server IP.
bootserver1_Netmask	1st boot server netmask. Default=0.0.0.0
bootserver1_Gateway	1st boot server gateway. Default=0.0.0.0
bootserver1_Port	1st boot server port. Min=1025, Max=65536, Default=6910
bootserver2_Ip	2nd boot server IP. Default=0.0.0.0
bootserver2_Netmask	2nd boot server netmask. Default=0.0.0.0
bootserver2_Gateway	2nd boot server gateway. Default=0.0.0.0
bootserver2_Port	2nd boot server port. Min=1025, Max=65536, Default=6910
bootserver3_Ip	3rd boot server IP. Default=0.0.0.0
bootserver3_Netmask	3rd boot server netmask. Default=0.0.0.0
bootserver3_Gateway	3rd boot server gateway. Default=0.0.0.0
bootserver3_Port	3rd boot server port. Min=1025, Max=65536, Default=6910
bootserver4_Ip	4th boot server IP. Default=0.0.0.0
bootserver4_Netmask	4th boot server netmask. Default=0.0.0.0
bootserver4_Gateway	4th boot server gateway. Default=0.0.0.0
bootserver4_Port	4th boot server port. Min=1025, Max=65536, Default=6910
verboseMode	Display verbose diagnostic information when set to 1. Default=0
interruptSafeMode	Interrupt safe mode (use if target device hangs during boot) when set to 1. Default=0
paeMode	PAE mode (use if PAE enabled in boot.ini of target device) when set to 1. Default=0
bootFromHdOnFail	For network recovery reboot to hard drive when set to 1, restore network connection when set to 0. Default=0
recoveryTime	When bootFromHdOnFail is 1, this is the number of seconds to wait before reboot to hard drive. Min=10, Max=60000, Default=50
pollingTimeout	Login polling timeout in milliseconds. Min=1000, Max=60000, Default=5000
generalTimeout	Login general timeout in milliseconds. Min=1000, Max=60000, Default=5000
records	If successful, records retrieved.

MCLI Get ServerBootstrapNames

Get the bootstrap names for a Server.	
/p or -p	Parameters needed for the Get.
One of these required	
serverId	GUID of the Server to Get bootstrap names for.
serverName	Name of the Server to Get bootstrap names for.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Bootstrap file name.
records	If successful, records retrieved.

MCLI Get ServerCustomProperty

Get the Server Custom Property names and values.	
/p or -p	Parameters needed for the Get.
One of these required	

serverId	GUID of the Server.
serverName	Name of the Server.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
name	Name of the Server custom property. Max Length=250
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the Server custom property. Max Length=250
value	Value of the Server custom property. Max Length=1000
records	If successful, records retrieved.

MCLI Get ServerInfo

Get the fields and status for a Server, all Servers in a Site that use a Store, service a DiskLocator, or for the whole Farm. All Servers are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
serverId	GUID of the Server to Get.
serverName	Name of the Server to Get.
siteId	GUID of the Site to Get all Servers.
siteName	Name of the Site to Get all Servers.
diskLocatorId	GUID of the Disk Locator to Get all Servers.
or this optional & resolution	
diskLocatorName	Name of the Disk Locator File to Get all Servers.
One of these optional & resolutions	
storeId	GUID of the Store to Get all Servers.
storeName	Name of the Store to Get all Servers.
Optional	
all	Set to 1 with storeId or storeName to Get all Servers for the Store including ones with invalid paths.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
serverName	Computer name with no spaces. ASCII computer name characters Max Length=21
description	User description. Default="" Max Length=250
adMaxPasswordAge	Number of days before a password expires. Min=1, Max=30, Default=7
licenseTimeout	Amount of seconds before a license times out. Min=15, Max=300, Default=30
vDiskCreatePacing	VDisk create time pacing in milliseconds. Min=0, Max=5, Default=0

firstPort	Number of the first UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6910
lastPort	Number of the last UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6930
threadsPerPort	Number of worker threads per IO port. Required that (threadPerPort * numberPorts * numberIPs) <= 1000. Min=1, Max=60, Default=8
buffersPerThread	Number of buffers per worker thread. Min=1, Max=128, Default=24
serverCacheTimeout	Number of seconds to wait before considering another Server is down. Min=5, Max=60, Default=8
ioBurstSize	Number of bytes read/writes can send in a burst of packets. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=4096, Max=61440, Default=32768
maxTransmissionUnits	Ethernet maximum transmission unit size for the protocol for use for Server and Device. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=502, Max=16426, Default=1506
maxBootDevicesAllowed	Maximum number of Devices allowed to boot simultaneously. Min=1, Max=1000, Default=500
maxBootSeconds	Maximum number of seconds for a Device to boot. Min=10, Max=900, Default=60
bootPauseSeconds	Number of seconds that a Device will pause during login if its server busy. Min=1, Max=60, Default=10
adMaxPasswordAgeEnabled /f or -f	Age the password, when set to 1. Default=0 List of fields to retrieve, if not included, all fields are retrieved.
serverId	Read-only GUID that uniquely identifies this Server. Length=36
serverName	Computer name with no spaces. ASCII computer name characters Max Length=21
siteId	GUID of the Site this Server is to be a member of. It is not used with siteName. Length=36
siteName	Name of the Site this Server is to be a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
adMaxPasswordAge	Number of days before a password expires. Min=1, Max=30, Default=7
licenseTimeout	Amount of seconds before a license times out. Min=15, Max=300, Default=30
vDiskCreatePacing	VDisk create time pacing in milliseconds. Min=0, Max=5, Default=0
firstPort	Number of the first UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6910
lastPort	Number of the last UDP port for use by the Stream Service, First and Last must allow at

threadsPerPort	least 5 ports. Min=1025, Max=65534, Default=6930 Number of worker threads per IO port. Required that (threadPerPort * numberPorts * numberIPs) <= 1000. Min=1, Max=60, Default=8
buffersPerThread	Number of buffers per worker thread. Min=1, Max=128, Default=24
serverCacheTimeout	Number of seconds to wait before considering another Server is down. Min=5, Max=60, Default=8
ioBurstSize	Number of bytes read/writes can send in a burst of packets. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=4096, Max=61440, Default=32768
maxTransmissionUnits	Ethernet maximum transmission unit size for the protocol for use for Server and Device. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=502, Max=16426, Default=1506
maxBootDevicesAllowed	Maximum number of Devices allowed to boot simultaneously. Min=1, Max=1000, Default=500
maxBootSeconds	Maximum number of seconds for a Device to boot. Min=10, Max=900, Default=60
bootPauseSeconds	Number of seconds that a Device will pause during login if its server busy. Min=1, Max=60, Default=10
adMaxPasswordAgeEnabled	Age the password, when set to 1. Default=0
eventLoggingEnabled	Enable event logging, when set to 1. Default=0
nonBlockingIoEnabled	Use non-Blocking IO, when set to 1. Default=1
role	Read-only Role of the user for this item. 100 is Farm Administrator, and 200 is Site Administrator. Default=999
ip	One or more streaming ip addresses. If more than one ip is included, the ip addresses are comma delimited.
initialQueryConnectionPoolSize	Initial size of database connection pool for non-transactional queries. Min=1, Max=1000, Default=50
initialTransactionConnectionPoolSize	Initial size of database connection pool for transactional queries. Min=1, Max=1000, Default=50
maxQueryConnectionPoolSize	Maximum size of database connection pool for non-transactional queries. Min=1, Max=32767, Default=1000
maxTransactionConnectionPoolSize	Maximum size of database connection pool for transactional queries. Min=1, Max=32767, Default=1000
refreshInterval	Interval, in number of seconds, the server should wait before refreshing settings. If set to 0, unused database connections are never released. Min=0, Max=32767, Default=300
unusedDbConnectionTimeout	Interval, in number of seconds, a connection should go unused before it is to be released. Min=0, Max=32767, Default=300

busyDbConnectionRetryCount	Number of times a failed database connection will be retried. Min=0, Max=32767, Default=2
busyDbConnectionRetryInterval	Interval, in number of milliseconds, the server should wait before retrying to connect to a database. Min=0, Max=10000, Default=25
localConcurrentIoLimit	Maximum concurrent IO transactions it performs for vDisks that are local. A value of 0 disables the feature. Min=0, Max=128, Default=4
remoteConcurrentIoLimit	Maximum concurrent IO transactions it performs for vDisks that are remote. A value of 0 disables the feature. Min=0, Max=128, Default=4
active	1 if the Server is currently active, 2 if unknown, and 0 otherwise. Min=0, Max=2, Default=0
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=4
logFileSizeMax	Maximum size log files can reach in Megabytes. Min=1, Max=50, Default=5
logFileBackupCopiesMax	Maximum number of log file backups. Min=1, Max=50, Default=4
powerRating	A strictly relative rating of this Server's capabilities when compared to other Servers in the Store(s) it belongs to; can be used to help tune load balancing. Min=0.1, Max=1000, Default=1
serverFqdn	Read-only fully qualified domain name. Default=null Max Length=1024
managementIp	IP address used for management communications between Servers. Default=0.0.0.0
lastCeipUploadAttempt	Time that this server last attempted a CEIP upload. Default=null
lastBugReportAttempt	Time that this server last attempted to upload or generate a bug report bundle. Default=null
lastBugReportStatus	Status of the last bug report on this server. Default=null Max Length=250
lastBugReportResult	Status of the last bug report on this server. Default=null Max Length=4000
lastBugReportSummary	Summary of the last bug report on this server. Default=null Max Length=250
contactIp	Read-only contact IP for the Server.
contactPort	Read-only contact port for the Server.
deviceCount	Read-only count of Devices. Default=0
records	If successful, records retrieved.

MCLI Get ServerStatus

Get the Server Status fields for a Server.

/p or -p

One of these required

Parameters needed for the Get.

serverId	GUID of the Server to Get status for.
serverName	Name of Server to Get status for.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
serverId	Read-only GUID of the Server. Can be used with Get Server. Length=36
serverName	Read-only Name of the Server. Can be used with Get Server.
ip	Read-only contact IP for the Server.
port	Read-only contact port for the Server.
deviceCount	Read-only count of Devices. Default=0
status	Status of the server, 0 if down, 1 if up and 2 if unknown. Default=0
records	If successful, records retrieved.

MCLI Get ServerStore

Get the directory and cache paths of a Server for one or all Stores.

/p or -p	Parameters needed for the Get.
One of these required	
serverId	GUID of a Server.
serverName	Name of a Server.
One of these optional	
storeId	GUID of the Store.
storeName	Name of the Store.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
storeId	GUID of the Store. storeName can be used instead. Length=36
storeName	Name of the Store. storeId can be used instead.
serverId	GUID of the server that uses the Store.
serverName	serverName can be used instead. Length=36
path	Name of the server that uses the Store.
cachePath	serverId can be used instead.
records	Directory path that the Server uses to access the Store. Default="" Max Length=255
	Cache path(s) that the Server uses with the Store. It is an ordered comma-delimited list. If none are specified the caches will be placed in the Store cachePath.
	Default=None
	If successful, records retrieved.

MCLI Get Site

Get the fields for a Site or all Sites. All Sites are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
siteId	GUID of the Site to Get.
siteName	Name of the Site to Get.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
siteName	Name of the Site. Max Length=50
description	User description. Default="" Max Length=250

/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
siteId	Read-only GUID that uniquely identifies this Site. Length=36
siteName	Name of the Site. Max Length=50
description	User description. Default="" Max Length=250
defaultCollectionId	GUID of the Collection to place new Devices into automatically. Not used with defaultCollectionName. Default=null Length=36
defaultCollectionName	Name of the Collection to place new Devices into automatically. Not used with defaultCollectionId. Default=null
inventoryFilePollingInterval	The number of seconds between polls for Disk changes in the Stores. Min=1, Max=600, Default=60
enableDiskUpdate	1 when Disk Updated is enabled for the Site, 0 otherwise. Default=0
diskUpdateServerId	GUID of the Disk Update Server for the Site. Not used with diskUpdateServerName. Default=null Length=36
diskUpdateServerName	Name of the Disk Update Server for the Site. Not used with diskUpdateServerId. Default=null
makUser	User name used for MAK activation. Default=null Max Length=64
makPassword	User password used for MAK activation. Default=null Max Length=64
role	Read-only Role of the user for this item. 100 is Farm Administrator, 200 is Site Administrator, and 999 is read-only. Default=999
records	If successful, records retrieved.

MCLI Get SiteView

Get the fields for a Site View or all Site Views in a Site or the whole Farm. All Site Views are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
siteViewId	GUID of the Site View to Get.
siteId	GUID of the Site to Get all Views for.
siteName	Name of the Site to Get all Views for.
or this optional & resolution	
siteViewName	Name of the Site View to Get.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
siteViewName	Name of the Site View. Max Length=50
description	User description. Default="" Max Length=250
deviceCount	Read-only count of Devices in this Site View. Default=0
deviceWithPVCount	Read-only count of Devices with Personal vDisk in this Site View. Default=0

activeDeviceCount	Read-only count of active Devices in this Site View. Default=0
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
siteViewId	Read-only GUID that uniquely identifies this Site View. Length=36
siteViewName	Name of the Site View. Max Length=50
siteId	GUID of the Site this View is to be a member of. It is not used with siteName. Length=36
siteName	Name of the Site this View is to be a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
deviceCount	Read-only count of Devices in this Site View. Default=0
deviceWithPVDCount	Read-only count of Devices with Personal vDisk in this Site View. Default=0
activeDeviceCount	Read-only count of active Devices in this Site View. Default=0
makActivateNeededCount	Read-only count of active Devices that need MAK activation in this Site View. Default=0
role	Read-only Role of the user for this item. 100 is Farm Administrator, and 200 is Site Administrator. Default=999
records	If successful, records retrieved.

MCLI Get Store

Get the fields for a Store or all Stores for a Server, Site or the Farm.

All Stores are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional	
storeId	GUID of the Store to Get.
storeName	Name of the Store to Get.
serverId	GUID of the Server to Get all Stores for.
serverName	Name of the Server to Get all Stores for.
siteId	GUID of the Site to Get all Stores for.
siteName	Name of the Site to Get all Stores for.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
storeName	Name of the Store. Max Length=50
description	User description. Default="" Max Length=250
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
storeId	Read-only GUID that uniquely identifies this Store. Length=36
storeName	Name of the Store. Max Length=50
siteId	GUID of the Site where Administrators of that Site can change this Store. Not used for Farm Stores. siteName can be used instead. Default=null Length=36
siteName	Name of the Site where Administrators of that Site can change this Store. Not used for Farm Stores. siteId can be used instead. Default=null
description	User description. Default="" Max Length=250

path	Default directory path that the Servers use to access this Store. Max Length=255
cachePath	Default Cache path(s) that the Servers use with this Store. It is an ordered comma-delimited list. If none are specified the caches will be placed in the WriteCache subdirectory of the Store path. Default=None
role	Read-only Role of the user for this item. 100 is Farm Administrator, 200 is Site Administrator, and 999 is read-only. Default=999
pathType	Read-only field indicating if the vdisks are on a server's local hard disk or on a remote share.
records	If successful, records retrieved.

MCLI Get StoreSharedOrServerPath

Get the Stores and paths for the serverName specified or Stores with only shared UNC paths.	
/p or -p	Parameters needed for the Get.
One of these required	
siteId	GUID of a Site used for authorization check.
siteName	Name of a Site used for authorization check.
Optional	
serverName	Name of a Server to also get local Store paths for.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
storeName	Name of the Store.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
storeId	GUID of the Store.
storeName	Name of the Store.
path	Directory path that the Servers use to access this Store.
records	If successful, records retrieved.

MCLI Get Task

Get the current Task fields for select, or all active and completed uncleared tasks.	
/p or -p	Parameters needed for the Get.
One of these optional	
taskId	ID of the Task to get.
siteId	GUID of the Site to get Tasks for.
siteName	Name of the Site to get Tasks for.
Optional	
state	The TaskState to get Tasks for. Values are: 0 (Processing), 1 (Cancelled), and 2 (Complete).
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
taskId	Unique ID of the task.

/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
taskID	Unique ID of the task.
siteId	GUID of the Site that this Task is being processed in. Default=null Length=36
siteName	Name of the Site that that this Task is being processed in.
handle	Handle to a running function.
serverFqdn	Qualified name of the server. Default=null Max Length=1024
ip	IP Address of the remote host.
port	Port number of the remote service.
startTime	Time the task was started. Format is: YYYY-MM-DD HH:MM:SS.
expirationTime	Time the task record may be removed from the database if the task does not complete. Format is: YYYY-MM-DD HH:MM:SS.
state	State of the Task. Values are: 0 (Processing), 1 (Cancelled), and 2 (Complete). Min=0, Max=2
commandType	Type of the command. Values are: Add, Delete, Get, Info, Run, RunWithReturn, Set and SetList. Default="" Max Length=13
command	Command being processed. Default="" Max Length=50
mapiException	Exception result in XML format. Default=null
results	Result in XML format. Default=null
records	If successful, records retrieved.

MCLI Get UndefinedDisks

Get undefined Disks for the Store on the Server specified.	
/p or -p	Parameters needed for the Get.
One of these required	
serverId	GUID of the Server to look for undefined Disks.
serverName	Name of the Server to look for undefined Disks.
One of these required	
storeId	GUID of the Store that the Server services to look for undefined Disks.
storeName	Name of the Store that the Server services to look for undefined Disks.
Optional	
autoAddEnabled	1 when undefined Disks found should be automatically added, 0 otherwise. Default=0
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
name	Name of the disk file without the extension.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the disk file without the extension.
status	Status of the disk file. Values are: 0 (Valid), 1 (Missing Properties File), 2 (Access Denied), 3 (Access Denied and Missing Properties File), 4 (Invalid Disk

format	File), 5 (Manifest Missing or Invalid), 6 (Both VHD and VHDX)
records	Format of the image. Values are: 0 (VHD), 1 (VHDX). Default=0
	If successful, records retrieved.
Get UpdateTask	
t the fields for an Update Task or all Update Tasks in a Site or the whole Farm. All Update Tasks are returned if no parameters are passed.	
/p or -p	Parameters needed for the Get.
One of these optional	
updateTaskId	GUID of the Update Task to Get.
siteId	GUID of the Site to Get all Update Tasks for.
siteName	Name of the Site to Get all Update Tasks for.
or this optional & resolution	
updateTaskName	Name of the Update Task to Get.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
updateTaskName	Name of the Update Task. It is unique within the Site. Max Length=50
description	User description. Default="" Max Length=250
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
updateTaskId	Read-only GUID that uniquely identifies this Update Task. Length=36
updateTaskName	Name of the Update Task. It is unique within the Site. Max Length=50
siteId	GUID of the Site that this Update Task is a member of. It is not used with siteName. Length=36
siteName	Name of the Site that this Update Task is a member of. It is not used with siteId.
description	User description. Default="" Max Length=250
enabled	1 when it will be processed, 0 otherwise. Default=1
hour	The hour of the day to perform the task. Min=0, Max=23, Default=0
minute	The minute of the hour to perform the task. Min=0, Max=59, Default=0
recurrence	The update will reoccur on this schedule. 0 = None, 1 = Daily, 2 = Every Weekday, 3 = Weekly, 4 = Monthly Date, 5 = Monthly Type. Min=0, Max=5, Default=0
dayMask	Days selected values. 1 = Monday, 2 = Tuesday, 4 = Wednesday, 8 = Thursday, 16 = Friday, 32 = Saturday, 64 = Sunday, 128 = Day. Default=0. This is used with Weekly and Monthly Type recurrence. Min=1, Max=255, Default=4

date	Comma delimited days of the month. Numbers from 1-31 are the only valid values. This is used with Monthly Date recurrence. Default="" Max Length=83
monthlyOffset	When to happen monthly. 0 = None, 1 = First, 2 = Second, 3 = Third, 4 = Forth, 5 = Last. This is used with Monthly Type recurrence. Min=0, Max=5, Default=3
esdType	Esd to use. Valid values are SCCM or WSUS. If no value, a custom script is run on the client. Default=null Max Length=50
preUpdateScript	Script file to run before the update starts. Default=null Max Length=255
preVmScript	Script file to run before the VM is loaded. Default=null Max Length=255
postUpdateScript	Script file to run after the update finishes. Default=null Max Length=255
postVmScript	Script file to run after the VM is unloaded. Default=null Max Length=255
domain	Domain to add the Disk Update Device(s) to. If not included, the first Domain Controller found on the Server is used. Default=null Max Length=255
organizationUnit	Organizational Unit to add the Disk Update Device(s) to. This parameter is optional. If it is not specified, the device is added to the built in Computers container. Child OU's should be delimited with forward slashes, e.g. "ParentOU/ChildOU". Special characters in an OU name, such as "'", '#', '+', ',', ';', '>', '=', must be escaped with a backslash. For example, an OU called "commaIn,TheMiddle" must be specified as "commaIn\,TheMiddle". The old syntax of delimiting child OU's with a comma is still supported, but deprecated. Note that in this case, the child OU comes first, e.g. "ChildOU,ParentOU". Default=null Max Length=255
postUpdateApprove	Access to place the version in after the update has occurred. 0 = Production, 1 = Test, 2 = Maintenance. Min=0, Max=2, Default=0
records	If successful, records retrieved.

MCLI Get VirtualHostingPool

Get the fields for a Virtual Hosting Pool or all Virtual Hosting Pools in a Site or the whole Farm. All Virtual Hosting Pools are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
One of these optional virtualHostingPoolId siteId	GUID of the Virtual Hosting Pool to Get. GUID of the Site to Get all Virtual Hosting Pools for.
siteName	Name of the Site to Get all Virtual Hosting Pools for.

or this optional & resolution

virtualHostingPoolName	Name of the Virtual Hosting Pool to Get.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
/s or -s	Name of field to sort on. If not included, the first field listed is used. Append a - to the field name to get descending order.
virtualHostingPoolName	Name of the Virtual Hosting Pool. It is unique within the Site. Max Length=50
description	User description. Default="" Max Length=250
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
virtualHostingPoolId	Read-only GUID that uniquely identifies this Virtual Hosting Pool. Length=36
virtualHostingPoolName	Name of the Virtual Hosting Pool. It is unique within the Site. Max Length=50
siteId	GUID of the Site that this Virtual Hosting Pool is a member of. It is not used with siteName. Length=36
siteName	Name of the Site that this Virtual Hosting Pool is a member of. It is not used with siteId.
type	Type of the Virtual Hosting Pool. 0 = Citrix XenServer, 1 = Microsoft SCVMM/Hyper-V, 2 = VMWare vSphere/ESX. Min=0, Max=3, Default=0
description	User description. Default="" Max Length=250
server	Name or IP of the Host Server. Max Length=255
port	Port of the Host Server. Min=80, Max=65534, Default=80
datacenter	Datacenter of the Virtual Hosting Pool. Default="" Max Length=250
updateLimit	Number of updates at the same time. Min=2, Max=1000, Default=1000
updateTimeout	Timeout for updates. Min=2, Max=240, Default=60
shutdownTimeout	Timeout for shutdown. Min=2, Max=30, Default=10
userName	Name to use when logging into the Server.
password	Password to use when logging into the Server.
xdHostingUnitUuid	UUID of XenDesktop Hosting Unit Default=null Length=36
prepopulateEnabled	Enable prepopulate when set to 1 Default=0
xsPvsSiteUuid	UUID of XenServer PVS_site Default=null Length=36
platformVersion	Hypervisor Host Version Default=null Max Length=250
xdHcHypervisorConnectionName	Hypervisor Connection Name for HCL Connection Details object Default=null Max Length=250
xdHcHypervisorConnectionUid	Hypervisor Connection Uid for HCL Connection Details object Default=null Max Length=250
xdHcRevision	Revision for HCL Connection Details object Default=null Max Length=250

xdHcCustomProperties	Custom Properties for HCL Connection Details object Default=null Max Length=250
xdHcSslThumbprints	Ssl Thumbprints for HCL Connection Details object Default=null Max Length=250
records	If successful, records retrieved.

MCLI Get XDSite

Get the fields for a XenDesktop Site or all XenDesktop Sites. All XenDesktop Sites are returned if no parameters are passed.

/p or -p	Parameters needed for the Get.
This optional	
xdSiteId	GUID of the XenDesktop Site to Get.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
xdSiteId	GUID of the XenDesktop Site. Length=36
configServices	Comma delimited list of XenDesktop Server addresses. Max Length=2000
records	If successful, records retrieved.

MCLI Info

MCLI Info commandName[/p name=value[name2=value2]] [/f field[field2]]

MCLI Info Group

Get the fields for the Groups for the user or the System.

/p or -p	Parameters needed for the Info request.
Optional	
domain	Domain of user (may be the name of the local computer).
user	Name of user.
adGroupsEnabled	Get Active Directory groups, when set to 1. Get Windows groups, when set to 0. If not included, the Farm adGroupsEnabled setting is used.
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
name	Name of the Group.
guid	GUID of the Active Directory group. It will be null for Windows groups.
records	If successful, records retrieved.

MCLI Info LocalServer

Return one record with the local server's NetBios name

/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
LocalServer	NetBios name of local server.
records	If successful, records retrieved.

MCLI Info MapiErrorCode

Return the string and numeric versions of each Mapi error code.

/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
mapiVersion	Version of the system in major.minor.point.build format.

dbVersion	Version of the database schema as a number. Default=0
type	Type of system. Values are 0 (Normal), 1 (OROM), and 2 (Secure). Default=0
dbEdition	Edition of the database. If 'Express Edition', monitor dbSize.
dbSize	Size of the database in MB. Monitor this value if the edition is 'Express Edition' and this value is close to reaching the 4000 MB maximum. Default=0
mapiVersionNumber	Internal version number of the system. It is a number that is increased by 100 for each major and minor release. Point releases are the numbers between each 100. Default=0
records	If successful, records retrieved.

MCLI Info Version

Return one record with the version information.	
/f or -f	List of fields to retrieve, if not included, all fields are retrieved.
mapiVersion	Version of the system in major.minor.point.build format.
dbVersion	Version of the database schema as a number. Default=0
type	Type of system. Values are 0 (Normal), 1 (OROM), and 2 (Secure). Default=0
dbEdition	Edition of the database. If 'Express Edition', monitor dbSize.
dbSize	Size of the database in MB. Monitor this value if the edition is 'Express Edition' and this value is close to reaching the 4000 MB maximum. Default=0
mapiVersionNumber	Internal version number of the system. It is a number that is increased by 100 for each major and minor release. Point releases are the numbers between each 100. Default=0
records	If successful, records retrieved.

MCLI Run

MCLI Run commandName[/p name=value[name2=value2]]

MCLI Run ActivateDevice

Proxy Activate with a Multiple Activation Key and/or apply the Confirmation ID to remote activate a Device DiskLocator pair.	
/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Activate.
deviceName	Name of the Device to Activate.
deviceMac	MAC of the Device to Activate.
This required	
makUsedToActivate	Multiple Activation Key to Activate the Device with.

MCLI Run AddDeviceToDomain

Assign a Device, all Devices in a Collection or View to a Domain.	
/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Add to the Domain.
deviceName	Name of the Device to Add to the Domain.
deviceMac	MAC of the Device to Add to the Domain.
collectionId	GUID of the Collection to Add all Devices to the Domain.
siteViewId	GUID of the Site View to Add all Devices to the Domain.
farmViewId	GUID of the Farm View to Add all Devices to the Domain.
farmViewName	Name of the Farm View to Add all Devices to the Domain.
or one of these required & resolutions	
collectionName	Name of the Collection to Add all Devices to the Domain.
siteViewName	Name of the Site View to Add all Devices to the Domain.
Optional	
domain	Domain to add the Device(s) to. If not included, the first Domain Controller found on the Server is used.
organizationUnit	Organizational Unit to add the Device(s) to. This parameter is optional. If it is not specified, the device is added to the built in Computers container. Child OU's should be delimited with forward slashes, e.g. "ParentOU/ChildOU". Special characters in an OU name, such as "'", '#', '+', ',', ';', '>', '=', must be escaped with a backslash. For example, an OU called "commaIn,TheMiddle" must be specified as "commaIn\,TheMiddle". The old syntax of delimiting child OU's with a comma is still supported, but deprecated. Note that in this case, the child OU comes first, e.g. "ChildOU,ParentOU".
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run AddDiskVersion

Add one or more new Versions to a Disk. A manifest file for the new Disk Version(s) must exist in the Store.

siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run ApplyAutoUpdate

Apply Auto Update for a Server or all Servers in a Site.	
/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to apply Auto Update.
serverName	Name of the Server to apply Auto Update.
siteId	GUID of the Site to apply Auto Update on all Servers.
siteName	Name of the Site to apply Auto Update on all Servers.

MCLI Run ArchiveAuditTrail

Archive the information in the Audit Trail up to a certain date to a file.	
When finished, the information archived will be removed from the Audit Trail.	
/p or -p	Parameters needed for this Run.
This required	
fileName	Name of the file to archive the Audit Trail to. This must be a full file path name.
Optional	
endDate	Last date of information to Archive. If not entered, all information is Archived. Format is yyyy/mm/dd.
purgeData	1 when the information archived will be removed from the Audit Trail. Default=1

MCLI Run AssignAuthGroup

Assign an AuthGroup to have Farm, Site or Collection Authorization. If no Site or Collection is specified, the AuthGroup is given Farm Authorization.	
/p or -p	Parameters needed for this Run.
One of these required	
authGroupId	GUID of the AuthGroup to assign Authorization for.
authGroupName	Name of the AuthGroup to assign Authorization for.
One of these optional	
siteId	GUID of the Site to assign Authorization to for the AuthGroup.
siteName	Name of the Site to assign Authorization to for the AuthGroup.
collectionId	GUID of the Collection to assign Authorization to for the AuthGroup.
or this optional & resolution	
collectionName	Name of the Collection to assign Authorization to for the AuthGroup.
Optional	

role	Authorization Role for the Collection. 300 or 400 can be used. Role can only be used with collectionId or collectionName. 300 is Collection Administrator, and 400 is Collection Operator. Default=400
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
MCLI Run AssignDevice	
Assign a Device to a Collection or View. Personal vDisk Devices cannot be moved to another Site.	
/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Assign.
deviceName	Name of the Device to Assign.
deviceMac	MAC of the Device to Assign.
One of these required	
collectionId	GUID of the Collection to Assign a Device or Devices. The Device is moved from whatever Collection it is currently in, to the Collection specified.
siteViewId	GUID of the Site View to Assign a Device.
farmViewId	GUID of the Farm View to Assign a Device.
farmViewName	Name of the Farm View to Assign a Device.
or one of these required & resolutions	
collectionName	Name of the Collection to Assign a Device or Devices. The Device is moved from whatever Collection it is currently in, to the Collection specified.
siteViewName	Name of the Site View to Assign a Device.
Optional	
copyTemplate	1 if the Template Device for the collection, if it exists, should be used for the property settings of the assigned Device(s). copyTemplate is only valid with collectionId or collectionName.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run AssignDisk

Assign a Disk to an Update Task.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator to Assign.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Assign.
One of these required	
updateTaskId	GUID of the Update Task to Assign a Disk.
updateTaskName	Name of the Update Task to Assign a Disk.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run AssignDiskLocator

Assign a Disk Locator to a Device, a Collection or View.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator to Assign.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Assign.
One of these required	
deviceId	GUID of the Device to Assign a Disk Locator.
deviceName	Name of the Device to Assign a Disk Locator.
deviceMac	MAC of the Device to Assign a Disk Locator.
collectionId	GUID of the Collection to Assign a Disk Locator or Locators to all Devices.
siteViewId	GUID of the Site View to Assign a Disk Locator to all Devices.
farmViewId	GUID of the Farm View to Assign a Disk Locator to all Devices.
farmViewName	Name of the Farm View to Assign a Disk Locator to all Devices.
or one of these required & resolutions	
collectionName	Name of the Collection to Assign a Disk Locator or Locators to all Devices.
siteViewName	Name of the Site View to Assign a Disk Locator to all Devices.
Optional	
removeExisting	1 to remove the existing Disk Locators before assigning the new one. Default=0
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run AssignServer

Assign a Server to a Site.

/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to Assign.
serverName	Name of the Server to Assign.
One of these required	
siteId	GUID of the Site to Assign a Server.
siteName	Name of the Site to Assign a Server.

MCLI Run Boot

Deprecated: use RunWithReturn Boot. Boot a Device, Collection or View.

/p or -p	Parameters needed for this Run.
One of these required	

deviceId	GUID of the Device to Boot.
deviceName	Name of the Device to Boot.
deviceMac	MAC of the Device to Boot.
collectionId	GUID of the Collection to Boot all Devices.
siteViewId	GUID of the Site View to Boot all Devices.
farmViewId	GUID of the Farm View to Boot all Devices.
farmViewName	Name of the Farm View to Boot all Devices.
or one of these required & resolutions	
collectionName	Name of the Collection to Boot all Devices.
siteViewName	Name of the Site View to Boot all Devices.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run CancelTask

Cancel a running Task.

/p or -p	Parameters needed for this Run.
This required	
taskId	Id of the Task to Cancel.

MCLI Run ClearTask

Clear a single or all completed or cancelled Tasks in a Site or the whole Farm.

/p or -p	Parameters needed for this Run.
One of these optional	
taskId	Id of the Task to Clear.
siteId	Site Id of the Tasks to Clear.
siteName	Site Name of the Tasks to Clear.

MCLI Run CopyPasteDevice

Copy properties of one Device to a Device, all the Devices in a Collection, Site View or Farm View.

/p or -p	Parameters needed for this Run.
One of these required	
deviceIdFrom	GUID of the Device to Copy from.
deviceNameFrom	Name of the Device to Copy from.
deviceMacFrom	Mac of the Device to Copy from.
One of these required	
deviceId	GUID of the Device to Copy to.
deviceName	Name of the Device to Copy to.
deviceMac	MAC of the Device to Copy to.
collectionId	GUID of the Collection to Copy to.
siteViewId	GUID of the Site View to Copy to.
farmViewId	GUID of the Farm View to Copy to.
farmViewName	Name of the Farm View to Copy to.
or one of these required & resolutions	
collectionName	Name of the Collection to Copy to.
siteViewName	Name of the Site View to Copy to.
Optional properties	If not specified, all are copied. Comma delimited list of properties. Values are: 1 (Description), 2 (Class), 3 (Port), 4 (Disabled), 5 (Boot Behavior), 6 (Disk Assignment), 7 (Personality), 8 (Printer), 9

(Type), 10 (Authentication) and 11 (Logging).
 One of these resolutions when needed
 siteId
 siteName

MCLI Run CopyPasteDisk

Copy properties of one Disk to a Disk.
 /p or -p
 This required
 diskLocatorIdFrom
 This required
 diskLocatorId
 Optional
 properties

Parameters needed for this Run.
 GUID of the Disk Locator to Copy from.
 GUID of the Disk Locator to Copy to.
 If not specified, all are copied. Comma delimited list of properties. Values are: 1 (Description), 2 (Class), 3 (Type), 4 (Disk Mode), 5 (Auto Update), 6 (HA), 7 (Active Directory), 8 (Printer), 10 (Version), 11 (Date), 12 (Author), 13 (Title), 14 (Company), 15 (Internal Filename), 16 (Original Filename), 17 (Hardware Target), 18 (Menu Text), 19 (Enabled), 20 (Server), and 21 (Store).

MCLI Run CopyPasteServer

Copy properties of one Server to a Server.
 /p or -p
 One of these required
 serverIdFrom
 serverNameFrom
 One of these required
 serverId
 serverName
 Optional
 properties

Parameters needed for this Run.
 GUID of the Server to Copy from.
 Name of the Server to Copy from.
 GUID of the Server to Copy to.
 Name of the Server to Copy to.
 If not specified, all are copied. Comma delimited list of properties. Values are: 1 (Configuration), 2 (Port), 4 (Active Directory), 5 (Advanced Server), 6 (Advanced Network), 7 (Advanced Pacing), 8 (Advanced Device) and 9 (Logging).

MCLI Run CreateDirectory

Create a Directory on the Server specified.
 /p or -p
 One of these required
 serverId
 serverName
 This required
 path

Parameters needed for this Run.
 GUID of the Server to create a Directory on.
 Name of the Server to create a Directory on.
 Path of the new Directory to create.

MCLI Run CreateDiskCancel

Cancel an active CreateDisk.
 /p or -p

Parameters needed for this Run.

This required name	Name of the Disk file that is being created.
One of these required storeId	GUID of the Store that the Disk will be a member of.
storeName	Name of the Store that the Disk will be a member of.

MCLI Run DisableCollection

Disable a Collection so Devices that exist in it are Disabled, even if a Device itself is set to be Enabled.

/p or -p	Parameters needed for this Run.
This required collectionId	GUID of the Collection to Disable.
or this required & resolution collectionName	Name of the Collection to Disable.
One of these resolutions when needed siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run DisableDevice

Disable one or more Devices.

/p or -p	Parameters needed for this Run.
One of these required deviceId	GUID of the Device to Disable.
deviceName	Name of the Device to Disable.
deviceMac	MAC of the Device to Disable.
collectionId	GUID of the Collection to Disable all Devices in.
siteViewId	GUID of the Site View to Disable all Devices in.
farmViewId	GUID of the Farm View to Disable all Devices in.
farmViewName	Name of the Farm View to Disable all Devices in.
or one of these required & resolutions collectionName	Name of the Collection to Disable all Devices in.
siteViewName	Name of the Site View to Disable all Devices in.
One of these resolutions when needed siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run DisableDeviceDiskLocator

Disable a Device's DiskLocator.

/p or -p	Parameters needed for this Run.
One of these required deviceId	GUID of the Device to Disable the DiskLocator for.
deviceName	Name of the Device to Disable the DiskLocator for.
deviceMac	MAC of the Device to Disable the DiskLocator for.
This required	

diskLocatorId	GUID of the DiskLocator to Disable for the Device.
or this required & resolution	
diskLocatorName	Name of the DiskLocator File to Disable for the Device.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run DisableDiskLocator

Disable a DiskLocator so all Devices that have it assigned will not make it available, even if a Device DiskLocator itself is set to be Enabled.	
/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the DiskLocator to Disable.
or this required & resolution	
diskLocatorName	Name of the DiskLocator File to Disable.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run DiskUpdateCancel

Cancel an active Update Task for an Update Device.	
/p or -p	Parameters needed for this Run.
This required	
updateTaskId	GUID of the Update Task to Cancel.
or this required & resolution	
updateTaskName	Name of the Update Task to Cancel.
One of these required	
deviceId	GUID of a specific Update Device to Cancel an Update Task for.
deviceName	Name of a specific Update Device to Cancel an Update Task for.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run DiskUpdateStart

Starts an Update Task.	
/p or -p	Parameters needed for this Run.
This required	
updateTaskId	GUID of the Update Task to Start.
or this required & resolution	
updateTaskName	Name of the Update Task to Start.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run DisplayMessage

Deprecated: use RunWithReturn DisplayMessage. Display a message on a Device, a Site, Collection or View.

/p or -p	Parameters needed for this Run.
This required	
message	Message to display on the Device(s).
One of these required	
deviceId	GUID of the Device to Display a Message.
deviceName	Name of the Device to Display a Message.
deviceMac	MAC of the Device to Display a Message.
collectionId	GUID of the Collection to Display a Message on all Devices.
siteViewId	GUID of the Site View to Display a Message all Devices.
farmViewId	GUID of the Farm View to Display a Message on all Devices.
farmViewName	Name of the Farm View to Display a Message on all Devices.
or one of these required & resolutions	
collectionName	Name of the Collection to Display a Message on all Devices.
siteViewName	Name of the Site View to Display a Message on all Devices.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run EnableCollection

Enable a Collection so Devices that exist in it are Enabled, if the Device itself is not set to be Disabled.

/p or -p	Parameters needed for this Run.
This required	
collectionId	GUID of the Collection to Enable.
or this required & resolution	
collectionName	Name of the Collection to Enable.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run EnableDevice

Enable one or more Devices. If the Device's Collection is Disabled, that overrides the Device setting.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Enable.
deviceName	Name of the Device to Enable.
deviceMac	MAC of the Device to Enable.
collectionId	GUID of the Collection to Enable all Devices in.
siteViewId	GUID of the Site View to Enable all Devices in.
farmViewId	GUID of the Farm View to Enable all Devices in.
farmViewName	Name of the Farm View to Enable all Devices in.

or one of these required & resolutions	
collectionName	Name of the Collection to Enable all Devices in.
siteViewName	Name of the Site View to Enable all Devices in.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run EnableDeviceDiskLocator

Enable a Device's DiskLocator. If the DiskLocator is Disabled, that overrides the Device DiskLocator setting.	
/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Enable the DiskLocator for.
deviceName	Name of the Device to Enable the DiskLocator for.
deviceMac	MAC of the Device to Enable the DiskLocator for.
This required	
diskLocatorId	GUID of the DiskLocator to Enable for the Device.
or this required & resolution	
diskLocatorName	Name of the DiskLocator to Enable for the Device.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run EnableDiskLocator

Enable a DiskLocator so Devices that have it assigned will make it available, if the Device DiskLocator itself is not set to be Disabled.	
/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the DiskLocator to Enable.
or this required & resolution	
diskLocatorName	Name of the DiskLocator File to Enable.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run ExportDisk

Export the disk stack to a manifest file.	
/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator that identifies the disk to export.

or this required & resolution	
diskLocatorName	Name of the Disk Locator that identifies the disk to export.
Optional	
version	Version to use as the start of the export. The export will include all versions starting with this to the highest one.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run ExportOemLicenses

Oem Only: Export the Oem Licenses for the Devices to the fileName specified.	
/p or -p	Parameters needed for this Run.
This required	
fileName	Name of the file to export the Oem Licenses to. This must be a full file path name.
One of these required	
deviceId	GUID of the Device, or comma-delimited list of Device GUIDs to Export Oem Licenses to the fileName specified.
deviceName	Name of the Device, or comma-delimited list of Device Names to Export Oem Licenses to the fileName specified.
deviceMac	MAC of the Device, or comma-delimited list of Device MACs to Export Oem Licenses to the fileName specified.
collectionId	GUID of the Collection to Export all Device Oem Licenses to the fileName specified.
siteViewId	GUID of the Site View to Export all Device Oem Licenses to the fileName specified.
farmViewId	GUID of the Farm View to Export all Device Oem Licenses to the fileName specified.
farmViewName	Name of the Farm View to Export all Device Oem Licenses to the fileName specified.
or one of these required & resolutions	
collectionName	Name of the Collection to Export all Device Oem Licenses to the fileName specified.
siteViewName	Name of the Site View to Export all Device Oem Licenses to the fileName specified.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run ForceInventory

Force the Inventory service to refresh its Inventory Table.

MCLI Run ImportDatabase

Import Devices from the version 4.x mdb database fileName specified.

/p or -p	Parameters needed for this Run.
This required	
fileName	Name of the database mdb file to import the Devices from. This must be a full file path name.
This required	
collectionId	GUID of the Collection to import the Devices into.
or this required & resolution	
collectionName	Name of the Collection to import the Devices into.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run ImportDevices

Import Devices from the contents of the comma or tab delimited fileName specified. Each record needs to have Device Name, Mac Address, Site Name, Collection Name, optional Description and optional Type. Description must exist for Type to be included, but it can have 0 length. Type can be 1 when it performs test of Disks, 2 when it performs maintenance on Disks, and 0 otherwise.

/p or -p	Parameters needed for this Run.
This required	
fileName	Name of the file to import the Devices from. This must be a full file path name.
One of these optional	
collectionId	GUID of the Collection to import the Devices into.
siteId	GUID of the Site to import the Devices into.
siteName	Name of the Site to import the Devices into.
or this optional & resolution	
collectionName	Name of the Collection to import the Devices into.
Optional	
copyTemplate	1 if the Template Device for the collection, if it exists, should be used for the property settings of the imported Devices.
doNotCreateNewSites	1 if new Sites found in the file should not be created. Default=0
doNotCreateNewCollections	1 if new Collections found in the file should not be created. Default=0
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run ImportOemLicenses

Oem Only: Import the Oem Licenses from the contents of the fileName specified.

/p or -p	Parameters needed for this Run.
This required	
fileName	Name of the file to import the Oem Licenses from. This must be a full file path name.

MCLI Run MarkDown

Mark Down a Device, Collection, View, Server or Site.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Mark Down.
deviceName	Name of the Device to Mark Down.
deviceMac	MAC of the Device to Mark Down.
collectionId	GUID of the Collection to Mark Down all Devices.
siteViewId	GUID of the Site View to Mark Down all Devices.
siteId	GUID of the Site. Can be used alone to Mark Down all Servers and Devices in the Site.
siteName	Name of the Site. Can be used alone to Mark Down all Servers and Devices in the Site.
farmViewId	GUID of the Farm View to Mark Down all Devices.
farmViewName	Name of the Farm View to Mark Down all Devices.
diskLocatorId	GUID of the DiskLocator to Mark Down all Devices.
serverId	GUID of the Server to Mark Down.
serverName	Name of the Server to Mark Down.
or one of these required & resolutions	
collectionName	Name of the Collection to Mark Down all Devices.
siteViewName	Name of the Site View to Mark Down all Devices.
diskLocatorName	Name of the DiskLocator to Mark Down all Devices.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run MergeDisk

Merge the Disk.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator File to Merge.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Merge.
Optional	
access	Access to set the version to when merge is finished. Default value is found in the Farm mergeMode setting. Values are: 0 (Production), 1 (Test) and 2 (Maintenance), Min=0, Max=2
base	When 1, specifies to create a new base from last base plus all updates from that base.

The default is to merge all updates from the last base by default.

One of these resolutions when needed

siteId	GUID of the Site.
siteName	Name of the Site.

One of these resolutions when needed

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run PromoteDiskVersion

MCLI Run Reboot

siteViewName	Name of the Site View to Reboot all Devices.
diskLocatorName	Name of the DiskLocator to Reboot all Devices.
Optional	
message	Message to display before rebooting the Device(s). Default=The target device is being shutdown remotely by the Console.
delay	Number of seconds to delay before rebooting the Device(s). Default=10
version	Version of the Disk to Reboot all Devices for. This is used with diskLocatorId or diskLocatorName.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run RemoveAuthGroup

Remove Farm, Site or Collection Authorization for an AuthGroup. If no Site or Collection is specified, Farm Authorization is removed for the AuthGroup.	
/p or -p	Parameters needed for this Run.
One of these required	
authGroupId	GUID of the AuthGroup to remove Authorization for.
authGroupName	Name of the AuthGroup to remove Authorization for.
One of these optional	
siteId	GUID of the Site to remove Authorization for the AuthGroup.
siteName	Name of the Site to remove Authorization for the AuthGroup.
collectionId	GUID of the Collection to remove Authorization for the AuthGroup.
or this optional & resolution	
collectionName	Name of the Collection to remove Authorization for the AuthGroup.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run RemoveDevice

Remove a Device from a View.	
/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Remove.
deviceName	Name of the Device to Remove.
deviceMac	MAC of the Device to Remove.
One of these required	
siteViewId	GUID of the Site View to Remove the Devices from.

farmViewId	GUID of the Farm View to Remove the Devices from.
farmViewName	Name of the Farm View to Remove the Devices from.
or this required & resolution	
siteViewName	Name of the Site View to Remove the Devices from.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run RemoveDeviceFromDomain

Remove a Device, all Devices in a Collection or View from a Domain.	
/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Remove from the Domain.
deviceName	Name of the Device to Remove from the Domain.
deviceMac	MAC of the Device to Remove from the Domain.
collectionId	GUID of the Collection to Remove all Devices from the Domain.
siteViewId	GUID of the Site View to Remove all Devices from the Domain.
farmViewId	GUID of the Farm View to Remove all Devices from the Domain.
farmViewName	Name of the Farm View to Remove all Devices from the Domain.
or one of these required & resolutions	
collectionName	Name of the Collection to Remove all Devices from the Domain.
siteViewName	Name of the Site View to Remove all Devices from the Domain.
Optional	
domain	Domain to remove the Device(s) from. If not included, the first Domain Controller found on the Server is used.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.

MCLI Run RemoveDirectory

Remove a Directory on the Server specified.	
/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to remove a Directory from. The directory must be empty to be removed.
serverName	Name of the Server to remove a Directory from. The directory must be empty to be removed.
This required	
path	Path of the Directory to remove.

MCLI Run RemoveDisk

Remove a Disk from an Update Task.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator to Remove.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Remove.
One of these optional	
updateTaskId	GUID of the Update Task to Remove a Disk.
updateTaskName	Name of the Update Task to Remove a Disk.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run RemoveDiskLocator

Remove a Disk Locator from a Device, Collection, View, or Site.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator to Remove.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Remove.
One of these optional	
deviceId	GUID of the Device to Remove a Disk Locator.
deviceName	Name of the Device to Remove a Disk Locator.
deviceMac	MAC of the Device to Remove a Disk Locator.
collectionId	GUID of the Collection to Remove a Disk Locator or Locators from all Devices.
siteViewId	GUID of the Site View to Remove a Disk Locator from all Devices.
farmViewId	GUID of the Farm View to Remove a Disk Locator from all Devices.
farmViewName	Name of the Farm View to Remove a Disk Locator from all Devices.
or one of these optional & resolutions	
collectionName	Name of the Collection to Remove a Disk Locator or Locators from all Devices.
siteViewName	Name of the Site View to Remove a Disk Locator from all Devices.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run ResetDatabaseConnection

Cause the database location to be reloaded.

MCLI Run ResetDeviceForDomain

MCLI Run RestartStreamService

MCLI Run RevertDiskVersion

Set the existing highest version disk to Maintenance or Test mode. A specified version can be reverted to Test mode if there are no Production versions higher than it. If the mode is Test, it can be set to Maintenance.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator File to Revert.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Revert.
Optional	
version	Specifies the version number that should be Reverted to Test mode.
test	If reverting the highest version and 1 then set the access to Test, otherwise set it to Maintenance.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run SetOverrideVersion

Specify a Disk Version all Production Devices will boot from.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator File to Override the Production Version for.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Override the Production Version for.
Optional	
version	Version to set as the Override Production Version. If Version is not included and if there is an Override Production Version, then no longer have it as the Override Version.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run SetupConnection

Setup the SOAP server connection that will be used for the MCLI and PowerShell command line interfaces.

/p or -p	Parameters needed for this Run.
Optional	

server	Server used for the connection. Default=localhost
port	Port used for the connection. Default=54321
user	User used for the connection. Default=Current user
domain	User domain used for the connection. Default=Current user
password	User password used for the connection. Default=Current user

MCLI Run Shutdown

Deprecated: use RunWithReturn Shutdown a Device, Collection or View.

/p or -p	Parameters needed for this Run.
deviceId	GUID of the Device to Shutdown.
deviceName	Name of the Device to Shutdown.
deviceMac	MAC of the Device to Shutdown.
collectionId	GUID of the Collection to Shutdown all Devices.
siteViewId	GUID of the Site View to Shutdown all Devices.
farmViewId	GUID of the Farm View to Shutdown all Devices.
farmViewName	Name of the Farm View to Shutdown all Devices.
diskLocatorId	GUID of the DiskLocator to Shutdown all Devices.
or one of these required & resolutions	
collectionName	Name of the Collection to Shutdown all Devices.
siteViewName	Name of the Site View to Shutdown all Devices.
diskLocatorName	Name of the DiskLocator to Shutdown all Devices.
Optional message	Message to display before shutting down the Device(s). Default=The target device is being shutdown remotely by the Console.
delay	Number of seconds to delay before shutting down the Device(s). Default=10
version	Version of the Disk to Shutdown all Devices for. This is used with diskLocatorId or diskLocatorName.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run StartDeviceDiskTempVersionMode

Set a Temporary Disk Version for the specified Device and optional DiskLocator. The Temporary Disk Version uses the production version that all production Devices boot from. Once set, the Device boots this Temporary Disk Version instead of any currently assigned vDisk. Not supported for non-production and Personal vDisk Devices. Cannot be done when the the Device already has a Temporary Disk Version, when the DiskLocator is using server side persistent cache mode or the active production version is in private mode.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to start to use a temporary disk version.
deviceName	Name of the Device to start to use a temporary disk version.
deviceMac	MAC of the Device to start to use a temporary disk version.
This optional	
diskLocatorId	GUID of the Disk Locator to use a temporary version of. If not specified, the only Disk Locator assigned to the Device is used.
or this optional & resolution	
diskLocatorName	Name of the Disk Locator to use a temporary version of. If not specified, the only Disk Locator assigned to the Device is used.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run StartStreamService

Start the Stream Service on a Server or all Servers in a Site.

/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to start the Stream Service.
serverName	Name of the Server to start the Stream Service.
siteId	GUID of the Site to start the Stream Service on all Servers.
siteName	Name of the Site to start the Stream Service on all Servers.

MCLI Run StopDeviceDiskTempVersionMode

Unset the Temporary Disk Version for the specified Device. The Device must not currently be booted. Once removed, the Device again uses any currently assigned vDisk when booted.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to no longer use a temporary disk version for.
deviceName	Name of the Device to no longer use a temporary disk version for.

deviceMac	MAC of the Device to no longer use a temporary disk version for.
diskLocatorId	GUID of the DiskLocator to no longer use temporary disk versions for.
siteId	GUID of the Site for resolution of the diskLocatorName.
siteName	Name of the Site for resolution of the diskLocatorName.
or this required & resolution	
diskLocatorName	Name of the DiskLocator to no longer use temporary disk versions for.
This optional & resolution	
version	Version of the DiskLocator to no longer use temporary disk versions for.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
diskLocatorId	GUID of the DiskLocator to no longer use temporary disk versions for.
diskLocatorName	Name of the DiskLocator to no longer use temporary disk versions for.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run StopStreamService

Stop the Stream Service on a Server or all Servers in a Site.

/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to stop the Stream Service.
serverName	Name of the Server to stop the Stream Service.
siteId	GUID of the Site to stop the Stream Service on all Servers.
siteName	Name of the Site to stop the Stream Service on all Servers.

MCLI Run UnlockAllDisk

Remove all locks for a Disk.

/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator to remove all locks for the Disk.
or this required & resolution	
diskLocatorName	Name of Disk Locator to remove all locks for the Disk.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	

storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run UnlockDisk

Remove lock for the Disk.	
/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator to remove a lock for the Disk.
or this required & resolution	
diskLocatorName	Name of the Disk Locator to remove a lock for the Disk.
Optional	
ownerId	GUID of the Owner of the Disk Lock.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.

MCLI Run UnmapDisk

No longer Map the Disk.

MCLI Run ValidateDirectory

Validate a Directory on the Server specified.	
/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to validate a Directory on.
serverName	Name of the Server to validate a Directory on.
This required	
path	Path of the Directory to validate.
This optional	
readOnly	1 when the directory should be validated for a managed read-only store.

MCLI RunWithReturn

MCLI RunWithReturn commandName [/p name=value [name2=value2]]

MCLI RunWithReturn Boot

Boot a Device, Collection or View. Returns a taskId of the Task being run. With the taskId, call ReturnWithReturn TaskStatus to get the percent complete, Get Task to get the results, and Run CancelTask to stop it early. The Task result has the deviceName/value of the devices that succeeded in the first name/value pair of each record of the XML.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Boot.

deviceName	Name of the Device to Boot.
deviceMac	MAC of the Device to Boot.
collectionId	GUID of the Collection to Boot all Devices.
siteViewId	GUID of the Site View to Boot all Devices.
farmViewId	GUID of the Farm View to Boot all Devices.
farmViewName	Name of the Farm View to Boot all Devices.
deviceIdList	Comma delimited list of GUIDs of the Devices to Boot. Maximum length is 8000 characters.
deviceNameList	Comma delimited list of Names of the Devices to Boot. Maximum length is 8000 characters.
deviceMacList	Comma delimited list of MACs of the Devices to Boot. Maximum length is 8000 characters.
or one of these required & resolutions	
collectionName	Name of the Collection to Boot all Devices.
siteViewName	Name of the Site View to Boot all Devices.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn CommandActions

Get a comma delimited list of Command Actions.	
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn CreateDisk

Create a Disk and the Disk Locator for it. Return the GUID of the DiskLocator created. If "" is returned as the GUID, then call CreateDiskStatus to get the final GUID when processing finishes.	
/p or -p	Parameters needed for this Run.
This required	
name	Name of the Disk file to be created.
This required	
size	Size of the disk in Megabytes for a fixed size disk. Maximum size in Megabytes for a dynamically sized disk. Min=1, VHD Max=2088960, VHDX Max=67108864
One of these required	
storeId	GUID of the Store that the Disk will be a member of.
storeName	Name of the Store that the Disk will be a member of.
One of these required	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these optional	
serverId	GUID of the only Server for this Disk.
serverName	Name of the only Server for this Disk.
Optional	
description	Description of the Disk that will be placed in the Disk Locator.
enabled	The Disk will be created disabled if set to 0. It is created Enabled by default. Default=1

format	Format of the image. Values are: 0 (VHD), 1 (VHDX), Default=0
type	Type that will be created. 1 for dynamic, or 0 for fixed. Default=1 for VHDX, 0 for VHD
vhdBlockSize	Block size in KB. For VHD it is only used with Dynamic type. Tested sizes for VHD are 512, 2048, and 16384. VHD Min=512, Max=16384, Default=2048. For VHDX it is used for all types. Tested size for VHDX is 32768. VHDX Min=1024, Max= 262144, Default=32768.
logicalSectorSize	Only used with VHDX format. Logical Sector Size. Values are: 512, 4096, Default=512
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn CreateDiskStatus

Get the Percent Finished for an active CreateDisk. When finished, the GUID of the DiskLocator created is returned.	
/p or -p	Parameters needed for this Run.
This required	
name	Name of the Disk file that is being created.
One of these required	
storeId	GUID of the Store that the Disk will be a member of.
storeName	Name of the Store that the Disk will be a member of.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn CreateMaintenanceVersion

Create a Maintenance version for the Disk Locator. Return the name of the new version file.	
/p or -p	Parameters needed for this Run.
This required	
diskLocatorId	GUID of the Disk Locator File to Enable Disk Maintenance on.
or this required & resolution	
diskLocatorName	Name of the Disk Locator File to Enable Disk Maintenance on.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn DeviceCount

Get count of Devices in a Collection or View.	
/p or -p	Parameters needed for this Run.
One of these required	

collectionId	GUID of the Collection to get the Device Count of.
siteViewId	GUID of the Site View to get the Device Count of.
farmViewId	GUID of the Farm View to get the Device Count of.
farmViewName	Name of the Farm View to get the Device Count of.
or one of these required & resolutions	
collectionName	Name of the Collection to get the Device Count of.
siteViewName	Name of the Site View to get the Device Count of.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn DiskLocatorCount

Get count of Disk Locators for a Site and Type.	
/p or -p	Parameters needed for this Run.
One of these required	
siteId	GUID of the Site to get the Disk Locator Count of.
siteName	Name of the Site to get the Disk Locator Count of.
One of these optional	
single	Include single server connection when set to 1. If this and All are not included, both connection types are included.
all	Include all server connections for the store when set to 1. If this and Single are not included, both connection types are included.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn DisplayMessage

Display a message on a Device, a Site, Collection or View. Returns a taskId of the Task being run. With the taskId, call ReturnWithReturn TaskStatus to get the percent complete, Get Task to get the results, and Run CancelTask to stop it early. The Task result has the deviceName/value of the devices that succeeded in the first name/value pair of each record of the XML.	
/p or -p	Parameters needed for this Run.
This required	
message	Message to display on the Device(s).
One of these required	
deviceId	GUID of the Device to Display a Message.
deviceName	Name of the Device to Display a Message.
deviceMac	MAC of the Device to Display a Message.
collectionId	GUID of the Collection to Display a Message on all Devices.

siteViewId	GUID of the Site View to Display a Message on all Devices.
farmViewId	GUID of the Farm View to Display a Message on all Devices.
farmViewName	Name of the Farm View to Display a Message on all Devices.
deviceIdList	Comma delimited list of GUIDs of the Devices to Display a Message. Maximum length is 8000 characters.
deviceNameList	Comma delimited list of Names of the Devices to Display a Message. Maximum length is 8000 characters.
deviceMacList	Comma delimited list of MACs of the Devices to Display a Message. Maximum length is 8000 characters.
or one of these required & resolutions	
collectionName	Name of the Collection to Display a Message on all Devices.
siteViewName	Name of the Site View to Display a Message on all Devices.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn Enabled

Return 1 if a Collection, Device, DiskLocator, or Device/DiskLocator is enabled. If a collectionName or diskLocatorName is specified, siteName or siteId must be included. If both the Device and DiskLocator are specified, the Enabled setting for the combination is returned.	
/p or -p	Parameters needed for this Run.
This optional	
collectionId	Collection GUID, to see if it is enabled.
or this optional & resolution	
collectionName	Collection name, to see if it is enabled.
One of these optional	
deviceId	Device GUID, to see if it is enabled. If diskLocatorName or diskLocatorId are also included the enabled setting for the combination is returned.
deviceName	Device name, to see if it is enabled. If diskLocatorName or diskLocatorId are also included the enabled setting for the combination is returned.
deviceMac	MAC of the Device, to see if it is enabled. If diskLocatorName or diskLocatorId are also included the enabled setting for the combination is returned.
This optional	
diskLocatorId	DiskLocator GUID, to see if it is enabled. If deviceName or deviceId are also included the enabled setting for the combination is returned.
or this optional & resolution	

diskLocatorName	DiskLocator name, to see if it is enabled. If deviceName or deviceId are also included the enabled setting for the combination is returned.
One of these resolutions when needed	
siteName	Name of the Site.
siteId	GUID of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn Exists

Return 1 if a Site, Server, Collection, View, Device, Store, Update Task or Virtual Hosting Pool Name is already used. If a collectionName, siteViewName, updateTaskName or virtualHostingPoolName is specified, siteName or siteId must be included.

/p or -p	Parameters needed for this Run.
One of these required	
siteName	Name of the Site.
serverName	Server name, to see if it is already used in the Farm.
farmViewName	Farm View name, to see if it is already used in the Farm.
deviceName	Device name, to see if it is already used in the Farm.
deviceMac	Device MAC, to see if it is already used in the Farm.
storeName	Store name, to see if it is already used.
or one of these required & resolutions	
collectionName	Collection name, to see if it is already used in a Site.
siteViewName	Site View name, to see if it is already used in the Site.
virtualHostingPoolName	Virtual Hosting Pool name, to see if it is already used in a Site.
updateTaskName	Update Task name, to see if it is already used in a Site.
diskLocatorName	DiskLocator name, to see if it is already used in a Site.
One of these resolutions when needed	
siteName	Name of the Site.
siteId	GUID of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn ImportDisk

Import a Disk. It will add a Disk Locator for the Disk to the Site. A manifest file must exist in the Store. The return value is the GUID of the DiskLocator added.

/p or -p	Parameters needed for this Run.
This required & resolution	
diskLocatorName	Name of the Disk Locator File. It is unique within the Store. ASCII Max Length=52
One of these optional	
serverId	GUID of the single Server that this Disk Locator is assigned to. It is not used with serverName. Default=null Length=36
serverName	Name of the single Server that this Disk Locator is assigned to. It is not used with serverId. Default=null
Optional	
description	User description. Default="" Max Length=250
menuText	Text that is displayed in the Boot Menu. If this field has no value, the name value is used. Default="" ASCII Max Length=64
enabled	1 when this disk can be booted, 0 otherwise. Default=1
rebalanceEnabled	1 when this Server can automatically rebalance Devices, 0 otherwise. Default=0
rebalanceTriggerPercent	Percent over fair load that triggers a dynamic Device rebalance. Min=5, Max=5000, Default=25
subnetAffinity	Qualifier for subnet affinity when assigning a Server. 0=None, 1=Best Effort, 2=Fixed. Min=0, Max=2, Default=0
format	Format of the image. Values are: 0 (VHD), 1 (VHDX), Default=0
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn ListDirectories

Look for Directories or Drives on the Server specified. Return a comma delimited list of the Directories or Drives found.

/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to get a list of Directories or Drives.
serverName	Name of the Server to get a list of Directories or Drives.
Optional	
path	Path to get list of Directories for. If not specified, the Drives are returned.

rv If successful, this rv is filled with a string.

MCLI RunWithReturn MaintenanceVersionExists

Return 1 if the if the DiskLocator has a maintenance version, 0 otherwise.

/p or -p Parameters needed for this Run.

This required

diskLocatorId DiskLocator GUID, to see if it has a maintenance version.

or this required & resolution

diskLocatorName DiskLocator name, to see if it has a maintenance version.

One of these resolutions when needed

siteId GUID of the Site.

siteName Name of the Site.

One of these resolutions when needed

storeId GUID of the Store that is needed when a diskLocatorName is used.

storeName Name of the Store that is needed when a diskLocatorName is used.

rv If successful, this rv is filled with a string.

MCLI RunWithReturn MapDisk

Map a disk. If successful, the drive letter or an empty string is returned. An empty string can be returned if a drive letter was not assigned by the operating system before the maxDiskLetterWaitSeconds is used up.

/p or -p Parameters needed for this Run.

This required

diskLocatorId GUID of the Disk Locator to Map the Disk.

or this required & resolution

diskLocatorName Name of the Disk Locator to Map the Disk.

One of these optional

serverId Specific Server GUID to use to Map the Disk.

serverName Specific Server Name to use to Map the Disk.

Optional

maxDiskLetterWaitSeconds Once mapping a disk is successful, this is the maximum amount of seconds spent waiting for the operating system to return a drive letter. If the operating system does not return a drive letter before the maximum wait time, then an empty string is returned. Default=30

One of these resolutions when needed

siteId GUID of the Site.

siteName Name of the Site.

One of these resolutions when needed

storeId GUID of the Store that is needed when a diskLocatorName is used.

storeName Name of the Store that is needed when a diskLocatorName is used.

rv If successful, this rv is filled with a string.

MCLI RunWithReturn MappedDiskId

If there is currently a mapped disk, return the diskLocatorId of the mapped disk.

/p or -p	Parameters needed for this Run.
One of these optional	
serverId	GUID of the Server.
serverName	Name of the Server.
One of these optional	
storeId	GUID of the Store.
storeName	Name of the Store.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn MappedDriveLetter

If there is currently a Mapped Drive, return the Letter of the Drive.

rv	If successful, this rv is filled with a string.
----	---

MCLI RunWithReturn MinimumLastAutoAddDeviceNumber

Get the minimum that the Device Number of the last Auto Added Device can be.

/p or -p	Parameters needed for this Run.
This required	
collectionId	GUID of the Collection to get the Minimum lastAutoAddDeviceNumber for.
or this required & resolution	
collectionName	Name of the Collection to get the Minimum lastAutoAddDeviceNumber for.
Optional	
autoAddPrefix	The string put before the Device Number for Auto Add.
autoAddSuffix	The string put after the Device Number for Auto Add.
autoAddNumberLength	The maximum length of the Device Number for Auto Add. This length plus the autoAddPrefix length plus the autoAddSuffix length must be less than 16.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn RebalanceDevices

Rebalance Devices for a Server. When successful, returns the number of Devices affected.

/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server to Rebalance Devices on, serverName.
serverName	Name of the Server to Rebalance Devices on, serverId.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn Reboot

Reboot a Device, Collection or View. Returns a taskId of the Task being run. With the taskId, call ReturnWithReturn TaskStatus to get the percent complete, Get Task to get the results, and Run CancelTask to stop it early. The Task result has the deviceName/value of the devices that succeeded in the first name/value pair of each record of the XML.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Reboot.
deviceName	Name of the Device to Reboot.
deviceMac	MAC of the Device to Reboot.
collectionId	GUID of the Collection to Reboot all Devices.
siteViewId	GUID of the Site View to Reboot all Devices.
farmViewId	GUID of the Farm View to Reboot all Devices.
farmViewName	Name of the Farm View to Reboot all Devices.
diskLocatorId	GUID of the DiskLocator to Reboot all Devices.
deviceIdList	Comma delimited list of GUIDs of the Devices to Reboot. Maximum length is 8000 characters.
deviceNameList	Comma delimited list of Names of the Devices to Reboot. Maximum length is 8000 characters.
deviceMacList	Comma delimited list of MACs of the Devices to Reboot. Maximum length is 8000 characters.
or one of these required &	resolutions
collectionName	Name of the Collection to Reboot all Devices.
siteViewName	Name of the Site View to Reboot all Devices.
diskLocatorName	Name of the DiskLocator to Reboot all Devices.
Optional	
message	Message to display before rebooting the Device(s). Default=The target device is being shutdown remotely by the Console.
delay	Number of seconds to delay before rebooting the Device(s). Default=10
version	Version of the Disk to Reboot all Devices for. This is used with diskLocatorId or diskLocatorName.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn ReportBug

Report a bug at individual server level or at site level. Return the id of the long running task.

/p or -p	Parameters needed for this Run.
One of these required	
siteId	GUID of the Site.
serverId	GUID of the Server.
or one of these required &	resolutions
siteName	Name of the Site.
serverName	Name of the Server.
This required	
Summary	Short summary describing the problem.
This optional	
srNumber	Service Request number of the reported problem.
This optional	
Description	Description of the reported problem.
This optional	
Path	Path where problem report bundle is saved.
This optional	
DateTime	DateTime around which the reported problem occurred.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn ServerCount

Get count of Servers in a Site.

/p or -p	Parameters needed for this Run.
One of these required	
siteId	GUID of the Site to get the Server Count of.
siteName	Name of the Site to get the Server Count of.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn ServerName

Return the name of the Server the SoapServer is running on.

rv	If successful, this rv is filled with a string.
----	---

MCLI RunWithReturn ServerStoreActiveDeviceCount

Get the count of Devices currently connected to any vdisk served from the Store by the Server.

/p or -p	Parameters needed for this Run.
One of these required	
serverId	GUID of the Server.
serverName	Name of the Server.
One of these required	
storeId	GUID of the Store.
storeName	Name of the Store.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn Shutdown

Shutdown a Device, Collection or View. Returns a taskId of the Task being run. With the taskId, call ReturnWithReturn TaskStatus to get the percent complete, Get Task to get the results, and Run CancelTask to stop it early. The Task result has the deviceName/value of the devices that succeeded in the first name/value pair of each record of the XML.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Shutdown.
deviceName	Name of the Device to Shutdown.
deviceMac	MAC of the Device to Shutdown.
collectionId	GUID of the Collection to Shutdown all Devices.
siteViewId	GUID of the Site View to Shutdown all Devices.
farmViewId	GUID of the Farm View to Shutdown all Devices.
farmViewName	Name of the Farm View to Shutdown all Devices.
diskLocatorId	GUID of the DiskLocator to Shutdown all Devices.
deviceIdList	Comma delimited list of GUIDs of the Devices to Shutdown. Maximum length is 8000 characters.
deviceNameList	Comma delimited list of Names of the Devices to Shutdown. Maximum length is 8000 characters.
deviceMacList	Comma delimited list of MACs of the Devices to Shutdown. Maximum length is 8000 characters.
or one of these required &	resolutions
collectionName	Name of the Collection to Shutdown all Devices.
siteViewName	Name of the Site View to Shutdown all Devices.
diskLocatorName	Name of the DiskLocator to Shutdown all Devices.
Optional	
message	Message to display before shutting down the Device(s). Default=The target device is being shutdown remotely by the Console.
delay	Number of seconds to delay before shutting down the Device(s). Default=10
version	Version of the Disk to Shutdown all Devices for. This is used with diskLocatorId or diskLocatorName.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn StoreFreeSpace

Get the free megabytes available in the Store.

/p or -p	Parameters needed for this Run.
One of these required & resolutions	
storeId	GUID of the Store.
storeName	Name of the Store.
One of these resolutions when needed	
serverId	GUID of the Server to use to determine the free space in the Store.
serverName	Name of the Server to use to determine the free space in the Store.
siteId	GUID of the Site.
siteName	Name of the Site.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn TaskStatus

Get the status of a Task in percent complete.

/p or -p	Parameters needed for this Run.
This required	
taskId	Id of the Task to get the Status of.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn UpdateBDM

Update the BDM Partition for a Device, Collection or View. Returns a taskId of the Task being run. With the taskId, call ReturnWithReturn TaskStatus to get the percent complete, Get Task to get the results, and Run CancelTask to stop it early. The Task result has the deviceName/value of the devices that succeeded in the first name/value pair of each record of the XML.

/p or -p	Parameters needed for this Run.
One of these required	
deviceId	GUID of the Device to Update.
deviceName	Name of the Device to Update.
collectionId	GUID of the Collection to Update all BDM Devices.
siteViewId	GUID of the Site View to Update all BDM Devices.
farmViewId	GUID of the Farm View to Update all BDM Devices.
farmViewName	Name of the Farm View to Update all BDM Devices.
deviceIds	Comma delimited list of GUIDs of the Devices to Update. Maximum length is 8000 characters.
deviceNames	Comma delimited list of names of the Devices to Update. Maximum length is 8000 characters.
or one of these required & resolutions	
collectionName	Name of the Collection to Update all BDM Devices.
siteViewName	Name of the Site View to Update all BDM Devices.
One of these resolutions when needed	

siteId	GUID of the Site.
siteName	Name of the Site.
rv	If successful, this rv is filled with a string.

MCLI RunWithReturn UploadCeip

Perform a one time upload of CEIP data. Return upload Id if successful.	
/p or -p	Parameters needed for this Run.
This optional	
oneTimeUpload	1 to perform a one time upload.
rv	If successful, this rv is filled with a string.

MCLI Set

MCLI Set commandName[/p name=value[name2=value2]][/r field=value[field2=value2]]

MCLI Set AuthGroup

Set one or more field values for an AuthGroup.	
/p or -p	Parameters needed to identify the record to be changed.
One of these required	
authGroupId	GUID of the AuthGroup to Set.
authGroupName	Name of the AuthGroup to Set.
/r or -r	Record containing the new values for fields to be changed.
authGroupName	Name of the Active Directory or Windows Group. Max Length=450
description	User description. Default="" Max Length=250

MCLI Set CeipData

Set one or more field values for CEIP data.	
/p or -p	Parameters needed to identify the record to be changed.
Optional	
uuid	CEIP UUID of this Farm. This is optional since there is only one.
/r or -r	Record containing the new values for fields to be changed.
enabled	1 if CEIP is enabled, otherwise 0. Min=0, Max=1
nextUpload	Date and time next CEIP upload is due if enabled is 1. Default=null
inProgress	1 if an upload is currently in progress, otherwise 0. Default=0
serverId	ID of server that is currently uploading, null if inProgress is 0. Default=null Length=36
oneTimeUpload	1 to perform a one time upload. Default=0

MCLI Set CisData

Set one or more field values for CIS data.	
/p or -p	Parameters needed to identify the record to be changed.

Optional	
cisDataId	CIS UUID of this Farm. This is optional since there is only a single record.
/r or -r	Record containing the new values for fields to be changed.
userNmae	Username used to obtain the token Default=null Max Length=255
path	Path where the last problem report bundle was saved Default=null Max Length=255
password	Password of the user required to obtain the token. This is required only by Set and Add

MCLI Set Collection

Set one or more field values for a Collection.

/p or -p	Parameters needed to identify the record to be changed.
This required	
collectionId	GUID of the Collection to Set.
or this required & resolution	
collectionName	Name of the Collection to Set.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
/r or -r	Record containing the new values for fields to be changed.
collectionName	Name of the Collection. It is unique within the Site. Max Length=50
description	User description. Default="" Max Length=250
templateDeviceId	GUID of a Device in the Collection whose settings are used for initial values of new Devices. Not used with templateDeviceName. Default=null Length=36
templateDeviceName	Name of a Device in the Collection whose settings are used for initial values of new Devices. Not used with templateDeviceId. Default=null
lastAutoAddDeviceNumber	The Device Number of the last Auto Added Device. Default=0
enabled	1 when Devices in the Collection can be booted, 0 otherwise. Default=1
autoAddPrefix	The string put before the Device Number for Auto Add. Default=null ASCII computer name characters no end digit Max Length=12
autoAddSuffix	The string put after the Device Number for Auto Add. Default=null ASCII computer name characters no begin digit Max Length=12
autoAddZeroFill	1 when zeros be placed before the Device Number up to the autoAddNumberLength for Auto Add, 0 otherwise. Default=1
autoAddNumberLength	The maximum length of the Device Number for Auto Add. This length plus the autoAddPrefix length plus the autoAddSuffix length must be less than 16. Required that ((lenautoAddPrefix+lenautoAddSuffix)+autoAdd NumberLength)<=15. Min=3, Max=9, Default=4

MCLI Set Device

Set one or more field values for one or more Devices.
/p or -p
Parameters needed to identify the record to be changed.

One of these required	
deviceID	GUID of the Device to Set.
deviceName	Name of the Device to Set.
deviceMac	MAC of the Device to Set.
collectionID	GUID of the Collection to set all Devices. deviceName and deviceMac cannot be set.
siteViewID	GUID of the Site View to set all Devices. deviceName and deviceMac cannot be set.
farmViewID	GUID of the Farm View to set all Devices. deviceName and deviceMac cannot be set.
farmViewName	Name of the Farm View to set all Devices. deviceName and deviceMac cannot be set.
or one of these required &	resolutions
collectionName	Name of the Collection to set all Devices. deviceName and deviceMac cannot be set.
siteViewName	Name of the Site View to set all Devices. deviceName and deviceMac cannot be set.
One of these resolutions when needed	
siteID	GUID of the Site.
siteName	Name of the Site.
/r or -r	Record containing the new values for fields to be changed.
deviceName	Computer name with no spaces. ASCII computer name characters Max Length=15
description	User description. Default="" Max Length=250
deviceMac	Ethernet address as a string in the form XX-XX-XX-XX-XX-XX. Uniquely identifies the Device. Length=17
bootFrom	Device to boot from. Choices are 1 for vDisk, 2 for Hard Disk, and 3 for Floppy. This cannot be Set for a Device with Personal vDisk. Min=1, Max=3, Default=1
className	Used by Automatic Update feature to match new versions of Disks to a Device. This cannot be Set for a Device with Personal vDisk. Default="" Max Length=41
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
enabled	1 when it can be booted, 0 otherwise. This cannot be Set for a Device with Personal vDisk. Default=1
localDiskEnabled	If there is a local disk menu choice for the Device, this is 1. This cannot be Set for a Device with Personal vDisk. Default=0
authentication	Device log in authentication. Choices are 0 for none, 1 for User Name/Password, and 2 for Extern. This cannot be Set for a Device with Personal vDisk. Min=0, Max=2, Default=0
user	Name of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=20

password	Password of user to authenticate before the boot process continues. This cannot be Set for a Device with Personal vDisk. Default="" ASCII Max Length=100
adTimestamp	The time the Active Directory machine account password was generated. Do not set this field, it is only set internally by PVS. Default=0
adSignature	The signature of the Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default=0
adPassword	The Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default="" ASCII Max Length=256
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device belongs to. Do not set this field, it is only set internally by PVS. Default=null Max Length=255
domainObjectSID	The value of the objectSID AD attribute of the same name for the Device's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=186
domainControllerName	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
domainTimeCreated	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null
type	1 when it performs test of Disks, 2 when it performs maintenance on Disks, 3 when it has a Personal vDisk, 4 when it has a Personal vDisk and performs tests, 0 otherwise. A Device with type 0 - 3 can only be Set to 0 - 3, and a Device with type 3 - 4 can only be Set to 3 - 4. Min=0, Max=4, Default=0
localWriteCacheDiskSize	The size in GB to format the Device cache file disk. If the value is 0, then the disk is not formatted. Min=0, Max=2048, Default=0
bdmBoot	Use PXE boot when set to 0, BDM boot when set to 1. Default is PXE Default=0
bdmType	Use PXE boot when set to 0, BDM (Bios) boot when set to 1 and BDM (Uefi) boot when set to 2. Default=0
bdmFormat	1 use VHD for BDMboot, 2 use ISO, 3 use USB. Default=0
bdmUpdated	Timestamp of the last BDM boot disk update. Default=null

bdmCreated	Timestamp when BDM device was created Default=null
xsPvsProxyUuid	UUID of XenServer PVS_proxy Default=null Length=36
enableXsProxy	Enable XenServerProxy when set to 1 Default=null
 MCLI Set Disk	
Set one or more field values for a Disk.	
/p or -p	Parameters needed to identify the record to be changed.
This required	
diskLocatorId	GUID of the Disk Locator.
or this required & resolution	
diskLocatorName	Name of the Disk Locator.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/r or -r	Record containing the new values for fields to be changed.
class	Class of the Disk. Max Length=40
imageType	Type of this image (software type). Max Length=40
writeCacheSize	RAM cache size (MB). Not 0 when used with Cache in Device RAM, and Cache in Device RAM with Overflow on Hard Disk. A value of 0 will disable the RAM use for Cache in Device RAM with Overflow on Hard Disk. Min=0, Max=131072, Default=0
autoUpdateEnabled	Automatically update this image for matching Devices when set to 1. Default 0
activationDateEnabled	Use activation date to activate image when set to 1. Default 0
adPasswordEnabled	Enable AD password management when set to 1.
haEnabled	Enable HA when set to 1.
printerManagementEnabled	Invalid printers will be deleted from the Device when set to 1.
writeCacheType	0 (Private), 1 (Cache on Server), 3 (Cache in Device RAM), 4 (Cache on Device Hard Disk), 7 (Cache on Server, Persistent), 9 (Cache in Device RAM with Overflow on Hard Disk), 10 (Private async), 11 (Server persistent async), 12 (Cache in Device RAM with Overflow on Hard Disk async) Min=0, Max=12, Default=0
licenseMode	0 (None), 1 (Multiple Activation Key), or 2 (Key Management Service). Min=0, Max=2, Default=0
activeDate	Date to activate the disk if autoUpdateEnabled and activationDateEnabled are 1. Format is yyyy/mm/dd. Empty when the

longDescription	autoUpdateEnabled or activationDateEnabled are 0.
operatingSystem	Description of the Disk. Max Length=399
osType	Operating System of Disk. Max Length=250
serialNumber	Operating System Type of Disk. Max Length=40
date	User defined serial number. Max Length=36
author	User defined date. Max Length=40
title	User defined author. Max Length=40
company	User defined title. Max Length=40
internalName	User defined company. Max Length=40
originalFile	User defined name. Max Length=63
hardwareTarget	User defined original file. Max Length=127
majorRelease	User defined hardware target. Max Length=127
minorRelease	User defined major release number. Min=0, Max=4294967295, Default=0
build	User defined minor release number. Min=0, Max=4294967295, Default=0
clearCacheDisabled	User defined build number. Min=0, Max=4294967295, Default=0
format	Clear cached secrets disabled.
	Format of the image. Values are: 0 (VHD), 1 (VHDX). Default=0

MCLI Set DiskLocator

Set one or more field values for a Disk Locator.

or this required & resolution
diskLocatorName Name of the Disk Locator File to Set.

One of these resolutions when needed

One of these resolutions when needed

storeId GUID of the Store that is needed when a diskLocatorName is used.

storeName Name of the Store that is needed when a diskLocatorName is used.

description User description. Default="" Max Length=250
menuText Text that is displayed in the Boot Menu. If this is blank, the value of description will be used.

command this field has no value, the name value is used. Default="" ASCII Max Length=64 CHID of the single Server that this Disk

serverName: Default-null Length-30
Name of the single Server that this Disk
Locator is assigned to. It is not used with

enabled 1 when this disk can be booted, 0 otherwise.

rebalanceEnabled 1 when this Server can automatically rebalance data when this Server can be accessed, 0 otherwise. Default=1

rebalance Devices, 0 otherwise. Default=0

rebalanceTriggerPercent	Percent over fair load that triggers a dynamic Device rebalance. Min=5, Max=5000, Default=25
subnetAffinity	Qualifier for subnet affinity when assigning a Server. 0=None, 1=Best Effort, 2=Fixed. Min=0, Max=2, Default=0

MCLI Set DiskUpdateDevice

Set one or more field values for one or more Disk Update Devices.	
/p or -p	Parameters needed to identify the record to be changed.
One of these required	
deviceId	GUID of the Disk Update Device to Set.
deviceName	Name of Disk Update Device to Set.
deviceMac	MAC of Disk Update Device to Set.
siteId	GUID of the Site. Can be used alone to Set all Disk Update Devices in the Site.
siteName	Name of the Site. Can be used alone to Set all Disk Update Devices in the Site.
diskLocatorId	GUID of the DiskLocator to Set the Disk Update Device for.
or this required & resolution	
diskLocatorName	Name of the DiskLocator to Set the Disk Update Device for.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/r or -r	Record containing the new values for fields to be changed.
description	User description. Default="" Max Length=250
port	UDP port to use with Stream Service. Min=1025, Max=65534, Default=6901
adTimestamp	The time the Active Directory machine account password was generated. Do not set this field, it is only set internally by PVS. Default=0
adSignature	The signature of the Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default=0
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=0
domainName	Fully qualified name of the domain that the Device belongs to. Do not set this field, it is only set internally by PVS. Default=null Max Length=255
domainObjectSID	The value of the objectSID AD attribute of the same name for the Device's computer account. Do not set this field, it is only

domainControllerName	set internally by PVS. Default=null Max Length=186
domainTimeCreated	The name of the DC used to create the host's computer account. Do not set this field, it is only set internally by PVS. Default=null Max Length=4000
adPassword	The time that the computer account was created. Do not set this field, it is only set internally by PVS. Format is: YYYY-MM-DD HH:MM:SS.SSS Default=null
	The Active Directory machine account password. Do not set this field, it is only set internally by PVS. Default="" Max Length=256

MCLI Set DiskVersion

Set one or more field values for one Disk Version.

/p or -p	Parameters needed to identify the record to be changed.
This required	
diskLocatorId	GUID of the Disk Locator Version to Set.
or this required & resolution	
diskLocatorName	Name of the Disk Locator Version to Set.
This required	
version	Version to Set.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
One of these resolutions when needed	
storeId	GUID of the Store that is needed when a diskLocatorName is used.
storeName	Name of the Store that is needed when a diskLocatorName is used.
/r or -r	Record containing the new values for fields to be changed.
description	User description. Default="" Max Length=250
scheduledDate	Date/Time that the Disk Version is scheduled to become available. Format is: YYYY-MM-DD HH:MM. When empty, the disk version is made available immediately. Default=null

MCLI Set Farm

Set one or more field values for a Farm.

/p or -p	Parameters needed to identify the record to be changed.
Optional	
farmId	GUID of the Farm to Set. This is optional since there is only one Farm.
/r or -r	Record containing the new values for fields to be changed.
farmName	Name of the Farm. Default="" Max Length=50
description	User description. Default="" Max Length=250
autoAddEnabled	1 when Auto Add is enabled, 0 otherwise. Default=0

auditingEnabled	1 when Auditing is enabled, 0 otherwise. Default=0
lastAuditArchiveDate	Last date of Audit Trail data that was Archived. Format is yyyy/mm/dd Default=null
defaultSiteId	GUID of the Site to place new Devices into automatically. Not used with defaultSiteName. Default=null Length=36
defaultSiteName	Name of the Site to place new Devices into automatically. Not used with defaultSiteId. Default=null
offlineDatabaseSupportEnabled	1 when Offline Database Support is enabled, 0 otherwise. Default=0
licenseServer	License server name. Default="" Max Length=255
licenseServerPort	License server port. Min=1025, Max=65534, Default=27000
licenseTradeUp	License server trade up, when set to 1. Default=0
licenseSKU	licenseSKU. 0 for on-premises, 1 for cloud. Min=0, Max=1, Default=0
automaticMergeEnabled	1 when Automatic Merge is enabled, 0 otherwise. If the number of versions becomes more than the maxVersions value, a merge will occur at the end of PromoteDiskVersion. Default=1
maxVersions	Maximum number a versions of a Disk that can exist before a merge will automatically occur. Min=3, Max=50, Default=5
mergeMode	Mode to place the version in after a merge has occurred. Values are: 0 (Production), 1 (Test) and 2 (Maintenance). Min=0, Max=2, Default=2

MCLI Set FarmView

Set one or more field values for a Farm View.

/p or -p

Parameters needed to identify the record to be changed.

One of these required

farmViewId

farmViewName

/r or -r

GUID of the Farm View to Set.

Name of the Farm View to Set.

Record containing the new values for fields to be changed.

farmViewName Max Length=50

description Max Length=250

MCLI Set Server

Set one or more field values for a Server. Restart the Stream Service after setting the fields.

/p or -p

Parameters needed to identify the record to be changed.

One of these required

serverId

serverName

/r or -r

GUID of the Server to Set.

Name of the Server to Set.

Record containing the new values for fields to be changed.

serverName	Computer name with no spaces. ASCII computer name characters Max Length=21
description	User description. Default="" Max Length=250
adMaxPasswordAge	Number of days before a password expires. Min=1, Max=30, Default=7
licenseTimeout	Amount of seconds before a license times out. Min=15, Max=300, Default=30
vDiskCreatePacing	VDisk create time pacing in milliseconds. Min=0, Max=5, Default=0
firstPort	Number of the first UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6910
lastPort	Number of the last UDP port for use by the Stream Service, First and Last must allow at least 5 ports. Min=1025, Max=65534, Default=6930
threadsPerPort	Number of worker threads per IO port. Required that (threadPerPort * numberPorts * numberIPs) <= 1000. Min=1, Max=60, Default=8
buffersPerThread	Number of buffers per worker thread. Min=1, Max=128, Default=24
serverCacheTimeout	Number of seconds to wait before considering another Server is down. Min=5, Max=60, Default=8
ioBurstSize	Number of bytes read/writes can send in a burst of packets. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=4096, Max=61440, Default=32768
maxTransmissionUnits	Ethernet maximum transmission unit size for the protocol for use for Server and Device. Required that ioBurstSize/ (maxTransmissionUnits-76)<=32. Min=502, Max=16426, Default=1506
maxBootDevicesAllowed	Maximum number of Devices allowed to boot simultaneously. Min=1, Max=1000, Default=500
maxBootSeconds	Maximum number of seconds for a Device to boot. Min=10, Max=900, Default=60
bootPauseSeconds	Number of seconds that a Device will pause during login if its server busy. Min=1, Max=60, Default=10
adMaxPasswordAgeEnabled	Age the password, when set to 1. Default=0
eventLoggingEnabled	Enable event logging, when set to 1. Default=0
nonBlockingIoEnabled	Use non-Blocking IO, when set to 1. Default=1
ip	One or more streaming ip addresses. If more than one ip is included, the ip addresses are comma delimited.
initialQueryConnectionPoolSize	Initial size of database connection pool for non-transactional queries. Min=1, Max=1000, Default=50
initialTransactionConnectionPoolSize	Initial size of database connection pool for transactional queries. Min=1, Max=1000, Default=50

maxQueryConnectionPoolSize	Maximum size of database connection pool for non-transactional queries. Min=1, Max=32767, Default=1000
maxTransactionConnectionPoolSize	Maximum size of database connection pool for transactional queries. Min=1, Max=32767, Default=1000
refreshInterval	Interval, in number of seconds, the server should wait before refreshing settings. If set to 0, unused database connections are never released. Min=0, Max=32767, Default=300
unusedDbConnectionTimeout	Interval, in number of seconds, a connection should go unused before it is to be released. Min=0, Max=32767, Default=300
busyDbConnectionRetryCount	Number of times a failed database connection will be retried. Min=0, Max=32767, Default=2
busyDbConnectionRetryInterval	Interval, in number of milliseconds, the server should wait before retrying to connect to a database. Min=0, Max=10000, Default=25
localConcurrentIoLimit	Maximum concurrent IO transactions it performs for vDisks that are local. A value of 0 disables the feature. Min=0, Max=128, Default=4
remoteConcurrentIoLimit	Maximum concurrent IO transactions it performs for vDisks that are remote. A value of 0 disables the feature. Min=0, Max=128, Default=4
logLevel	Level to perform logging at. Values are: 0 (None), 1 (Fatal), 2 (Error), 3 (Warning), 4 (Info), 5 (Debug), and 6 (Trace). Min=0, Max=6, Default=4
logFileSizeMax	Maximum size log files can reach in Megabytes. Min=1, Max=50, Default=5
logFileBackupCopiesMax	Maximum number of log file backups. Min=1, Max=50, Default=4
powerRating	A strictly relative rating of this Server's capabilities when compared to other Servers in the Store(s) it belongs to; can be used to help tune load balancing. Min=0.1, Max=1000, Default=1
lastCeipUploadAttempt	Time that this server last attempted a CEIP upload. Default=null
lastBugReportAttempt	Time that this server last attempted to upload or generate a bug report bundle. Default=null
lastBugReportStatus	Status of the last bug report on this server. Default=null Max Length=250
lastBugReportResult	Status of the last bug report on this server. Default=null Max Length=4000
lastBugReportSummary	Summary of the last bug report on this server. Default=null Max Length=250

MCLI Set ServerBiosBootstrap

Oem Only: Set the bootstrap fields for the Server dell_bios.bin BIOS bootstrap file.	
/p or -p	Parameters needed to identify the record to be changed.
One of these required	
serverId	GUID of the Server to Set the dell_bios.bin BIOS bootstrap file.
serverName	Name of the Server to Set the dell_bios.bin BIOS bootstrap file.
/r or -r	Record containing the new values for fields to be changed.
enabled	Automatically update the BIOS on the target device with these setting when set to 1, otherwise do not use these settings. Default=0
dhcpEnabled	Use DHCP to retrieve target device IP when set to 1, otherwise use the static domain, dnsIpAddress1 and dnsIpAddress2 settings. Default=1
lookup	Use DNS to find the Server when set to 1 with the serverName host value, otherwise use the bootserver1_Ip, bootserver1_Port, bootserver2_Ip, bootserver2_Port, bootserver3_Ip, bootserver3_Port, bootserver4_Ip, and bootserver4_Port settings. Default=1
verboseMode	Display verbose diagnostic information when set to 1. Default=0
interruptSafeMode	Interrupt safe mode (use if target device hangs during boot) when set to 1. Default=0
paeMode	PAE mode (use if PAE enabled in boot.ini of target device) when set to 1. Default=0
bootFromHdOnFail	For network recovery reboot to hard drive when set to 1, restore network connection when set to 0. Default=0
recoveryTime	When bootFromHdOnFail is 1, this is the number of seconds to wait before reboot to hard drive. Min=10, Max=60000, Default=50
pollingTimeout	Login polling timeout in milliseconds. Min=1000, Max=60000, Default=5000
generalTimeout	Login general timeout in milliseconds. Min=1000, Max=60000, Default=5000
serverName	Host to use for DNS lookup. Only used when lookup is 1. Default=IMAGESERVER1
bootserver1_Ip	1st boot server IP. Only used when lookup is 0.
bootserver1_Port	1st boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
bootserver2_Ip	2nd boot server IP. Only used when lookup is 0. Default=0.0.0.0
bootserver2_Port	2nd boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
bootserver3_Ip	3rd boot server IP. Only used when lookup is 0. Default=0.0.0.0

bootserver3_Port	3rd boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
bootserver4_Ip	4th boot server IP. Only used when lookup is 0. Default=0.0.0.0
bootserver4_Port	4th boot server port. Only used when lookup is 0. Min=1025, Max=65536, Default=6910
domain	Domain of the primary and secondary DNS servers. Only used when dhcpEnabled is 0.
dnsIpAddress1	Primary DNS server IP. Only used when dhcpEnabled is 0.
dnsIpAddress2	Secondary DNS server IP. Only used when dhcpEnabled is 0.

MCLI Set ServerBootstrap

Set the bootstrap fields for the Server and named bootstrap file specified.	
/p or -p	Parameters needed to identify the record to be changed.
One of these required	
serverId	GUID of the Server to Set the named bootstrap file on.
serverName	Name of the Server to Set the named bootstrap file on.
This required	
name	Name of the bootstrap file.
/r or -r	Record containing the new values for fields to be changed.
bootserver1_Ip	1st boot server IP.
bootserver1_Netmask	1st boot server netmask. Default=0.0.0.0
bootserver1_Gateway	1st boot server gateway. Default=0.0.0.0
bootserver1_Port	1st boot server port. Min=1025, Max=65536, Default=6910
bootserver2_Ip	2nd boot server IP. Default=0.0.0.0
bootserver2_Netmask	2nd boot server netmask. Default=0.0.0.0
bootserver2_Gateway	2nd boot server gateway. Default=0.0.0.0
bootserver2_Port	2nd boot server port. Min=1025, Max=65536, Default=6910
bootserver3_Ip	3rd boot server IP. Default=0.0.0.0
bootserver3_Netmask	3rd boot server netmask. Default=0.0.0.0
bootserver3_Gateway	3rd boot server gateway. Default=0.0.0.0
bootserver3_Port	3rd boot server port. Min=1025, Max=65536, Default=6910
bootserver4_Ip	4th boot server IP. Default=0.0.0.0
bootserver4_Netmask	4th boot server netmask. Default=0.0.0.0
bootserver4_Gateway	4th boot server gateway. Default=0.0.0.0
bootserver4_Port	4th boot server port. Min=1025, Max=65536, Default=6910
verboseMode	Display verbose diagnostic information when set to 1. Default=0
interruptSafeMode	Interrupt safe mode (use if target device hangs during boot) when set to 1. Default=0
paeMode	PAE mode (use if PAE enabled in boot.ini of target device) when set to 1. Default=0
bootFromHdOnFail	For network recovery reboot to hard drive when set to 1, restore network connection when set to 0. Default=0

recoveryTime	When bootFromHdOnFail is 1, this is the number of seconds to wait before reboot to hard drive. Min=10, Max=60000, Default=50
pollingTimeout	Login polling timeout in milliseconds. Min=1000, Max=60000, Default=5000
generalTimeout	Login general timeout in milliseconds. Min=1000, Max=60000, Default=5000

MCLI Set ServerStore

Set the directory path and cache paths of a Server for a Store.

/p or -p

Parameters needed to identify the record to be changed.

One of these required
serverId

GUID of a Server that uses the path to get to the Store.

serverName

Name of a Server that uses the path to get to the Store.

One of these required
storeId

GUID of the Store.

storeName

Name of the Store.

/r or -r

Record containing the new values for fields to be changed.

path

Directory path that the Server uses to access the Store. Default="" Max Length=255
Cache path(s) that the Server uses with the Store. It is an ordered comma-delimited list. If none are specified the caches will be placed in the Store cachePath.

Default=None

cachePath

MCLI Set Site

Set one or more field values for a Site.

/p or -p

Parameters needed to identify the record to be changed.

One of these required
siteId

GUID of the Site to Set.

siteName

Name of the Site to Set.

/r or -r

Record containing the new values for fields to be changed.

siteName

Name of the Site. Max Length=50

description

User description. Default="" Max Length=250

defaultCollectionId

GUID of the Collection to place new Devices into automatically. Not used with defaultCollectionName. Default=null Length=36

defaultCollectionName

Name of the Collection to place new Devices into automatically. Not used with defaultCollectionId. Default=null

inventoryFilePollingInterval The number of seconds between polls for Disk changes in the Stores. Min=1, Max=600, Default=60

enableDiskUpdate

1 when Disk Updated is enabled for the Site, 0 otherwise. Default=0

diskUpdateServerId	GUID of the Disk Update Server for the Site. Not used with diskUpdateServerName. Default=null Length=36
diskUpdateServerName	Name of the Disk Update Server for the Site. Not used with diskUpdateServerId. Default=null
makUser	User name used for MAK activation. Default=null Max Length=64
makPassword	User password used for MAK activation. Default=null Max Length=64
enableXsProxy	Enable XenServerProxy when set to 1 Default=null
virtualHostingPoolId	GUID of the VirtualHostingPool object.
virtualHostingPoolName	Name of the VirtualHostingPool object.
xsPvsSiteUuid	GUID of the XenServer PVS Site.

MCLI Set SiteView

Set one or more field values for a Site View.

/p or -p	Parameters needed to identify the record to be changed.
This required	
siteViewId	GUID of the Site View to Set.
or this required & resolution	
siteViewName	Name of the Site View to Set.
One of these resolutions when needed	
siteId	GUID of the Site.
siteName	Name of the Site.
/r or -r	Record containing the new values for fields to be changed.
siteViewName	Name of the Site View. Max Length=50
description	User description. Default="" Max Length=250

MCLI Set Store

Set one or more field values for a Store.

/p or -p	Parameters needed to identify the record to be changed.
One of these required	
storeId	GUID of the Store to Set.
storeName	Name of the Store to Set.
/r or -r	Record containing the new values for fields to be changed.
storeName	Name of the Store. Max Length=50
siteId	GUID of the Site where Administrators of that Site can change this Store. Not used for Farm Stores. siteName can be used instead. Default=null Length=36
siteName	Name of the Site where Administrators of that Site can change this Store. Not used for Farm Stores. siteId can be used instead. Default=null
description	User description. Default="" Max Length=250
path	Default directory path that the Servers use to access this Store. Max Length=255
cachePath	Default Cache path(s) that the Servers use with this Store. It is an ordered comma-

domain	Domain to add the Disk Update Device(s) to. If not included, the first Domain Controller found on the Server is used. Default=null Max Length=255
organizationUnit	Organizational Unit to add the Disk Update Device(s) to. This parameter is optional. If it is not specified, the device is added to the built in Computers container. Child OU's should be delimited with forward slashes, e.g. "ParentOU/ChildOU". Special characters in an OU name, such as "'", '#', '+', ',', ';', '>', '=', must be escaped with a backslash. For example, an OU called "commaIn,TheMiddle" must be specified as "commaIn\,TheMiddle". The old syntax of delimiting child OU's with a comma is still supported, but deprecated. Note that in this case, the child OU comes first, e.g. "ChildOU,ParentOU". Default=null Max Length=255
postUpdateApprove	Access to place the version in after the update has occurred. 0 = Production, 1 = Test, 2 = Maintenance. Min=0, Max=2, Default=0

MCLI Set VirtualHostingPool

Set one or more field values for a Virtual Hosting Pool.

This required

`virtualHostingPoolId` GUID of the Virtual Hosting Pool to Set.

or this required & resolution

virtualHostingPoolName Name of the Virtual Hosting Pool to Set.

One of these resolutions when needed

GUID of the Site.

Name of the Site.

SECOND

Record containing the new values for fields to be changed

virtualHostingPoolName

Name of the Virtual Hosting Pool. It is unique within the Site. Max Length=50

type

Type of the Virtual Hosting Pool. 0 = Citrix XenServer, 1 = Microsoft SCVMM/Hyper-V, 2 = VMWare vSphere/ESX. Min=0, Max=3, Default=0

description

User description. Default="" Max Length=250
Name or IP of the Host Server. Max

Length=255
Port of the Host Server. Min=80, Max=65534,

Default=80
Datacenter of the Virtual Hosting Pool.

Default="" Max Length=250
Number of updates at the same time. Min=2,

Max=1000, Default=1000
Timeout for updates. Min=2, Max=240,

Default=60
Timeout for shutdown. Min=2, Max=30,

userName	Name to use when logging into the Server.
password	Password to use when logging into the Server.
xdHostingUnitUuid	UUID of XenDesktop Hosting Unit Default=null Length=36
prepopulateEnabled	Enable prepopulate when set to 1 Default=0
xsPvsSiteUuid	UUID of XenServer PVS_site Default=null Length=36
platformVersion	Hypervisor Host Version Default=null Max Length=250
xdHcHypervisorConnectionName	Hypervisor Connection Name for HCL Connection Details object Default=null Max Length=250
xdHcHypervisorConnectionUid	Hypervisor Connection Uid for HCL Connection Details object Default=null Max Length=250
xdHcRevision	Revision for HCL Connection Details object Default=null Max Length=250
xdHcCustomProperties	Custom Properties for HCL Connection Details object Default=null Max Length=250
xdHcSslThumbprints	Ssl Thumbprints for HCL Connection Details object Default=null Max Length=250
disableHostXsProxy	True to disable PVS-Accelerator Default=null

MCLI Set XDSite

Set the configServices field value for a XenDesktop Site.	
/p or -p	Parameters needed to identify the record to be changed.
This required	
xdSiteId	GUID of the XenDesktop Site to Set.
/r or -r	Record containing the new values for fields to be changed.
configServices	Comma delimited list of XenDesktop Server addresses. Max Length=2000

MCLI SetList

```
MCLI SetList commandName[ /p name=value[ name2=value2]][ /r
record1field=value[ record1field2=value2][ /r record2field=value[
record2field2=value2]]]
```

MCLI SetList DeviceBootstraps

Set the Bootstrap Files for a Device.	
/p or -p	Parameters needed to identify the record to be changed.
One of these required	
deviceId	GUID of the Device.
deviceName	Name of the Device.
deviceMac	MAC of the Device.
/r or -r	Records with fields to set.
bootstrap	Name of the bootstrap file. Max Length=259
menuText	Text that is displayed in the Boot Menu. If this field has no value, the bootstrap value is used. Default="" ASCII Max Length=64

MCLI SetList DeviceCustomProperty

MCLI SetList DeviceDiskPrinters

MCLI SetList DevicePersonality

MCLI SetList DiskLocatorCustomProperty

MCLI SetList ServerCustomProperty